


Flexible Power Combinations High-Speed and Versatile Load Simulations



PEL-3000 Series Programmable D.C. Electronic Load

The PEL-3000 Series, a signal-channel programmable D.C. electronic load with power rating from 175W to 1050W. The PEL-3000 Series is an ideal electronic load to meet the test requirement of Server Power, Switching Power Supply (SPS), battery modules for HEV and automobile devices. The adjustable high speed slew rate of 16A/ μ s simulates rise and fall speed of different load current so as to test the adequacy of the response time of power supply. The Sequence function is divided into Fast Sequence and Normal Sequence according to the test time of each step. Both Dynamic and Sequence are to assist users to simulate the genuine load change. Based upon the functionalities described above, the PEL-3000 Series can test a vast variety of power supply ranging from the fundamental static sink current to complex dynamic load simulations so as to enhance product quality and reliability.

- Operating Voltage (DC) : 1.5V~150V
- Operating Mode : C.C./C.V./C.R./C.P./C.C+ C.V./C.R+ C.V./C.P+ C.V
- Parallel Connection of Inputs for Higher Capacity (Max : 9,450W)
- Support of High Slew Rate : Max 16A/ μ s
- Run Program Function (Go/NoGo Test)
- Sequence Function for High Efficient Load Simulations
- Commands are Compatible With Kikusui PLZ-4W Model (*)
- Dynamic (Switching) Function : 0.0166Hz~20KHz
- Soft Start Function : Off/On (1~200ms, Res : 1ms)
- Adjustable OCP/OVP/OPP/UVF Setting
- Short Circuit Function
- Timer Function : Elapsed Time of Load on
- Cut Off Time (Auto Load Off Timer) : 1s to 999h 59min 59s or Off
- External Channel Control/Monitoring Via Analog Control Connector
- Setup Memories : 100 sets & 3.5 Inch TFT LCD Display
- Multi Interface : USB 2.0 Device/Host, RS-232, GPIB (Optional)



Normal Sequence Diagram

By applying a complete sequence editing function, users can control electronic load without using a computer or writing a program so as to save cost and time of R&D.

For more details, please contact your nearest distributor or you may directly write to india_marketing@goodwill.com.tw

Bangalore & Pune : Integrated Services & Consultancy, +91-9845070872, sales@isc4esaindia.com

Chennai : Vamara Techware, +91 9894388839, sales@vamara.in

Hyderabad : GSAS Micro Systems, +91-9704414410, satya@gsasindia.com

Kolkata : Arihant Trading Company, +91-9830033381, gautamg1966@gmail.com

Mumbai : Automate Process Control, +91-9223508308, automate.mumbai@gmail.com

Delhi : Avante Global Services Pvt Ltd, 011-26473068, pkg@avante.in ;

SRB Instruments Pvt. Ltd, 9810190551, info@srbinstruments.com

Thiruvananthapuram : Innovative Instruments Inc, 0471-2316385, instrument_inc@vsnl.net

GW INSTEK
Simply Reliable

GOOD WILL INSTRUMENT CO., LTD.

www.gwinstek.com