



AP SIN 3000

Fast-Switching Low-Noise Signal Generator



SSB Phase Noise



Level Accuracy

9 kHz to 3300 MHz Signal Generator

The APSIN3000 is a compact, high-performance analog signal generator with frequency coverage from 9 kHz to 3300 MHz, mHz resolution and a precisely leveled, broad output power range. It provides excellent signal quality with low phase noise, good harmonic suppression and low spurious. It supports AM/FM/PM and pulse modulation and has an internal low-drift OCXO reference.

A truly portable version of the APSIN3000 is available with an optional internal battery and weighs less than 3 kgs.

Key Features

- Very low phase noise
- Externally lockable high-stability reference (OCXO)
- Easy remote control from PC (GUI)
- VXI-11/SCPI-99 fully supported

Applications

- High-Performance Lab Generator
- Automated test systems (ATE)
- Field measurements



For further information, please contact us:

91-11-3081 0200

91-11-2695 0011

marcom@aimil.com

www.aimil.com



Corporate Office:

"Naimex House",
A-8, Mohan Co-operative Industrial Estate,
Mathura Road, New Delhi-110044

Also Offices at :

- Mumbai • Bangalore • Kolkata • Chennai
- Vadodara • Hyderabad • Chandigarh
- Guwahati • Indore • Kochi • Lucknow
- Bhubaneswar