

Hipot

Insulation Resistance

Hipot

PE Continuity

Hipot

Hipot

PE Continuity

DUT Resistance Measurement

All 4 Safety !

DUT Resistance Measurement

Hipot

Insulation Resistance

DUT Resistance Measurement

DUT Resistance Measurement

PE Continuity

PE Continuity

Insulation Resistance

DUT Resistance Measurement

Insulation Resistance

FST 200 4S Analyzer



Technical Specification

Input: 230VAC or optionally 115VAC, 50Hz / 60Hz; 360VA
Interfaces: IEEE488, Ethernet, RS-232, USB

PE-Continuity Test

Output: Max. 12VAC, 50Hz
Maximum test current: 2 ranges, 10A and 25A,
setting accuracy -0+20%
Measuring ranges
Standard: 0-500mΩ
Optional: 0-100mΩ

Insulation Resistance Test

Output: 100-500VDC, freely programmable
Maximum test current: 3, 0mA, current limited,
short circuit proof
Measuring ranges: Autorange, 0, 5-10MΩ; 5-100MΩ;
50-1000MΩ; 0, 5-10GΩ

High Voltage Test

Output: Range: 0-5000VAC
Optional: DC output
Maximum test current: 10mA
Maximum test apparent power: 50VA

Resistance Measurement

Output: Max. 50VAC
Measuring ranges: Autorange, 0-2Ω; 0-10Ω; 0-100Ω; 0-500Ω
Maximum test current: 200mA

- Robust for production environment
- Accurate
- Calibration - Easy, Fast and Cost Efficient with Replaceable Calibration Module
- Simple and Reliable Construction
- User Friendly



FST 210 3S Analyzer



FST 110 High Voltage Tester



FST 130 PE-Continuity Tester

sales@synergytech.in

marketing@synergytech.in



Call Us

Hyderabad 040 2799 0486 / 040 2779 2521
Bangalore 080 3200 1683 / 080 2349 0111
Chennai 044 3255 8851 / 044 2654 0919
Kolkata 033 2417 4322 / 033 2422 4842
Pune 020 2546 8459 / 020 2546 8468
Delhi 011 2623 2520 / 011 4248 1121

Synergy Measurement Technologies Pvt Ltd

www.synergytech.in

FINERO The Quality Control Company

Regd. Office: Synergy Measurement Technologies Pvt Ltd, Plot No. 100/2, Road No. 1, S.P. Colony, Trimulgherry, Secunderabad - 500 015