



POWER GUARD



SINCE 1962

New



PG09



Features

The Power Guard has a smart socket consisting of an energy metering ASIC and a large LCD. It displays various electrical parameters such as V, A, kW, PF, kWh and EUT etc. It is useful in monitoring energy quality and consumption.

- Displays TRMS V, TRMS A, kW, PF, kWh etc.
- Display Energy Usage Time (EUT)
- Red LED flashes when the Energy is being used
- Large LCD Display with Backlight

Applications

- Appliance Testing
- Energy Audit
- QC
- Studying Energy Efficiency of Electrical Equipment
- Building Management Systems
- Power Management
- Generator / Motor Characteristics
- Plant Maintenance

Specifications

Functions	Input Range	Display Format	Accuracy Class
RMS Voltage	195 ~ 265 Vrms	XXX.XX V	0.5
RMS Current	0.02 ~ 10 Arms	XXXX mA	1
Active Power	0.2 ~ 1 W 1 ~ 5 W 5 ~ 2200 W	XXXX.XX W	< 10 5 1
Power Factor	For : 0.2 ~ 5 W For : 5 ~ 10 W For : 10 ~ 2200 W	X.XXX COSΦ	> 0.03 PF < 0.03 PF < 0.01 PF
Active Energy	For : 5 ~ 2200 W	XXXX.XX kWh	1
Energy Usage Time (EUT)	Days/Hours/Minutes Years/Months	XX.XX.XX XX.XX	- -
Applications	Teaching, Demonstration & Testing of Electrical Energy Saving of Household & Office Appliances. It can be used in Houses, Offices, Shops, Schools, Laboratories etc.		

MECO INSTRUMENTS PRIVATE LTD.

Plot No. EL-1, MIDC Electronic Zone, TTC Indl. Area, Mahape, Navi Mumbai 400 710. (INDIA)

Tel : 0091-22-27673311-16 (Sales), 27673300 (Board) ● Fax : 0091-22-27673310, 27673330

Email : sales@mecoinst.com ● Web : www.mecoinst.com