



Hall Effect Sensors

We trust only the best for our customers. So for reliable and precise performance, we provide Hall Effect Sensors from the specialist, Winson Semiconductor Corp.

Based out at Hsin-Chu, Taiwan, Winson is a professional IC design house providing competitive, reliable products in semiconductor vertical integrated market since last 12 years. Specialised in Hall Effect ICs, Winson provides **best cost / performance solutions** on various applications.



Product Range

- Unipolar/Bipolar Hall Effect Switch IC
- Linear Hall Effect IC
- Two-phase Half Wave Hall Effect IC
- One-Phase Full Wave Hall Effect IC
- Current Sensors

Applications

- Brushless Motor
- Cover Detector
- Magnetic Switch
- Current Sensing
- Positioning and Contact-Less Switches and many more...



Authorised distributor

Emaar Impex Pvt. Ltd

16A, Hanuman Terrace, Tara Temple Lane, Lamington Road,
Mumbai - 400 007 India Tel : +91-22-23801086 Fax : +91-22-66459190
Email : sales@emaarindia.in Web: www.emaarindia.com

Winson Semiconductor Corp. (Taiwan)

2F, No.193, Gaotie 8th Road, Zhubei,
Hsin Chu, Taiwan

Tel: 886-3-667 3166 Fax: 886-3-667 3167




MERCURY ELECTRONICS

Authorised Distributor for MEC in India

Website : www.mercury-crystal.com

Package	Type	Package Dimension L x W x H (mm)	Frequency Range MHz
CRYSTAL UNITS			
X32	SMD	3.2 x 2.5 x 0.7	12.0 - 50
X42	SMD	4.2 x 2.5 x 0.6	12.0 - 50
MJ	SMD	5 x 3.2 x 1.09	6 - 125
MF	SMD	6.0 x 3.5 x 1.0	10 - 100
MQ	SMD	7.0 x 5.0 x 1.26	0 - 125
M49	SMD	11.4 x 4.7 x 4.2	3.2 - 70.0
M49L	SMD	11.4 x 4.7 x 3.2	3.2 - 70.0
MP5	SMD	12.0 x 4.5 x 5.2	3.5 - 70.0
MP4	SMD	12.0 x 4.5 x 4.2	3.5 - 70.0
UM1	DIP	7.8 x 3.2 x 8.0	1.0 - 160
UM5	DIP	7.8 x 3.2 x 6.0	10.0 - 160
HUS	DIP	10.7 x 4.3 x 3.5	3.2 - 70
HUSL	DIP	10.7 x 4.3 x 2.5	3.2 - 70
H49	DIP	11.5 x 4.3 x 13.6	1.0 - 160



CLOCK OSCILLATORS

Square Wave / TTL/CMOS Output

H14	DIP	12.8 x 20.2	0.125 - 160
H8	DIP	12.8 x 5.88	0.125 - 160
SWO	SMD	7.0 x 5.0 x 1.4	0.4 - 125.0
H57	SMD	7.0 x 5.0 x 1.4	32.768
H53	SMD	5.0 x 3.2 x 1.2	1.0 - 125.0

Also available: Square Wave / Spread Spectrum (low EMI), Square Wave / LVPECL & LVDS output, Square Wave / LPO (Low Power), Sine Wave / 50 Ohms, Sine Wave / 10K Ohms // 15 pF

- Engineered in USA
- 1Hz to 622.080MHz Oscillators
- 0.001 to 100ppm Oscillator Stability
- TTL, CMOS, ECL, PECL, LVDS outputs
- Spread Spectrum LOW EMI Oscillators
- Blue Tooth Crystals

VCXO, TCXO, OCXO, VCTCXO & Crystal Filters also available



Authorised Distributor

EMAAR IMPEX Pvt.Ltd

16A, Hanuman Terrace, Tara Temple Lane,
Lamington Road, Mumbai - 400 007 India
Tel : +91-22-23801086 Fax : +91-22-66459190
Email : sales@emaarindia.in Web: www.emaarindia.com

MERCURY ELECTRONIC INDUSTRIAL CO., LTD. (Taiwan)

Address: 31 Tin-Ping Rd., Shui-Fong Industrial Park,
Shui-Fong Taipei Sien Taiwan
Tel: (886)-2-2406-2779 Fax: (886)-2-2496-0769
sales-tw@mecrystal.com