

corresponding information.

Void distance(). Demonstrates the process of distance determination.

Void direction(). Demonstrates the process of direction determination.

Void closing. Provides an exit screen before exiting.

Setbkcolor(number). Sets the background colour of choice from 16 colour options (0 through 15). Instead of specifying the number, the respective colour name can also be used in block

letters.

Setcolor(number). Selects a foreground or drawing colour from 16 colours.

Settextstyle(font,direction,character size). Sets the values for the text characteristics to be used for displaying texts.

Outtextxy(x,y,"Literal expression"). Displays the string in graphics mode. (x,y) denotes the starting coordinates of the string on the screen.

Setfillstyle(pattern,color). Used to fill the colour. It enables an additional feature of filling the colours with specific pattern of colouring as well.

Floodfill(). Used for filling the required colour in geometrical figures. Geometrical figures can be drawn using the inbuilt functions of the shapes (rectangle, circle, etc).

EFY note. The source code of this article is available on www.efymag.com website.

RADAR.C

```

/* ***** RADAR.C for RADAR DEMO IN C ***** */

#include<stdio.h>
#include<conio.h>
#include<graphics.h>
#include<dos.h>
// FUNCTIONS USED
void principle();
void distance();
void direction();
void closing();
void main()
{
    int gd=DETECT,gm,x,y;
    initgraph(&gd,&gm,"c:\\turbo3\\bgi"); //initializing Graphics Mode
    principle();
    distance();
    direction();
    closing();
    getch();
    closegraph();
    restorecrtmode();
}
void principle()
{
    setbkcolor(BLUE);
    setcolor(WHITE);
    delay(2000);
    rectangle(80,300,180,360);
    setfillstyle(1,YELLOW); // TRANSMITTER
    floodfill(85,305,WHITE);
    setcolor(RED); // ARROW TO DUPLER
    settextstyle(11,0,2);
    outtextxy(87,325,"TRANSMITTER");
    delay(1000);
    setcolor(WHITE);
    moveto(180,330);
    lineto(230,330);
    lineto(225,335);
    moveto(230,330);
    lineto(225,325);
    setfillstyle(1,CYAN);
    rectangle(230,300,310,360); // DUPLER
    moveto(270,300);
    lineto(270,360);
    floodfill(235,305,WHITE); // PART 1
    setcolor(RED);
    outtextxy(238,325,"DUPLER");
    delay(1000);
    setcolor(WHITE);
    moveto(250,300); // ARROW FROM DUPLER
    lineto(250,250);
    lineto(255,255);
    moveto(250,250);
    lineto(245,255);
    delay(1000);
    setcolor(RED);
    settextstyle(11,0,2);
    outtextxy(246,85,"ANTENNA");
    setcolor(WHITE);
    rectangle(250,230,290,240); // ANTENNA
    rectangle(245,240,295,250);
    setfillstyle(9,BROWN);
    floodfill(257,232,WHITE);
    floodfill(247,243,WHITE);
    setfillstyle(1,LIGHTGRAY);
    ellipse(290,130,90,89,5,30);
    floodfill(290,130,WHITE);
    setfillstyle(9,BROWN);
    arc(300,130,105,255,31);
    floodfill(275,130,WHITE);
    setfillstyle(7,BROWN);
    moveto(260,230);
    lineto(270,140);
    moveto(280,230);
    lineto(270,140);
    floodfill(275,225,WHITE);
    rectangle(255,115,268,145);
    rectangle(250,120,255,140);
    setfillstyle(1,DARKGRAY);
    floodfill(258,117,WHITE);
    floodfill(253,123,WHITE);
    delay(1000);
    setcolor(WHITE);
    moveto(290,125);
    lineto(330,47); // ARROW TO TARGET
    moveto(530,47);
    lineto(525,52);
    lineto(524,44);
    setcolor(RED);
    settextstyle(11,0,2);
    outtextxy(515,25,"TARGET");
    setcolor(WHITE);
    setfillstyle(1,LIGHTGREEN); // TARGET
    circle(540,50,10);
    floodfill(540,50,WHITE);
    delay(500);
    setfillstyle(1,RED);
    floodfill(540,50,WHITE);
    delay(500);
    setfillstyle(1,LIGHTGREEN);
    floodfill(540,50,WHITE);
    delay(500);
    delay(1000);
    moveto(534,57); // ARROW TO ANTENNA
    lineto(296,137);
    moveto(296,137);
    lineto(300,141);
    moveto(296,137);
    lineto(299,131);
    delay(1000);
    moveto(290,250); // ARROW TO DUPLER
    lineto(290,300);
    lineto(285,295);
    moveto(290,300);
    lineto(295,295);
    setfillstyle(1,CYAN);
    floodfill(275,305,WHITE); // PART 2
    setcolor(RED);
    settextstyle(11,0,2);
    outtextxy(238,325,"DUPLER");
    delay(1000);
    setcolor(WHITE);
    moveto(310,330); // ARROW TO RECEIVER
    lineto(360,330);
    lineto(355,325);
    moveto(360,330);
    lineto(355,335);
    setfillstyle(1,YELLOW);
    rectangle(360,300,440,360); // RECEIVER
    floodfill(365,305,WHITE);
    setcolor(RED);
    settextstyle(11,0,2);
    outtextxy(368,325,"RECEIVER");
    delay(1000);
    setcolor(WHITE);
    moveto(440,330); // ARROW TO DISPLAY
    lineto(490,330);
    lineto(485,325);
    moveto(490,330);
    lineto(485,335);
    setfillstyle(1,CYAN);
    circle(540,330,50); // DISPLAY
    floodfill(540,330,WHITE);
    setcolor(RED);
    settextstyle(11,0,2);
    outtextxy(515,327,"DISPLAY");
    delay(3000);
    cleardevice();
}
void distance()
{
    setbkcolor(RED);
    setcolor(BLUE);
    ellipse(200,200,90,89,10,40); // ANTENNA
    arc(210,200,105,255,42);
    rectangle(130,360,180,385);
    moveto(140,360);
    lineto(155,220);
    moveto(170,360);
    lineto(155,220);
    rectangle(145,180,167,220);
    rectangle(135,190,145,210);
    setcolor(WHITE);
    settextstyle(11,0,2);
    outtextxy(127,400,"ANTENNA");
    setcolor(BLUE);
    setfillstyle(1,YELLOW);
    floodfill(200,200,BLUE);
    setfillstyle(9,BROWN);
    floodfill(135,365,BLUE);
    setfillstyle(7,BROWN);
    floodfill(155,340,BLUE);
    setfillstyle(9,LIGHTGREEN);
    floodfill(147,182,BLUE);
    floodfill(140,195,BLUE);
}

```