

Manage Inputs and Outputs

Create an Input or Output

Use one of the following options:

- ▶ Drag-and-drop an item from the [Toolbox](#) to the Function diagram or into the Entity Explorer
- ▶ Right-click on a Function in the diagram or Entity Explorer pane to invoke the right-click menu and choose **Add Input** or **Add Output** (the default Input/Output data type is char)
- ▶ Right-click on a Function in the diagram or Entity Explorer pane to invoke the right-click menu and choose **Add Pair** (this option is available for the Function type [Input to Output](#))
- ▶ Use the `Ctrl+Shift+I` (for Inputs), `Ctrl+Shift+O` (for Outputs), or `Ctrl+Shift+R` (for an Input and Output pair) [Keyboard Shortcuts](#)
- ▶ Select Functions in the [Main Menu](#) and then the Input/Output type of your choice

The names of the Inputs and Outputs within a single Function must be unique.

Select an Input or Output

Use one of the following options in the Entity Explorer or in the Function Flow Editor:

- ▶ To select a single item, click or use the cursor keys
- ▶ To select multiple items, click and hold the Ctrl key
- ▶ To select a range of items, click and hold the Shift key

Rename an Input or Output

1. Use one of the following options:

- ▶ Click the Name portion of the item in the Function Navigation workspace
- ▶ Select the **Name** field on the General tab in the Properties tool pane
- ▶ Choose **Rename** from the [Right-Click Menu](#)
- ▶ Use the `F2` [Keyboard Shortcut](#)
- ▶ Choose **Edit ▶ Rename** from the [Main Menu](#)

2. Enter the new name.

The name of the Inputs and Outputs within a single Function must be unique (Input/Output names are case-sensitive).

When an Input is mapped to an Output, renaming the Input for the first time applies the same name to the Output.

Change the Properties of Multiple Inputs or Outputs

1. [Select](#) one or more Inputs or Outputs to be changed.
2. The system will display a set of common features of selected items in the properties pane.

When only items with related User Controls are selected, the user can change the prompt, font, size, color, and other visual options of the items.

For more information about Input and Output Properties, see [Function Input and Output Properties](#), [Input Properties](#), and [Output Properties](#).

Copy an Input or Output

The copy feature works in Entity Explorer, the Function Navigation diagram, and between them.

Copy an Input or Output Using Copy and Paste

1. Select an Input or Output to be copied.
2. Use one of the following options:
 - ▷ Choose **Edit ► Copy** from the Main Menu
 - ▷ Choose **Copy** from the Right-Click Menu
 - ▷ Use the **Ctrl+C** Keyboard Shortcut
3. Use one of the following options to paste the Input or Output:
 - ▷ Choose **Edit ► Paste** from the Main Menu
 - ▷ Choose **Paste** from the Right-Click Menu
 - ▷ Use the **Ctrl+V** Keyboard Shortcut

The above actions work between DFCs opened in different tabs of Process Builder.

Copy an Input or Output Using Drag-and-Drop and Holding Ctrl Key

Source	Target	Action
Input	Function or place between Inputs.	This DFC creates a copy of an Input.
Input	Another Input.	This DFC overwrites the target Input's properties.
Output	Function or place between Outputs.	This DFC creates a copy of an Output.
Output	Another Output.	This DFC overwrites the target Output's properties.

After Copying an Input or Output

The system creates copies of Inputs or Outputs with original names, adding and then incrementing a number at the end of names that already exist (e.g., Input, Input1...).

The system preserves all Input and Output properties except invalid pointers to Outputs from previous Functions.

Move an Input or Output

The move feature works in Entity Explorer, the Function Navigation diagram, and between them.

Move an Input or Output Using Cut and Paste

1. Select an Input or Output to be moved.
2. Use one of the following options:
 - ▷ Choose **Edit ► Cut** from the Main Menu
 - ▷ Choose **Cut** from the Right-Click Menu
 - ▷ Use the **Ctrl+X** Keyboard Shortcut

3. Use one of the following options to paste the Input or Output:

- ▷ Choose **Edit ► Paste** from the [Main Menu](#)
- ▷ Choose **Paste** from the [Right-Click Menu](#)
- ▷ Use the `Ctrl+V` [Keyboard Shortcut](#)

The above actions work between Operations opened in different tabs of Process Builder.

Move an Input or Output Using Drag-and-Drop

Source	Target	Action
Input	Place between Inputs in a Function.	The Input is moved.
Output	Place between Outputs in a Function.	The Output is moved.

It is possible to change the order of Inputs and Outputs in the Entity Explorer or in Function Navigation by dragging and dropping an Input or Output within the same Function.

After moving an Input or Output

The system moves the Inputs or Outputs with original names, adding and then incrementing a number at the end of names that already exist (e.g., Input, Input1...).

The system preserves all Input and Output properties except invalid pointers to Outputs from previous Functions.

Remove an Input or Output

1. [Select](#) one or more Inputs or Outputs to be removed.
2. Use one of the following options:
 - ▷ Choose **Edit ► Delete** from the [Main Menu](#)
 - ▷ Choose **Edit ► Cut** from the [Main Menu](#)
 - ▷ Choose **Delete** or **Cut** from the [Right-Click Menu](#)
 - ▷ Use the `Del` [Keyboard Shortcut](#)

The system removes invalid links between Inputs and Outputs after deletion.

In an Input To Output Function, the system will remove items in pairs.