Red GaAsP 0.5-Inch 7-Segment Numeric LED Displays

FND500, FND507 FND560, FND567

Optoelectronic Products

General Description The FND500, FND507, FND560 and FND567 are red GaAsP single-digit 7-Segment LED displays with a 0.5-inch character height. These displays are designed for applications in which the viewer is within twenty feet of the display.

Low Forward Voltage — Typically $V_F = 1.7 \text{ V}$ Fits Standard DIP Sockets with 0.6-Inch Pin Row Maximized Contrast Ratio With Integral Lens Cap Horizontal Stacking 0.6-Inch Minimum. 1-Inch Typical FND560/567 Suitable For Use In High Ambient Light FND500 Common Cathode, Right-Hand **Decimal Point** FND507 Common Anode, Right-Hand Decimal Point FND560 Common Cathode, Right-Hand Decimal Point, High Brightness FND567 Common Anode, Right-Hand Decimal Point, High Brightness

Absolute Maximum Ratings


Maximum Temperature and Humidity -25°C to +85°C Storage Temperature -25°C to +85°C Operating Temperature Pin Temperature (Soldering, 5 8) 260°C Relative Humidity at 65°C 98%

Maximum Voltage and Currents

Reverse Voltage 3.0 V ٧R Average Forward do ١Ę Current/Segment or **Decimal Point** 25 mA Derate from 25°C Ambient Temperature 0.3 mA/°C **Peak Forward Current** lok

Segment or Decimal Point (100 us pulse width) 1000 pps, TA = 25°C 200 mA


Package Outline



Notes All dimensions in inches bold and millimeters (parentheses) Tolerance unless specified = $\pm .015$ ($\pm .381$)

Connection Diagram Typical Electrical Characteristics

FND500, FND507 FND560, FND567



Pin FND507/567 FND500/560 Seament E Seament E Segment D Seament D Common Cathode Common Anode Seament C Seament C **Decimal Point** 5 Decimal Point Seament B Segment B Seament A Seament A Common Cathode Common Anode Seament F Seament F Seament G Segment G

Units

Test Conditions

Fiectrical at	ng Kaglant Characteristics	IA =	25-0	
				•
Symbol	Charactaristic			

Symbol	Characteristic	101111	1 . 1	1000	0	TOOL OOKOINONO
V _F	Forward Voltage	1.5	1.7	2.0	V	I _F = 20 mA
BVR	Reverse Breakdown Voltage	3.0	12		(v	I _R = 1.0 mA
10."	Axial Luminous Intensity, Average			ļ	İ	
	Each-Segment					<u> </u>
	FND500, FND507	300	600	1	μcd	i _F = 20 mA
	FND560, FND567	740	1200		μcd	IF = 20.mA
$\Delta I_{\mathbf{O}}$	Intensity Matching, Segment-to-Segment		± 33	1	96	I _F = 20 mA
	Intensity Matching Within One Intensity Class]	±20		96	I _F = 20 mA,
		1	1			all segments
		1	1	1	1	at once
Lo	Average Segment Luminance		1	-	1	
•	FND500, FND507		35		[ftL	I _F = 20 mA
	FND560, FND567	1	70		ftL	I _F = 20 mA
$\theta_{1/2}$	Viewing Angle to Half Intensity	1	±27	1	degrees	
λ _{pk}	Peak Wavelength	}	665	1	nm	IF = 20 mA