


Formats with variable information field length

For a variable number of data bytes the actual length has to be transmitted in the telegram header. This length indication is located twice (because of transmission security) at the telegram beginning in a fixed telegram header.

A) Format of the request telegram (Send/request frame):



B) Format of the response telegram (Response frame):



SYN = Synchronisation bits, min. 33 bits idle state (Idle)

SD2 = Start byte 2 (Start delimiter), Code: 68H

LE = Length, Value: 4 to 249

LEr = Length byte repeated (repeat)

DA = Destination address

SA = Source address

FC = Frame Control

DATA_UNIT = Data field, variable Length (L-3), max 246 bytes

FCS = Frame Check Sequence

ED = End Delimiter, Code: 16H

L = Length of information field, variable number of bytes L = 4 bis 249

Fig. Frame format with variable length