

Assignment – 3

Objective:

1. Blinking Of Led For Raspberry Pi
2. Traffic Lights Code For Raspberry Pi

Code 1:

```
import RPi.GPIO as
```

```
GPIOfrom time import
```

```
sleep
```

```
GPIO.setwarnings(False)
```

```
GPIO.setmode(GPIO.BOARD
```

```
)
```

```
GPIO.setup(8, GPIO.OUT, initial=GPIO.LOW)
```

```
while True:
```

```
    GPIO.output(8, GPIO.HIGH)
```

```
    sleep(1)
```

```
    GPIO.output(8, GPIO.LOW)
```

```
    sleep(1)
```

Code 2:

```
import RPi.GPIO as GPIO
import time
import signal
import sys

GPIO.setmode(GPIO.BCM)
GPIO.setup(9, GPIO.OUT)
GPIO.setup(10, GPIO.OUT)
GPIO.setup(11, GPIO.OUT)

def allLightsOff(signal, frame):
    GPIO.output(9, False)
    GPIO.output(10, False)
    GPIO.output(11, False)
    GPIO.cleanup() sys.exit(0)

signal.signal(signal.SIGINT, allLightsOff)

while True:
    GPIO.output(9, True)
    time.sleep(3)
    GPIO.output(10, True)
    time.sleep(1)
    GPIO.output(9, False)
    GPIO.output(10, False)
    GPIO.output(11, True)
    time.sleep(5)
    GPIO.output(11, False)
    GPIO.output(10, True)
    time.sleep(2)
    GPIO.output(10, False)
```