

Assignment -4

Question-1:

Write code and connections in wokwi for the ultrasonic sensor. Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events. Upload document with wokwi share link and images of IBM cloud

CODE 1 :

```
#include <WiFi.h>
#include <PubSubClient.h> void callback(char* subscribetopic, byte*
payload, unsigned int payloadLength);
#define ORG "rflzln"
#define DEVICE_TYPE "esp32"
#define DEVICE_ID "12345"
#define TOKEN "12345678" String data3; char server[] =
ORG ".messaging.internetofthings.ibmcloud.com"; char
publishTopic[] = "iot-2/evt/Data/fmt/json"; char
subscribetopic[] = "iot-2/cmd/test/fmt/String"; char
authMethod[] = "use-token-auth"; char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
WiFiClient wifiClient;
PubSubClient client(server, 1883, callback
,wifiClient); const int trigPin = 5; const int
echoPin = 18; #define SOUND_SPEED 0.034 long
duration; float distance; void setup() {
Serial.begin(115200); pinMode(trigPin, OUTPUT);
pinMode(echoPin, INPUT); wificonnect();
mqttconnect();
} void
loop()
{
digitalWrite(trigPin, LOW);
delayMicroseconds(2);
digitalWrite(trigPin, HIGH);
delayMicroseconds(10);
digitalWrite(trigPin, LOW);
duration = pulseIn(echoPin,
HIGH); distance = duration *
SOUND_SPEED/2;
Serial.print("Distance (cm): ");
Serial.println(distance);
if(distance<100)
{
Serial.println("ALERT!!");
delay(1000);
PublishData(distance);
delay(1000); if (!
client.loop())
{ mqttconnect();
} }
delay(1000)
; }
void PublishData(float dist)
{ mqttconnect();
String payload = "{\"Distance\":\""; payload += dist;
payload += "\",\"ALERT!!\":\"\"Distance less than
100cms\""; payload += "}";
Serial.print("Sending payload: ");
Serial.println(payload);

if (client.publish(publishTopic, (char*) payload.c_str())) {
Serial.println("Publish ok");
```

```

} else {
  Serial.println("Publish failed");
}
}

void mqttconnect() { if
(!client.connected()) {
  Serial.print("Reconnecting client to ");
  Serial.println(server);
  while (!!!client.connect(clientId, authMethod, token)) {
    Serial.print(".");
    delay(500); }
  initManagedDevice(
  );
  Serial.println();
}
}

void wificonnect()
{
  Serial.println();
  Serial.print("Connecting to ");
  WiFi.begin("Wokwi-GUEST", "", 6);
  while (WiFi.status() !=
  WL_CONNECTED) { delay(500);
  Serial.print(".");
}
  Serial.println("");
  Serial.println("WiFi connected");
  Serial.println("IP address: ");
  Serial.println(WiFi.localIP());
}

void initManagedDevice() {
if (client.subscribe(subscribetopic)) {
  Serial.println((subscribetopic));
  Serial.println("subscribe to cmd OK");
} else {
  Serial.println("subscribe to cmd FAILED");
}
}

void callback(char* subscribetopic, byte* payload, unsigned int
payloadLength) {
  Serial.print("callback invoked for topic:
  "); Serial.println(subscribetopic); for
  (int i = 0; i < payloadLength; i++)
  {
    data3 += (char)payload[i];
  }
  Serial.println("data: "+ data3);
  data3="";
}

```

Wokwi Link : <https://wokwi.com/projects/347205982600823378>

Output and Simulation :

WOKWI

SAVE

SHARE

sketch.ino

Docs

sketch.ino

diagram.json

LIBRARY.txt

libraries.txt

Library Manager

```

1 #include <Wifi.h>
2 #include <PubSubClient.h>
3 void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
4 #define ORG "rflz1n"
5 #define DEVICE_TYPE "esp32"
6 #define DEVICE_ID "12345"
7 #define TOKEN "12345678"
8 String data3;
9 char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
10 char publishTopic[] = "iot-2/evt/Data/fmt/json";
11 char subscribetopic[] = "iot-2/cmd/test/fmt/String";
12 char authMethod[] = "use-token-auth";
13 char token[] = TOKEN;
14 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
15 WiFiClient wificlient;
16 PubSubClient client(server, 1883, callback ,wificlient);
17 const int trigPin = 5;
18 const int echoPin = 18;
19 #define SOUND_SPEED 0.034
20 long duration;
21 float distance;
22 void setup() {
23   Serial.begin(115200);
24   pinMode(trigPin, OUTPUT);
25   pinMode(echoPin, INPUT);
26   wificlient.connect();
27   mqttconnect();
28 }

```

Simulation

01:14.335 100%

Editing Ultrasonic Distance Sensor

Distance: 55cm

ALERT!!

Sending payload: {"Distance":54.96,"ALERT!!":"Distance less than 100cms"}

Publish ok

Distance (cm): 54.96

ALERT!!

Sending payload: {"Distance":54.96,"ALERT!!":"Distance less than 100cms"}

Publish ok

Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events.

Browse

Action

Device Types

Interfaces

Add Device

Identity

Device Information

Recent Events

State

Logs

The recent events listed show the live stream of data that is coming and going from this device.

Event	Value	Format	Last Received
Data	{"Distance":54.96,"ALERT!!":"Distance less than ...	json	a few seconds ago
Data	{"Distance":54.96,"ALERT!!":"Distance less than ...	json	a few seconds ago
Data	{"Distance":54.96,"ALERT!!":"Distance less than ...	json	a few seconds ago
Data	{"Distance":54.96,"ALERT!!":"Distance less than ...	json	a few seconds ago
Data	{"Distance":54.96,"ALERT!!":"Distance less than ...	json	a few seconds ago