

Assignment -4 Data
Publish to IOT Device

Assignment Date	27 October 2022
Student Name	Mohamed Arsath
Student Roll Number	110119104034
Maximum Marks	2 Marks

Question-1:

Write code and connections in wokwi for ultrasonic sensor. Whenever distance is less 100 cms send "alert" to ibm cloud and display in device recent events.

Solution:

```
#include <WiFi.h> //library for wifi
```

```
#include <PubSubClient.h> //library for MQTT
```

```
void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);
```

```
//-----credentials of IBM Accounts-----
```

```
#define ORG "rdegk" //IBM ORGANITION ID
```

```
#define DEVICE_TYPE "weather1" //Device type mentioned in ibm watson IOT Platform
```

```
#define DEVICE_ID "weather1" //Device ID mentioned in ibm watson IOT Platform
```

```
#define TOKEN "_oa-3bajxqvCrO(6kW " //Token
```

```
String data3; float dist;
```

```
//----- Customise the above values -----char server[] = ORG
```

```
".messaging.internetofthings.ibmcloud.com"; // Server Name
```

```
char publishTopic[] = "iot-2/evt/Data/fmt/json"; // topic name and type of event perform and format in which data to be send
```

```
char subscribetopic[] = "iot-2/cmd/test/fmt/String"; // cmd REPRESENT command type AND  
COMMAND IS TEST OF FORMAT STRING char authMethod[] = "use-token-auth"; //  
authentication method
```

```
char token[] = TOKEN; char clientId[] = "d:" ORG ":" DEVICE_TYPE  
":" DEVICE_ID;//client id
```

```
//-----
```

```
WiFiClient wifiClient; // creating the instance for wificlient
```

```
PubSubClient client(server, 1883, callback ,wifiClient); //calling the predefined client id by passing  
parameter like server id,portand wificredential
```

```
int LED = 4;
```

```
int trig = 5;
```

```
int echo = 18;
```

```
void setup()
```

```
{
```

```
Serial.begin(115200);
```

```
pinMode(trig,OUTPUT);
```

```
pinMode(echo,INPUT);
```

```
pinMode(LED, OUTPUT);
```

```
delay(10); wificonnect();
```

```
mqttconnect();
```

```
}
```

```
void loop()// Recursive Function
```

```
{
```

```
digitalWrite(trig,LOW);
```

```
digitalWrite(trig,HIGH);
```

```
delayMicroseconds(10);
```

```
digitalWrite(trig,LOW); float
```

```
dur = pulseIn(echo,HIGH); float
```

```
dist = (dur * 0.0343)/2;
```

```
Serial.print ("Distancein cm");
```

```
Serial.println(dist);
```

```

    PublishData(dist);
    delay(1000); if
    (!client.loop()) {
    mqttconnect();
    }
}

/* .....retrieving to Cloud..... */

```

```

void PublishData(float dist) {
    mqttconnect();//function call for connecting to ibm
    /*   creating the String in in form JSon to update the data to ibm
    cloud
    */ String
    object; if
    (dist <100)
    {
        digitalWrite(LED,HIGH);
        Serial.println("object is near");
        object = "Near";
    }
    else
    {
        digitalWrite(LED,LOW);
        Serial.println("no object found");
        object = "No";
    }

    String payload = "{\"distance\":";
    payload += dist;  payload += ","
    "\"object\":"; payload +=
    object;  payload += "\"}";

```

```

    Serial.print("Sending payload: ");
    Serial.println(payload); if (client.publish(publishTopic,
(char*) payload.c_str())) {
        Serial.println("Publish ok");// if it sucessfully upload data on the cloud then it will print publish ok
        in Serial monitor or else it will print publish failed
    } else {
        Serial.println("Publish failed");
    }
}

void mqttconnect() { if
(!client.connected()) {
    Serial.print("Reconnecting client to ");
    Serial.println(server); while (!client.connect(clientId,
authMethod, token)) { Serial.print("."); delay(500);
    }
    initManagedDevice();
    Serial.println();
}
}

void wificonnect() //function defination for wificonnect
{
    Serial.println();
    Serial.print("Connecting to ");
    WiFi.begin("Wokwi-GUEST", "", 6);//passing the wifi credentials to establish the connection
    while (WiFi.status() != WL_CONNECTED) { delay(500);
        Serial.print(".");
    }
    Serial.println("");
    Serial.println("WiFi connected");
    Serial.println("IP address: ");
    Serial.println(WiFi.localIP());
}

```

```

}

void initManagedDevice() { if
(client.subscribe(subscribetopic)) {
Serial.println((subscribetopic));
    Serial.println("subscribe to cmd OK");
} else {
    Serial.println("subscribe to cmd FAILED");
}
}

void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{
    Serial.print("callback invoked for topic: ");
    Serial.println(subscribetopic); for (int i =
0; i < payloadLength; i++) {
//Serial.print((char)payload[i]);    data3 +=
(char)payload[i];
    }
    data3="";
}

```

Reference:

<https://wokwi.com/projects/347311168141918803>


WOKWI SAVE SHARE sketch.ino Docs M

sketch.ino diagram.json libraries.txt Library Manager

```
64 /*
65  * creating the String in in form JSON to update the data to ibm cloud
66  */
67 String object;
68 if (dist < 100)
69 {
70   digitalWrite(LED,HIGH);
71   Serial.println("object is near");
72   object = "Near";
73 }
74 else
75 {
76   digitalWrite(LED,LOW);
77   Serial.println("no object found");
78   object = "No";
79 }
80
81 String payload = "{\"distance\":";
82 payload += dist;
83 payload += "," " \"object\":\":";
84 payload += object;
85 payload += "\"}";
86
87 Serial.print("Sending payload: ");
88 Serial.println(payload);
89
90
91
92
```

Simulation

00:59.614 98%



object is near
Sending payload: {"distance":59.51,"object":"Near"}
Publish ok
Distancein cm59.51
object is near
Sending payload: {"distance":59.51,"object":"Near"}
Publish ok

IBM Watson IoT Platform 110119104034@aaimsec.ac.in ID: rdegylk

← Back

Device Drilldown - weather1

Recent Events

The recent events listed show the live stream of data that is coming and going from this device.

Event	Value	Format	Last Received
Data	{"distance":59.51,"object":"Near"}	json	a few seconds ago
Data	{"distance":59.51,"object":"Near"}	json	a few seconds ago
Data	{"distance":2.01,"object":"Near"}	json	a few seconds ago
Data	{"distance":347.01,"object":"No"}	json	a few seconds ago
Data	{"distance":403.49,"object":"No"}	json	a few seconds ago

0 Simulations running