

ASSIGNMENT-3

Name: Sai Vignesh.PJ

QUESTION:

Write a python code for blinking LED and Traffic lights for Raspberrypi.

Solution:

PYTHON CODE FOR BLINKING LED

```
import RPi.GPIO as GPIO # Import Raspberry Pi GPIO library
from time import sleep # Import the sleep function from the time module

GPIO.setwarnings(False) # Ignore warning for now
GPIO.setmode(GPIO.BOARD) # Use physical pin numbering
GPIO.setup(8, GPIO.OUT, initial=GPIO.LOW) # Set pin 8 to be an output pin and set initial value to low (off)

while True: # Run forever
    GPIO.output(8, GPIO.HIGH) # Turn on
    sleep(1) # Sleep for 1 second
    GPIO.output(8, GPIO.LOW) # Turn off
    sleep(1) # Sleep for 1 second
```

PYTHON CODE FOR TRAFFIC LIGHT

```
import RPi.GPIO as GPIO

import time

import signal

import sys


# Setup

GPIO.setmode(GPIO.BCM)

GPIO.setup(9, GPIO.OUT)

GPIO.setup(10, GPIO.OUT)

GPIO.setup(11, GPIO.OUT)


# Turn off all lights when user ends demo

def allLightsOff(signal, frame):

    GPIO.output(9, False)

    GPIO.output(10, False)

    GPIO.output(11, False)

    GPIO.cleanup()

    sys.exit(0)

signal.signal(signal.SIGINT, allLightsOff)


# Loop forever

while True:

    # Red

    GPIO.output(9, True)
```

```
time.sleep(3)

# Red and amber
GPIO.output(10, True)
time.sleep(1)

# Green
GPIO.output(9, False)
GPIO.output(10, False)
GPIO.output(11, True)
time.sleep(5)

# Amber
GPIO.output(11, False)
GPIO.output(10, True)
time.sleep(2)

# Amber off (red comes on at top of
loop) GPIO.output(10, False)
```