

### Assignment -3

Assignment Date	19 September 2022
Student Name	Duggi Reddy Srinivasa Reddy
Student Roll Number	111519106029
Maximum Marks	2 Marks

#### Question:

Write a python code for blinking LED and Traffic lights for Raspberry pi.

#### Solution:

CODE:

RASPBERRY PI LED BLINK:

```
import RPi.GPIO as GPIO
import time
GPIO.setmode(GPIO.BCM)
GPIO.setwarnings(False)
GPIO.setup(18,GPIO.OUT)
print ("LED on")
GPIO.output(18,GPIO.HIGH)
time.sleep(1) print ("LED off")
GPIO.output(18,GPIO.LOW)
```

## RASPBERRY PI FOR TRAFFIC LIGHT:

```
import RPi.GPIO as GPIO
import time
import signal
import sys

GPIO.setmode(GPIO.BCM)
GPIO.setup(9, GPIO.OUT)
GPIO.setup(10, GPIO.OUT)
GPIO.setup(11, GPIO.OUT)

def allLightsOff(signal, frame):
    GPIO.output(9, False)
    GPIO.output(10, False)
    GPIO.output(11, False)
    GPIO.cleanup()
    sys.exit(0)

signal.signal(signal.SIGINT, allLightsOff)

while True:
    GPIO.output(9, True)
    time.sleep(3)
    GPIO.output(10, True)
    time.sleep(1)
    GPIO.output(9, False)
    GPIO.output(10, False)
    GPIO.output(11, True)
    time.sleep(5)
    GPIO.output(11, False)
    GPIO.output(10, True)
    time.sleep(2)
    GPIO.output(10, False)
```