

TRAFFIC LIGHT RASBERRY PYTHON CODE

```
from gpiozero import LED
from time import sleep

red= LED(17)          #pin numbers connected to Led's
aster=(22) green=(27)

while True:
    red.on()           #RED light
    print("Red light is ON")
    for i in range(100,0,-1):
        print("Remaining time: ",i)
    sleep(1)  red.off()

    aster.on()         # ASTER light
    print("Yellow light is ON")
    for i in range(5,0,-1):
        print("Remaining time: ",i)
    sleep(1)  aster.off()

    green.on           #GREEN light
    print("Green light is ON")
    for i in range(30,0,-1):
        print("Remaining time: ",i)
    sleep(1)  green.off()
```

LED BLINKING CODE

```
Import RPi.GPIO as GP

From time import sleep

GP.setwarnings(False)

GP.setmode(GP.BOARD)

GP.setup(8,GP.OUT,initial=GP.LOW)

While True: #infinite loop

    GP.output(8, GPIO.HIGH) # Turn on

    Print("The LED is ON")

    Sleep(2) # Sleep for 2 second

    GP.output(8, GPIO.LOW) # Turn off

    Print("The LED is OFF")

    Sleep(2) # Sleep for 2 second
```

Subathra M
960219106134