

**Assignment -4**  
ESP32 Programming with IBM Cloud

Assignment Date	26 October 2022
Student Name	JERRY JOE SHELTON P
Student Roll Number	820419106021
Maximum Marks	2 Marks

**Question-1:**

Write code and connections in wokwi for ultrasonic sensor. Whenever distance is less than 100cms send "alert" to ibm cloud and display in device recent events.

Upload document with wokwi share link and images of ibm cloud.

**Solution:**

```
#include <WiFi.h> //library for wifi
#include <PubSubClient.h> //library for MQTT

#define ECHO_GPIO 12
#define TRIGGER_GPIO 13
#define MAX_DISTANCE_CM 100 // Maximum of 5 meters
#include "Ultrasonic.h"

Ultrasonic ultrasonic(13, 12); int
distance;
void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);
//-----credentials of IBM Accounts-----

#define ORG "iagzqu" //IBM ORGANITION ID
#define DEVICE_TYPE "deena" //Device type mentioned in ibm watson IOT
Platform #define DEVICE_ID "raspberrypi" //Device ID mentioned in ibm watson IOT
Platform #define TOKEN "DINESHkum@ind6"
String data3;
float h, t;

//----- Customise the above values -----
char server[] = ORG ".messaging.internetofthings.ibmcloud.com"; // Server Name char
publishTopic[] = "iot-2/evt/Data/fmt/json"; // topic name and type of event perform and format
in which data to be send
char subscribetopic[] = "iot-2/cmd/command/fmt/String"; // cmd REPRESENT command type AND
COMMAND IS TEST OF FORMAT STRING char authMethod[] = "use-token-auth"; // authentication
method char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID; //client id

//-----
WiFiClient wifiClient; // creating the instance for wificlient
PubSubClient client(server, 1883, callback ,wifiClient); //calling the predefined client id by
passing parameter like server id,portand wificredential
```

```

void setup()// configuring the ESP32
{
    Serial.begin(115200);
    delay(10);
    Serial.println();
    wificonnect();
    mqttconnect();
}
void loop()// Recursive Function
{

    distance = ultrasonic.read(CM);
    if(distance < 100){
        Serial.print("Distance in CM: ");
        Serial.println(distance);
        PublishData(distance);
        delay(1000); if
        (!client.loop()) {
            mqttconnect();
        }

    }

    delay(1000);

}

/*.....retrieving to Cloud ..... */

void PublishData(float temp) {
    mqttconnect();//function call for connecting to ibm
    /* creating the String in in form JSon to update the data to ibm
       cloud
    */
    String payload = "{\"Alert Distance\":\"";
    payload += temp; payload += "\"}";

    Serial.print("Sending payload: ");
    Serial.println(payload);

    if (client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Publish ok");// if it sucessfully upload data on the cloud then it will
        print publish ok in Serial monitor or else it will print publish failed
    } else {
        Serial.println("Publish failed");
    }

}

void mqttconnect() {
    if (!client.connected()) {
        Serial.print("Reconnecting client to ");
        Serial.println(server);
    }
}

```

```

        while (!client.connect(clientId, authMethod, token))
        { Serial.print("."); delay(500);
        }
        initManagedDevice(); Serial.println();
    }
} void wificonnect() //function definition for
wificonnect
{
    Serial.println();
    Serial.print("Connecting to ");

    WiFi.begin("Wokwi-GUEST", "", 6); //passing the wifi credentials to establish the connection
    while (WiFi.status() != WL_CONNECTED) {
        delay(500);
        Serial.print(".");
    }
    Serial.println("");
    Serial.println("WiFi connected");
    Serial.println("IP address: ");
    Serial.println(WiFi.localIP());
}
void initManagedDevice() {
    if (client.subscribe(subscribetopic)) {
        Serial.println((subscribetopic));
        Serial.println("subscribe to cmd OK");
    } else {
        Serial.println("subscribe to cmd FAILED"); }
}
void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{

    Serial.print("callback invoked for topic:
    "); Serial.println(subscribetopic); for (int
    i = 0; i < payloadLength; i++) {
        //Serial.print((char)payload[i]); data3 +=
        (char)payload[i];
    }
    Serial.println("data: "+ data3);
    if(data3=="lighton") {
Serial.println(data3);
    } else
    {
Serial.println(data3);
    } data3="";
}

```

WOKWI SAVE SHARE Docs

sketch.ino

```

1 #include <WiFi.h> //library for wifi
2 #include <PubSubClient.h> //library for MQTT
3
4 #define ECHO_GPIO 12
5 #define TRIGGER_GPIO 13
6 #define MAX_DISTANCE_CM 100 // Maximum of 5 meters
7 #include "Ultrasonic.h"
8
9 Ultrasonic ultrasonic(13, 12);
10 int distance;
11
12 void callback(char* subscribtopic, byte* payload, unsigned int payloadLength);
13
14 //-----credentials of IBM Accounts-----
15
16 #define ORG "bxdd09" //IBM ORGANITION ID
17 #define DEVICE_TYPE "ESP32" //Device type mentioned in ibm watson IOT Platform
18 #define DEVICE_ID "Assign4" //Device ID mentioned in ibm watson IOT Platform
19 #define TOKEN "45625689713" //Token
20 String data;
21 float h, t;
22
23 //----- Customise the above values -----
24
25 char server[] = ORG ".messaging.internetofthings.ibmcloud.com"; // Server Name
26 char publishTopic[] = "iot-2/evt/data/fmt/json"; // topic name and type of event perform
27 char subscribtopic[] = "iot-2/cmd/command/fmt/string"; // cmd REPRESENT command type AND
28 char authMethod[] = "use-token-auth"; // authentication method
29 char token[] = TOKEN;
30 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID; //client id
31
32 //-----
33
34 WiFiClient wificlient; // creating the instance for wificlient
35 PubSubClient client(server, 1883, callback, wificlient); //calling the predefined client

```

Simulation

Publish ok

Distance in CM: 28

Sending payload: {"Alert Distance":28.00}

Publish ok

Distance in CM: 28

Sending payload: {"Alert Distance":28.00}

Publish ok

Browse Action Device Types Interfaces Add Device

Identity Device Information Recent Events State Logs

The recent events listed show the live stream of data that is coming and going from this device.

Event	Value	Format	Last Received
Data	{"Alert Distance":28}	json	a few seconds ago
Data	{"Alert Distance":28}	json	a few seconds ago
Data	{"Alert Distance":28}	json	a few seconds ago
Data	{"Alert Distance":28}	json	a few seconds ago
Data	{"Alert Distance":28}	json	a few seconds ago

Items per page 50 | 1-2 of 2 items

1 of 1 page

0 Simulations running

Wokwi share link: <https://wokwi.com/projects/346461295197815380>