

ASSIGNMENT: ULTRASONIC ALARM SYSTEM USING LED, ULTRASONIC SENSOR(HC-SR04) AND A BUZZER

DATE	10/11/2022
TEAM ID	PNT2022TMID33565
STUDENT NAME	Naveen TR
STUDENT ROLL Number	922519106097

CODE:

```
#include <WiFi.h>
#include <PubSubClient.h>

WiFiClient wifiClient;
String data3;

#define ORG "3ynghb"
#define DEVICE_TYPE "Assignment"
#define DEVICE_ID "1234"
#define TOKEN "234567890"
#define speed 0.034
#define led 14

char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/shreedharen/fmt/json";
char topic[] = "iot-2/cmd/led/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);

const int trigpin=5;
const int echopin=18;
String command;
String data="";
long duration;
float dist;
```

```
void setup()
{
  Serial.begin(115200);
  pinMode(led, OUTPUT);
  pinMode(trigpin, OUTPUT);
  pinMode(echopin, INPUT);
  wifiConnect();
  mqttConnect();
}

void loop() {
  bool isNearby = dist < 100;
  digitalWrite(led, isNearby);

  publishData();
  delay(500);

  if (!client.loop()) {
    mqttConnect();
  }
}

void wifiConnect() {
  Serial.print("Connecting to "); Serial.print("Wifi");
  WiFi.begin("Wokwi-GUEST", "", 6);
  while (WiFi.status() != WL_CONNECTED) {
    delay(500);
    Serial.print(".");
  }
  Serial.print("WiFi connected, IP address: "); Serial.println(WiFi.localIP());
}
```

```
}
```

```
void mqttConnect() {  
  if (!client.connected()) {  
    Serial.print("Reconnecting MQTT client to "); Serial.println(server);  
    while (!client.connect(clientId, authMethod, token)) {  
      Serial.print(".");  
      delay(500);  
    }  
    initManagedDevice();  
    Serial.println();  
  }  
}
```

```
void initManagedDevice() {  
  if (client.subscribe(topic)) {  
    // Serial.println(client.subscribe(topic));  
    Serial.println("IBM subscribe to cmd OK");  
  } else {  
    Serial.println("subscribe to cmd FAILED");  
  }  
}
```

```
void publishData()  
{  
  digitalWrite(trigpin, LOW);  
  digitalWrite(trigpin, HIGH);  
  delayMicroseconds(10);  
  digitalWrite(trigpin, LOW);  
  duration=pulseIn(echopin, HIGH);  
  dist=duration*speed/2;
```

```
if(dist<100){
    String payload = "{\"Alert Distance\":\"";
    payload += dist;
    payload += "\"}";

    Serial.print("\n");
    Serial.print("Sending payload: ");
    Serial.println(payload);
    if (client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Publish OK");
    }
}

if(dist>100){
    String payload = "{\"Distance\":\"";
    payload += dist;
    payload += "\"}";

    Serial.print("\n");
    Serial.print("Sending payload: ");
    Serial.println(payload);
    if(client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Publish OK");
    }else {
        Serial.println("Publish FAILED");
    } } }
```

OUTPUT:

