

Assignment -4

Assignment Date	20 OCTOBER 2022
Student Name	SAHITHI K
Student Roll Number	722819106039
Maximum Marks	2 Marks

Question-1:

Write code and connections in wowki for ultrasonic sensor.

Whenever distance is less than 100 cms send “alert” to IBM cloud and display in device recent events.

Solution:

WOWKI LINK: <https://wokwi.com/projects/346235465961046612>

```
#include <WiFi.h>
#include <PubSubClient.h>
#define TRIGGER 2
#define ECHO 15
#define sound_speed 0.034
int distance;

void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);

//-----credentials of IBM Accounts-----

#define ORG "wp72r7"
#define DEVICE_TYPE "iot-device-1"
#define DEVICE_ID "123456789"
#define TOKEN "987654321"
```

String data3;

//----- Customise the above values -----

```
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";  
char publishTopic[] = "iot-2/evt/Data/fmt/json"; char  
subscribetopic[] = "iot-2/cmd/test/fmt/String"; char authMethod[]  
= "use-token-auth"; char token[] = TOKEN; char clientId[] = "d:"  
ORG ":" DEVICE_TYPE ":" DEVICE_ID;
```

//----- WiFiClient wifiClient;

```
PubSubClient client(server, 1883, callback ,wifiClient); void setup()  
{  
  Serial.begin(115200); pinMode(TRIGGER,  
OUTPUT); pinMode(ECHO, INPUT);  
  delay(10); Serial.println();  
wificonnect();  
  mqttconnect();  
}
```

void loop()

```
{  
  
  digitalWrite(TRIGGER, HIGH);  
delayMicroseconds(10); digitalWrite(TRIGGER,  
LOW);  
  
  int duration=pulseIn(ECHO,HIGH);  
distance=(duration*sound_speed)/2;  
  Serial.print("Distance:");  
  Serial.print(distance);  
Serial.println("cms"); if(distance<100){ PublishData(distance);  
  }  
  delay(1000); if (!client.loop())
```

```
{  
mqttconnect();  
}  
}
```

/.....retrieving to Cloud...../

```
void PublishData(int d) { mqttconnect();
```

```
String payload = "{\"message\":\"alert\"};
```

```
Serial.print("Sending payload: ");
```

```
Serial.println(payload);
```

```
if (client.publish(publishTopic, (char*) payload.c_str())) {
```

```
Serial.println("Publish ok");
```

```
} else {
```

```
Serial.println("Publish failed");
```

```
}
```

```
}
```

```
void mqttconnect() { if (!client.connected())
```

```
{
```

```
Serial.print("Reconnecting client to ");
```

```
Serial.println(server); while (!client.connect(clientId,
```

```
authMethod, token)) { Serial.print(".");
```

```
delay(500);
```

```
}
```

```
initManagedDevice();
```

```
Serial.println();
```

```
}
```

```
}
```

```

void wificonnect()
{
    Serial.println();
    Serial.print("Connecting to ");

    WiFi.begin("Wokwi-GUEST", "", 6); while (WiFi.status()
    != WL_CONNECTED) {
        delay(500);
        Serial.print("."); }
    Serial.println("");
    Serial.println("WiFi connected");
    Serial.println("IP address: ");
    Serial.println(WiFi.localIP());
}

void initManagedDevice() {
    if (client.subscribe(subscribetopic)) {
        Serial.println((subscribetopic));
        Serial.println("subscribe to cmd OK");
    } else {
        Serial.println("subscribe to cmd FAILED");
    }
}

void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{
    Serial.print("callback invoked for topic: ");
    Serial.println(subscribetopic); for (int i =
    0; i < payloadLength; i++) {    data3 +=
    (char)payload[i];
    }

    Serial.println("data: "+ data3);
}

```

data3="";


}

WOKWI SAVE SHARE Docs

sketch.ino diagram.json libraries.txt Library Manager

```
1 #include <WiFi.h>
2 #include <PubSubClient.h>
3 #define TRIGGER 2
4 #define ECHO 15
5 #define sound_speed 0.034
6 int distance;
7
8 void callback(char* subscribetopic, byte* payload, unsigned int payloadlength);
9
10 //-----credentials of IBM Accounts-----
11
12 #define ORG "wp72r7"
13 #define DEVICE_TYPE "iot-device-1"
14 #define DEVICE_ID "123456789"
15 #define TOKEN "987654321"
16 String data3;
17
18
19 //----- Customise the above values -----
20 char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
21 char publishTopic[] = "iot-2/evt/Data/fmt/json";
22 char subscribetopic[] = "iot-2/cmd/test/fmt/String";
23 char authMethod[] = "use-token-auth";
24 char token[] = TOKEN;
25 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
26
27
28 //-----
29 WiFiClient wificlient;
30 PubSubClient client(server, 1883, callback, wificlient);
31 void setup()
32 {
33   Serial.begin(115200);
34   pinMode(TRIGGER, OUTPUT);
35   pinMode(ECHO, INPUT);
36 }
```

Simulation



Connecting to
WiFi connected
IP address:
10.10.0.2
Reconnecting client to wp72r7.messaging.internetofthings.ibmcloud.com
iot-2/cmd/test/fmt/String
subscribe to cmd OK

399 cms.
399 cms.
399 cms.
212 cms.
30 cms.
Sending payload: {"message":"alert"}
Publish ok
30 cms.

CIRCUIT DIAGRAM:

IBM Watson IoT Platform

karthikayenn.c@sece.ac.in
ID: wp7277

Browse

Action

Device Types

Interfaces

Add Device

Browse Devices

All DevicesDiagnose

This table shows a summary of all devices that have been added. It can be filtered, organized, and searched on using different criteria. To get started, you can add devices by using the Add Device button, or by using API.

Search by Device ID

Device Simulator

Device ID	Status	Device Type	Class ID	Date Added	Descriptive Location	Added By	Device Class	Firmware Version	Hardware Version	Manufacturer	Model	Serial Number	Description
123456789	Disconnected	iot-device-1	Device	Oct 22, 2022 9:47 PM		karthikayenn.c@sece.ac.in							

Identity

Device Information

Recent Events

State

Logs

The recent events listed show the live stream of data that is coming and going from this device.

Event	Value	Format	Last Received
Data	["message":"alert"]	json	a few seconds ago
Data	["message":"alert"]	json	a few seconds ago
Data	["message":"alert"]	json	a few seconds ago
Data	["message":"alert"]	json	a few seconds ago
Data	["message":"alert"]	json	a few seconds ago

Items per page: 50 | 1-1 of 1 item

1 of 1 page

IBM CLOUD RECENT EVENTS: