TEAM ID :	**PNT2022TMID35130**
PROJECT NAME :	**PERSONAL ASSISTANCE FOR SENIORS WHO ARE SELF RELIANT**

Iot device program :

```
#include <WiFi.h>//library for wifi
#include <PubSubClient.h>//library for MQtt
#include <LiquidCrystal_I2C.h>
#include "DHT.h"// Library for dht11
#define DHTPIN 15     // what pin we're connected to
#define DHTTYPE DHT11   // define type of sensor DHT 11
#define Buzzer 2
DHT dht (DHTPIN, DHTTYPE);// creating the instance by passing pin and typr of dht connected
void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);

//-------credentials of IBM Accounts------

#define ORG "1l6lvg"//IBM ORGANITION ID
#define DEVICE_TYPE "nodeMCU"//Device type mentioned in ibm watson IOT Platform
#define DEVICE_ID "12345"//Device ID mentioned in ibm watson IOT Platform
#define TOKEN "?nUW@lkY)OglhHt)i6"     //Token
String data3="";

//-------- Customise the above values --------
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";// Server Name char publishTopic[] = "iot-2/evt/Data/fmt/json";// topic name and type of event perform and format in which data to be send
```

```
char subscribetopic[] = "iot-2/cmd/command/fmt/String";// cmd  REPRESENT command type
AND COMMAND IS TEST OF FORMAT STRING
char authMethod[] = "use-token-auth";// authentication method char
token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;//client id LiquidCrystal_I2C
lcd(0x27,16,2);

//---------------------------------------
WiFiClient wifiClient; // creating the instance for wificlient
PubSubClient client(server, 1883, callback ,wifiClient); //calling the predefined client id by passing parameter like server id,portand wificredential void setup()// configureing the ESP32
{
  Serial.begin(115200);   dht.begin();
  pinMode(Buzzer,OUTPUT);
  delay(10);   Serial.println();
wificonnect();
mqttconnect();
}

void loop()// Recursive Function
{    if
(!client.loop()) {
mqttconnect();
  } }
void PublishData(float temp, float humid) {
mqttconnect();//function call for connecting to ibm

}  void mqttconnect() {
if (!client.connected())
{
    Serial.print("Reconnecting client to ");
Serial.println(server);      while (!!!client.connect(clientId,
```

```
authMethod, token)) {       Serial.print(".");
delay(500);
    }
     initManagedDevice();
     Serial.println();
  } }
void wificonnect() //function defination for wificonnect
{
  Serial.println();
  Serial.print("Connecting to ");

  WiFi.begin("Wokwi-GUEST", "", 6);//passing the wifi credentials to establish the
connection   while (WiFi.status() != WL_CONNECTED) {     delay(500);
    Serial.print(".");
  }
  Serial.println("");
  Serial.println("WiFi connected");
  Serial.println("IP address: ");
  Serial.println(WiFi.localIP());
}

void initManagedDevice() {   if
(client.subscribe(subscribetopic)) {
    Serial.println((subscribetopic));
    Serial.println("subscribe to cmd OK");
  } else {
    Serial.println("subscribe to cmd FAIBuzzer");
  }
}

void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)  {
```

```
  Serial.print("callback invoked for topic: ");
Serial.println(subscribetopic);   for (int i =
0; i < payloadLength; i++) {
//Serial.print((char)payload[i]);     data3 +=
(char)payload[i];
  }

  Serial.println("Medicine Name: "+ data3);
if(data3 != "")
  {     lcd.init();     lcd.print(data3);
digitalWrite(Buzzer,HIGH);
delay(20000);
digitalWrite(Buzzer,LOW);
  }   else
  {
digitalWrite(Buzzer,LOW);
  }
data3="";
}
```