PYTHON CODE FOR BLINKING LED AND TRAFFIC LIGHTS FOR RASPBERRY PI

For LED:

```python
import RPi.GPIO as GPIO

from time import sleep

GPIO.setwarnings(False)

GPIO.setmode(GPIO.BOARD)

GPIO.setup(8,GPIO.OUT,initial=GPIO.LOW)

while True:

GPIO.output(8,GPIO.HIGH)

sleep(1)

GPIO.output(8,GPIO.LOW)

sleep(1)
```

For Traffic Lights:

```python
import Rpi.GPIO as GPIO

import time

import signal

import sys

 GPIO.setmode(GPIO.BCM)

GPIO.setup(9,GPIO.OUT)

GPIO.setup(10,GPIO.OUT)

GPIO.setup(11,GPIO.OUT)

 def allLightsOff(signal,framer):
```

```python
    GPIO.output(9,False)
    GPIO.output(10,False)
    GPIO.output(11,False)
    GPIO.cleanup()
    sys.exit(0)
signal.signal(signal.SIGINT,allLightsOff)


while True:
#Red
GPIO.output(9,True)
Time.sleep(3)
#Red and amber
GPIO.output(10,True)
Time.sleep(1)


#Green
GPIO.output(9,False)
GPIO.output(10,False)
GPIO.output(11,True)
Time.sleep(5)
#Amber
GPIO.output(11,False)
```

```
GPIO.output(10,True)

Time.sleep(2)

#Amber off(red comes on at top of loop)

GPIO.output(10,False)
```