

Assignment -3
Python Programming

Assignment Date	07 October 2022
Student Name	KEERTHIKA K
Student Roll Number	811219104008
Maximum Marks	2 Marks

Question:

Write a python code for blinking LED and Traffic lights for Raspberry Pi.

PROGRAM:

```
import RPi.GPIO as
GPIO import time
import os import signal
import sys

if('TRAFFIC_LIGHT_COUNTRY' in os.environ) and (os.environ['TRAFFIC_LIGHT_C
O UNTRY'] in ['UK', 'USA']):
    pattern = os.environ['TRAFFIC_LIGHT_COUNTRY'].lower()
else:
    print('TRAFFIC_LIGHT_COUNTRY should be set to UK or USA')
    sys.exit(1)

# Setup
GPIO.setmode(GPIO.BCM)
GPIO.setup(9, GPIO.OUT)
GPIO.setup(10, GPIO.OUT)
GPIO.setup(11, GPIO.OUT)

# Turn off all lights when user ends demo
def allLightsOff(signal, frame):
```

```
GPIO.output(9, False)
GPIO.output(10, False)
GPIO.output(11, False)
GPIO.cleanup() sys.exit(0)
signal.signal(signal.SIGINT,
T, allLightsOff)
```

```
# Loop forever while
```

```
True:
```

```
    # Red GPIO.output(9,
    True) time.sleep(3)
```

```
    # Red and amber for UK only if
    (pattern == 'uk'):
```

```
        GPIO.output(10, True) time.sleep(1)
```

```
    # Green
```

```
    GPIO.output(9, False)
    GPIO.output(10, False)
    GPIO.output(11, True) time.sleep(5)
```

```
    # Amber, longer in US than UK
```

```
    GPIO.output(11, False)
    GPIO.output(10, True)
    if (pattern == 'uk'):
```

```
        time.sleep(2)
```

```
    else:
```

```
        time.sleep(3)
```

```
    # Amber off (red comes on at top of loop)
```

```
    GPIO.output(10, False)
```