

# ASSIGNMENT 4

Team ID: PNT2022TMID52302

Project Name: Gas Leakage monitoring & Alerting system for Industries

Submitted by DANIEL R (963519106017)

## QUESTION:

Write code and connections in wokwi for the ultrasonic sensor. Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events.

Upload document with wokwi share link and images of IBM cloud

## Solution Code:

```
#include<WiFi.h>
#include<PubSubClient.h>
voidcallback(char* subscribetopic, byte* payload, unsignedintpayloadLength);
#define ORG "pjny99"//IBM ORGANITION ID
#define DEVICE_TYPE "UltrasonicSensor"
#define DEVICE_ID "01151122"
#define TOKEN "LRGui+TSM?4HjrNAfo"//Token
String data3;
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
charpublishTopic[] = "iot-2/evt/Data/fmt/json";
charsubscribetopic[] = "iot-2/cmd/test/fmt/String";
charauthMethod[] = "use-token-auth";
char token[] = TOKEN;
charclientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
WiFiClientwifiClient;
PubSubClient client(server, 1883, callback ,wifiClient);
constinttrigPin = 5;
constintechoPin = 18;
#define SOUND_SPEED 0.034
long duration;
float distance;
voidsetup()
{
    Serial.begin(115200);
    pinMode(trigPin, OUTPUT);
```

```

    pinMode(echoPin, INPUT);
    wificonnect();
    mqttconnect();
}
void loop()
{
    digitalWrite(trigPin, LOW);
    delayMicroseconds(2);
    digitalWrite(trigPin, HIGH);
    delayMicroseconds(10);
    digitalWrite(trigPin, LOW);
    duration = pulseIn(echoPin, HIGH);
    distance = duration * SOUND_SPEED/2;
    Serial.print("Distance (cm): ");
    Serial.println(distance);
    if(distance<100) {
        Serial.println("ALERT!!");
        delay(1000);
        PublishData(distance);
        delay(1000);
        if (!client.loop()) {
            mqttconnect();
        }
    }
    delay(1000);
}
void PublishData(float dist)
{
    mqttconnect();
    String payload = "{\"Distance\": ";
    payload += dist;
    payload += ", \"ALERT!!\": \"\" \"Distance less than 100cms\"";
    payload += "}";
    Serial.print("Sending payload: ");
    Serial.println(payload);
    if (client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Publish ok");
    } else {
        Serial.println("Publish failed");
    }
}
void mqttconnect()
{
    if (!client.connected()) {
        Serial.print("Reconnecting client to ");
    }
}

```

```

    Serial.println(server);
    while (!client.connect(clientId, authMethod, token)) {
        Serial.print("."); delay(500);
    }
    initManagedDevice();
    Serial.println();
}

void wificonnect()
{
    Serial.println();
    Serial.print("Connecting to ");
    WiFi.begin("Wokwi-GUEST", "", 6);
    while (WiFi.status() != WL_CONNECTED) {
        delay(500); Serial.print(".");
    }
    Serial.println("");
    Serial.println("WiFi connected");
    Serial.println("IP address: ");
    Serial.println(WiFi.localIP());
}

void initManagedDevice()
{
    if (client.subscribe(subscribetopic)) {
        Serial.println((subscribetopic));
        Serial.println("subscribe to cmd OK");
    } else {
        Serial.println("subscribe to cmd FAILED");
    }
}

void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{
    Serial.print("callback invoked for topic: ");
    Serial.println(subscribetopic);
    for (int i = 0; i < payloadLength; i++) {
        Serial.print((char)payload[i]);
        data3 += (char)payload[i];
    }
    Serial.println("data: " + data3);
    data3 = "";
}

```

**wokwi link** : <https://wokwi.com/projects/347736057197888083>

# OUTPUT :

