Write a python code for led blinking in raspberry pi SOLUTION:

import RPi.GPIO as GPIO # Import Raspberry Pi GPIO library

from time import sleep # Import the sleep function from the time module

GPIO.setwarnings(False) # Ignore warning for now

GPIO.setmode(GPIO.BOARD) # Use physical pin numbering

GPIO.setup(8, GPIO.OUT, initial=GPIO.LOW) # Set pin 8 to be an output pin and set initial value to

low (off)

while True: # Run forever

GPIO.output(8, GPIO.HIGH) # Turn on

sleep(1) # Sleep for 1 second

GPIO.output(8, GPIO.LOW) # Turn off

sleep(1) # Sleep for 1 second

```
File Edit Format Run Options Window Help

import RPI.GPIO as GPIO # Import Raspberry Pi GPIO library

from time import sleep # Import the sleep function from the time module

GPIO.setwarnings(False) # Ignore warning for now

GPIO.setwode(GPIO.BOARD) # Use physical pin numbering

GPIO.setup(8, GPIO.OUT, initial=GPIO.LOW) # Set pin 8 to be an output pin and set initial value to low (off)

while True: # Run forever

GPIO.output(8, GPIO.HIGH) # Turn on

sleep(1) # Sleep for 1 second

GPIO.output(8, GPIO.LOW) # Turn off

sleep(1) # Sleep for 1 second
```

Write a python code for traffic light in raspberry pi SOLUTION:

from gpiozero import Button, TrafficLights, Buzzer from time import sleep

```
buzzer = Buzzer(15)
button = Button(21)
lights = TrafficLights(25, 8, 7)
while True:
button.wait_for_press()
buzzer.on()
light.green.on()
sleep(1)
```

lights.amber.on() sleep(1)

lights.red.on() sleep(1) lights.off() buzzer.off()

Last modified: 2:05 pm