

```

#include <WiFi.h>
#include <PubSubClient.h>
void callback(char* subscribtopic, byte* payload, unsigned int
payloadLength);
//-----credentials of IBM Accounts-----
#define ORG "x9ptyw"//IBM ORGANITION ID
#define DEVICE_TYPE "ESP32"//Device type mentioned in ibm watson IOT Platform
#define DEVICE_ID "12345"//Device ID mentioned in ibm watson IOT Platform
#define TOKEN "123456789" //Token
String data3;
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json";
char subscribtopic[] = "iot-2/cmd/test/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
WiFiClient wifiClient;
PubSubClient client(server, 1883, callback ,wifiClient);
const int trigPin = 12;
const int echoPin = 13;
#define SOUND_SPEED 0.034
long duration;
float distance;
void setup() {
  Serial.begin(115200);
  pinMode(trigPin, OUTPUT);
  pinMode(echoPin, INPUT);
  wificonnect();
  mqttconnect();
}
void loop()
{
  digitalWrite(trigPin, LOW);
  delayMicroseconds(2);
  digitalWrite(trigPin, HIGH);
  delayMicroseconds(10);
  digitalWrite(trigPin, LOW);
  duration = pulseIn(echoPin, HIGH);
  distance = duration * SOUND_SPEED/2;
  Serial.print("Distance (cm): ");
  Serial.println(distance);
  if(distance<100)
  {
    Serial.println("ALERT!!");
    delay(1000);
    PublishData(distance);
    delay(1000);
    if (!client.loop()) {

```

```

mqttconnect();
}
}
delay(1000);
}
void PublishData(float dist) {
mqttconnect();
String payload = "{\"Distance\":\"";
payload += dist;
payload += "\",\"ALERT!!\":\"\"Distance less than 100cms\"";
payload += "\"}";
Serial.print("Sending payload: ");
Serial.println(payload);

if (client.publish(publishTopic, (char*) payload.c_str())) {
Serial.println("Publish ok");
} else {
Serial.println("Publish failed");
}
}

void mqttconnect() {
if (!client.connected()) {
Serial.print("Reconnecting client to ");
Serial.println(server);
while (!!!client.connect(clientId, authMethod, token)) {
Serial.print(".");
delay(500);
}
initManagedDevice();
Serial.println();
}
}

void wificonnect()
{
Serial.println();
Serial.print("Connecting to ");
WiFi.begin("Wokwi-GUEST", "", 6);
while (WiFi.status() != WL_CONNECTED) {
delay(500);
Serial.print(".");
}
Serial.println("");
Serial.println("WiFi connected");
Serial.println("IP address: ");
Serial.println(WiFi.localIP());
}

void initManagedDevice() {
if (client.subscribe(subscribetopic)) {

```

```
Serial.println(subscribetopic);
Serial.println("subscribe to cmd OK");
} else {
Serial.println("subscribe to cmd FAILED");
}
}
void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{
Serial.print("callback invoked for topic: ");
Serial.println(subscribetopic);
for (int i = 0; i < payloadLength; i++) {
//Serial.print((char)payload[i]);
data3 += (char)payload[i];
}
Serial.println("data: "+ data3);
data3="";
}
```

WOKWI

SAVE

SHARE

sketch.ino

Docs

SIGN UP

sketch.ino

diagram.json

libraries.txt

Library Manager

```

15 char token[] = TOKEN;
16 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
17 WiFiClient wifiClient;
18 PubSubClient client(server, 1883, callback ,wifiClient);
19 const int trigPin = 12;
20 const int echoPin = 13;
21 #define SOUND_SPEED 0.034
22 long duration;
23 float distance;
24 void setup() {
25   Serial.begin(115200);
26   pinMode(trigPin, OUTPUT);
27   pinMode(echoPin, INPUT);
28   wifiConnect();
29   mqttConnect();
30 }
31 void loop()
32 {
33   digitalWrite(trigPin, LOW);
34   delayMicroseconds(2);
35   digitalWrite(trigPin, HIGH);
36   delayMicroseconds(10);
37   digitalWrite(trigPin, LOW);
38   duration = pulseIn(echoPin, HIGH);
39   distance = duration * SOUND_SPEED/2;
40   Serial.print("Distance (cm): ");
41   Serial.println(distance);
42   if(distance<100)
43   {
44     Serial.println("ALERT!!");
45     delay(1000);
46   }

```

Simulation

00:19.932 62%

Editing Ultrasonic Distance Sensor

Distance: 73cm

Connecting to

WiFi connected

IP address:

10.10.0.2

Reconnecting client to x9ptyw.messaging.internetofthings.ibmcloud.com

.....

IBM Watson IoT Platform

harikrishna3404@gmail.com

ID: x9ptyw

Browse

Action

Device Types

Interfaces

Add Device

Device ID	Status	Device Type	Class ID	Date Added
12345	Disconnected	ESP32	Device	Nov 7, 2022 2:12 PM

Identity

Device Information

Recent Events

State

Logs

The recent events listed show the live stream of data that is coming and going from this device.

Event	Value	Format	Last Received
event_1	{"Distance":73,"Alert":"Distance less than 100"}	json	a few seconds ago
event_1	{"Distance":85,"Alert":"Distance less than 100"}	json	a few seconds ago
event_1	{"Distance":42,"Alert":"Distance less than 100"}	json	a few seconds ago
event_1	{"Distance":62,"Alert":"Distance less than 100"}	json	a few seconds ago
event_1	{"Distance":52,"Alert":"Distance less than 100"}	json	a few seconds ago

<https://wokwi.com/projects/new/esp32>