

Assignment -4
SmartFarmer - IoT Enabled Smart Farming Application
ESP32 Programming with IBM Cloud

Assignment Date	24 October 2022
Student Name	RAMAKUMAR B
Student Roll Number	113219041093
Maximum Marks	2 Marks

Question:

Write code and connections in wokwi for ultrasonic sensor. Whenever distance is less than 100cms send “alert” to ibm cloud and display in device recent events.

Upload document with wokwi share link and images of ibm cloud.

Solution:

```
#include <WiFi.h> //library for wifi
#include <PubSubClient.h> //library for MQTT

#define ECHO_GPIO 12
#define TRIGGER_GPIO 13
#define MAX_DISTANCE_CM 100 // Maximum of 5 meters
#include "Ultrasonic.h"

Ultrasonic ultrasonic(13, 12);
int distance;

void callback(char* subscribetopic, byte* payload, unsigned int
payloadLength);

//-----credentials of IBM Accounts-----

#define ORG "dv1snq" //IBM ORGANITION ID
#define DEVICE_TYPE "ESP32" //Device type mentioned in ibm watson IOT Platform
#define DEVICE_ID "12345" //Device ID mentioned in ibm watson IOT Platform
#define TOKEN "45682367915" //Token
String data3;
float h, t;

//----- Customise the above values -----
char server[] = ORG ".messaging.internetofthings.ibmcloud.com"; // Server Name
char publishTopic[] = "iot-2/evt/Data/fmt/json"; // topic name and type of
event perform and format in which data to be send
char subscribetopic[] = "iot-2/cmd/command/fmt/String"; // cmd REPRESENT
command type AND COMMAND IS TEST OF FORMAT STRING
```

```

char authMethod[] = "use-token-auth";// authentication method
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;//client id

//-----
WiFiClient wifiClient; // creating the instance for wificlient
PubSubClient client(server, 1883, callback ,wifiClient); //calling the
predefined client id by passing parameter like server id,portand
wificredential

void setup()// configureing the ESP32
{
    Serial.begin(115200);
    delay(10);
    Serial.println();
    wificonnect();
    mqttconnect();
}

void loop()// Recursive Function
{
    distance = ultrasonic.read(CM);
    if(distance < 100){
        Serial.print("Distance in CM: ");
        Serial.println(distance);
        PublishData(distance);
        delay(1000);
        if (!client.loop()) {
            mqttconnect();
        }
    }

    delay(1000);
}

/*.....retrieving to
Cloud. .... */

void PublishData(float temp) {
    mqttconnect();//function call for connecting to ibm
    /*
        creating the String in in form JSon to update the data to ibm cloud
    */
    String payload = "{\"Alert Distance\":\"";

```

```

payload += temp;
payload += "}";

Serial.print("Sending payload: ");
Serial.println(payload);

if (client.publish(publishTopic, (char*) payload.c_str())) {
    Serial.println("Publish ok");// if it sucessfully upload data on the cloud
    then it will print publish ok in Serial monitor or else it will print publish
    failed
} else {
    Serial.println("Publish failed");
}
}

void mqttconnect() {
    if (!client.connected()) {
        Serial.print("Reconnecting client to ");
        Serial.println(server);
        while (!!!client.connect(clientId, authMethod, token)) {
            Serial.print(".");
            delay(500);
        }

        initManagedDevice();
        Serial.println();
    }
}

void wificonnect() //function defination for wificonnect
{
    Serial.println();
    Serial.print("Connecting to ");

    WiFi.begin("Wokwi-GUEST", "", 6);//passing the wifi credentials to establish
    the connection
    while (WiFi.status() != WL_CONNECTED) {
        delay(500);
        Serial.print(".");
    }
    Serial.println("");
    Serial.println("WiFi connected");
    Serial.println("IP address: ");
    Serial.println(WiFi.localIP());
}

```

```

void initManagedDevice() {
  if (client.subscribe(subscribetopic)) {
    Serial.println((subscribetopic));
    Serial.println("subscribe to cmd OK");
  } else {
    Serial.println("subscribe to cmd FAILED");
  }
}

void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{
  Serial.print("callback invoked for topic: ");
  Serial.println(subscribetopic);
  for (int i = 0; i < payloadLength; i++) {
    //Serial.print((char)payload[i]);
    data3 += (char)payload[i];
  }
  Serial.println("data: "+ data3);
  if(data3=="lighton")
  {
    Serial.println(data3);
  }
  else
  {
    Serial.println(data3);
  }
  data3="";
}

```

Wokwi link:

<https://wokwi.com/projects/346659959540286034>

WOKWI SAVE SHARE Docs

sketch.ino diagram.json libraries.txt Ultrasonic.h Ultrasonic.cpp Library Manager

```
1 #include <WiFi.h> //library for wifi
2 #include <PubSubClient.h> //library for MQTT
3
4 #define ECHO_GPIO 12
5 #define TRIGGER_GPIO 13
6 #define MAX_DISTANCE_CM 100 // Maximum of 5 meters
7 #include "Ultrasonic.h"
8
9 Ultrasonic ultrasonic(13, 12);
10 int distance;
11
12 void callback(char* subscribtopic, byte* payload, unsigned int payloadlength);
13
14 //-----credentials of IBM Accounts-----
15
16 #define ORG "dvsinq" //IBM ORGANIZATION ID
17 #define DEVICE_TYPE "ESP32" //Device type mentioned in ibm watson IOT Platform
18 #define DEVICE_ID "12345" //Device ID mentioned in ibm watson IOT Platform
19 #define TOKEN "45682367915" //Token
20 String data3;
21 float h, t;
22
23
24 //----- Customise the above values -----
25 char server[] = ORG ".messaging.internetofthings.ibmcloud.com"; // Server Name
26 char publishTopic[] = "iot-2/evt/Data/fmt/json"; // topic name and type of event perform
27 char subscribtopic[] = "iot-2/cmd/command/fmt/String"; // cmd REPRESENT command type AND
28 char authMethod[] = "use-token-auth"; // authentication method
29 char token[] = TOKEN;
30 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID; //client id
31
32
```

Simulation

WOKWI SAVE SHARE Docs

sketch.ino diagram.json libraries.txt Ultrasonic.h Ultrasonic.cpp Library Manager

```
1 #include <WiFi.h> //library for wifi
2 #include <PubSubClient.h> //library for MQTT
3
4 #define ECHO_GPIO 12
5 #define TRIGGER_GPIO 13
6 #define MAX_DISTANCE_CM 100 // Maximum of 5 meters
7 #include "Ultrasonic.h"
8
9 Ultrasonic ultrasonic(13, 12);
10 int distance;
11
12 void callback(char* subscribtopic, byte* payload, unsigned int payloadlength);
13
14 //-----credentials of IBM Accounts-----
15
16 #define ORG "dvsinq" //IBM ORGANIZATION ID
17 #define DEVICE_TYPE "ESP32" //Device type mentioned in ibm watson IOT Platform
18 #define DEVICE_ID "12345" //Device ID mentioned in ibm watson IOT Platform
19 #define TOKEN "45682367915" //token
20 String data3;
21 float h, t;
22
23
24 //----- Customise the above values -----
25 char server[] = ORG ".messaging.internetofthings.ibmcloud.com"; // Server Name
26 char publishTopic[] = "iot-2/evt/Data/fmt/json"; // topic name and type of event perform
27 char subscribtopic[] = "iot-2/cmd/command/fmt/String"; // cmd REPRESENT command type AND
28 char authMethod[] = "use-token-auth"; // authentication method
29 char token[] = TOKEN;
30 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID; //client id
31
32
```

Simulation

00:42.062 103%

Editing Ultrasonic Distance Sensor

Distance: 59cm

Publish ok

Distance in CM: 62

Sending payload: {"Alert Distance":62.00}

Publish ok

Distance in CM: 62

Sending payload: {"Alert Distance":62.00}

Publish ok

Browse

Action

Device Types

Interfaces

Add Device +

The recent events listed show the live stream of data that is coming and going from this device.

Event	Value	Format	Last Received
Data	{"Alert Distance":62}	json	a few seconds ago
Data	{"Alert Distance":62}	json	a few seconds ago
Data	{"Alert Distance":62}	json	a few seconds ago
Data	{"Alert Distance":62}	json	a few seconds ago
Data	{"Alert Distance":62}	json	a few seconds ago

Items per page 50

1-1 of 1 item

1 of 1 page

< 1 >

WOKWI

SAVE

SHARE

Docs

sketch.ino

diagram.json

libraries.txt

Ultrasonic.h

Ultrasonic.cpp

Library Manager

> callback

Aa

?

of 4

↑

↓

≡

×

```

1 #include <WiFi.h> //library for wifi
2 #include <PubSubClient.h> //library for MQTT
3
4 #define ECHO_GPIO 12
5 #define TRIGGER_GPIO 13
6 #define MAX_DISTANCE_CM 100 // Maximum of 5 meters
7 #include "Ultrasonic.h"
8
9 Ultrasonic ultrasonic(13, 12);
10 int distance;
11
12 void callback(char* subscribetopic, byte* payload, unsigned int payloadlength);
13
14 //-----credentials of IBM Accounts-----
15
16 #define ORG "dvisng" //IBM ORGANIZATION ID
17 #define DEVICE_TYPE "ESP32" //Device type mentioned in ibm watson IOT Platform
18 #define DEVICE_ID "i2345" //Device ID mentioned in ibm watson IOT Platform
19 #define TOKEN "45682367915" //Token
20 String data3;
21 float h, t;
22
23
24 //----- Customise the above values -----
25 char server[] = ORG ".messaging.internetofthings.ibmcloud.com"; // Server Name
26 char publishTopic[] = "iot-2/evt/Data/fmt/json"; // topic name and type of event perform
27 char subscribetopic[] = "iot-2/cmd/command/fmt/String"; // cmd REPRESENT command type AND
28 char authMethod[] = "use-token-auth"; // authentication method
29 char token[] = TOKEN;
30 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID; //client id
31
32

```

Simulation

00:39:161 100%

▶

⏏

⏸

Editing Ultrasonic Distance Sensor

Distance: 124cm

Publish ok

Distance in CM: 56

Sending payload: {"Alert Distance":56.00}

Publish ok

Distance in CM: 56

Sending payload: {"Alert Distance":56.00}

Publish ok