

Instructions: Television



Resource name	Television
Description	This resource allows you to create a TV where participants can change channels and play content from an auxiliary source (e.g., a Blu-ray disc or a VHS tape). The TV can be linked to an escape room puzzle and its solution.
Usage requirements	None.
Settings	
Skin	This setting allows you to select the appearance of the TV. It can take the following values: "Smart TV", "Retro with remote", or "Retro".
Aspect ratio	This setting allows you to select the TV screen aspect ratio. It can take the following values: "16:9" or "4:3".

Action after solving	This setting allows you to select the action that will be carried out after the participants access the correct source, that is, the source specified by the solution of the linked puzzle. It can take the following values:	
	None	
	Show message	If this action is selected, participants will be able to see a message on the TV after accessing the correct source and the linked puzzle will be completed once a certain amount of time has elapsed since that moment. This time can be specified, in seconds, through the “Minimum success message duration” setting. The message must be specified through the “Channels” setting if the correct source is a channel, or through the “Auxiliary source content” setting otherwise.
	Play video	If this action is selected, participants will be able to watch a video on the TV after accessing the correct source and the linked puzzle will be completed once the playback of that video has finished. If the correct source is a channel, the video to be played must be specified through the “Channels” setting. Otherwise, the video must be specified through the “Auxiliary source content” setting.
Maximum channel number length	This setting allows specifying the maximum number of digits a channel can have. For example, if its value is 4, participants will be able to select channels between 0 and 9999.	
Loop channel videos	This setting allows specifying whether the videos associated with the channels will be played in a loop.	
Simulate signal noise	This setting allows applying a signal noise effect to the content played on the TV.	
Message text size	This setting allows adjusting the text size of the messages associated with a channel or the auxiliary source.	
Top content margin	This setting allows specifying, in %, the top margin between the edge of the TV and the content being played.	
Bottom content margin	This setting allows specifying, in %, the bottom margin between the edge of the TV and the content being played.	
Left content margin	This setting allows specifying, in %, the left margin between the edge of the TV and the content being played.	
Right content margin	This setting allows specifying, in %, the right margin between the edge of the TV and the content being played.	
Initial volume	This setting allows specifying, in %, the initial volume level of the TV.	
Auxiliary source type	This setting allows specifying whether the TV will have an auxiliary source and, if so, what type it will be. The available auxiliary sources depend on the value selected for the “Skin” setting. The possible values for the “Auxiliary source type” setting are: “None”, “Internal storage” (only available for the Smart TV skin), “Disc” (only available for the Smart TV skin), and “VHS” (only available for the retro skins).	

Initial state of the auxiliary source	If there is an auxiliary source that can be inserted and removed (e.g., a disc or a VHS tape), this setting allows specifying whether that source will initially be inside or outside the player.						
Initial state of the VHS player	This setting is only available for the “Retro” skin and allows specifying whether the VHS player will initially be turned on or off.						
Allow fast forward and rewind	This setting allows specifying whether participants will be able to rewind and fast-forward the video associated with the auxiliary source, if any exists.						
Channels	In this section, you can associate videos and messages with the TV channels. For each channel to which you want to associate content, you must specify the following setting: <table border="1"> <tr> <td>Channel number</td><td>It must be an integer greater than or equal to 0 whose number of digits is less than or equal to the value specified in the “Maximum channel number length” setting.</td></tr> </table> In addition, you must also specify one of the following two settings: <table border="1"> <tr> <td>Video</td><td>The URL of the video that will be associated with the channel. This video will be played whenever the channel is accessed. The video must be compatible with HTML5 and use one of the following formats: mp4, webm, or ogg. In addition, the video URL must end with the extension corresponding to the format used (.mp4, .webm, or .ogg).</td></tr> <tr> <td>Message</td><td>The text of the message that will be associated with the channel. This text will be displayed whenever the channel is accessed.</td></tr> </table>	Channel number	It must be an integer greater than or equal to 0 whose number of digits is less than or equal to the value specified in the “Maximum channel number length” setting.	Video	The URL of the video that will be associated with the channel. This video will be played whenever the channel is accessed. The video must be compatible with HTML5 and use one of the following formats: mp4, webm, or ogg. In addition, the video URL must end with the extension corresponding to the format used (.mp4, .webm, or .ogg).	Message	The text of the message that will be associated with the channel. This text will be displayed whenever the channel is accessed.
Channel number	It must be an integer greater than or equal to 0 whose number of digits is less than or equal to the value specified in the “Maximum channel number length” setting.						
Video	The URL of the video that will be associated with the channel. This video will be played whenever the channel is accessed. The video must be compatible with HTML5 and use one of the following formats: mp4, webm, or ogg. In addition, the video URL must end with the extension corresponding to the format used (.mp4, .webm, or .ogg).						
Message	The text of the message that will be associated with the channel. This text will be displayed whenever the channel is accessed.						
Default channel content	This setting allows changing the content that will be displayed by default when accessing a channel that does not have any associated video or message. It is possible to specify either a video or a message in the same way as for channels.						
Auxiliary source content	This setting allows associating content (video or message) with the selected auxiliary source so that it is displayed on the TV when that source is selected by the participants. To do so, you must specify either a video or a message in the same way as for channels.						
Keep TV state	This setting allows preserving the TV state (selected source, volume, auxiliary source state, etc.) when the application is closed. To avoid issues related to automatic video playback in web browsers, the TV will always be turned off when the application starts, even if this setting is enabled.						
Background	This setting allows you to change the default background. You can enter the URL of any image from your resource catalog.						
Solution	You can link the TV to an escape room puzzle and specify a solution for that puzzle. If you do so, participants will be able to complete the puzzle by selecting a specific channel on the TV or by selecting the auxiliary source. Additionally, you can require participants to finish playing a video or to view a message for a certain amount of time in order to complete the puzzle. See the description of the “Action after solving” setting for more details. If participants are required to select a specific channel to solve the puzzle, the solution must consist of the channel digits separated by semicolons. For example, if participants must select channel 1234, the solution should be: 1;2;3;4 On the other hand, if participants must select the auxiliary source to solve the puzzle, the solution must be the following word: <i>input</i>						