

# Raspberry Pi Zero 2 W - Small SPI Screen GPIO Pinout

Viewed from above with Pin 1 at upper-left. All 40 physical header pins are shown; only used screen wires are marked.

## LEFT SIDE / ODD PINS

|    |        |                     |
|----|--------|---------------------|
| 1  | 3.3V   | BROWN / VCC         |
| 3  | GPI02  |                     |
| 5  | GPI03  |                     |
| 7  | GPI04  |                     |
| 9  | GND    | RING WHITE / GND    |
| 11 | GPI017 |                     |
| 13 | GPI027 | WHITE / RST         |
| 15 | GPI022 |                     |
| 17 | 3.3V   |                     |
| 19 | GPI010 | YELLOW / DIN / MOSI |
| 21 | GPI09  |                     |
| 23 | GPI011 | BLUE / CLK / SCLK   |
| 25 | GND    |                     |
| 27 | GPI00  |                     |
| 29 | GPI05  |                     |
| 31 | GPI06  |                     |
| 33 | GPI013 |                     |
| 35 | GPI019 |                     |
| 37 | GPI026 |                     |
| 39 | GND    |                     |

## RIGHT SIDE / EVEN PINS

|    |        |                         |
|----|--------|-------------------------|
| 2  | 5V     |                         |
| 4  | 5V     | RING RED / 5V           |
| 6  | GND    | GRAY / GND              |
| 8  | GPI014 |                         |
| 10 | GPI015 |                         |
| 12 | GPI018 | PURPLE / BL             |
| 14 | GND    |                         |
| 16 | GPI023 |                         |
| 18 | GPI024 |                         |
| 20 | GND    |                         |
| 22 | GPI025 | GREEN / DC              |
| 24 | GPI08  | ORANGE / CS             |
| 26 | GPI07  |                         |
| 28 | GPI01  |                         |
| 30 | GND    |                         |
| 32 | GPI012 | RING GREEN / DATA / DIN |
| 34 | GND    | BUTTON WHITE / GND      |
| 36 | GPI016 | BUTTON RED / GPI016     |
| 38 | GPI020 |                         |
| 40 | GPI021 |                         |

## Screen wires used

|        |           |          |        |           |          |
|--------|-----------|----------|--------|-----------|----------|
| BROWN  | -> Pin 1  | 3.3V/VCC | YELLOW | -> Pin 19 | DIN/MOSI |
| GRAY   | -> Pin 6  | GND      | GREEN  | -> Pin 22 | DC       |
| PURPLE | -> Pin 12 | BL       | BLUE   | -> Pin 23 | CLK/SCLK |
| WHITE  | -> Pin 13 | RST      | ORANGE | -> Pin 24 | CS       |

## Ring light wires added

|       |           |                     |
|-------|-----------|---------------------|
| RED   | -> Pin 4  | 5V                  |
| WHITE | -> Pin 9  | GND                 |
| GREEN | -> Pin 32 | GPI012 / DATA / DIN |

## Button wires added

|                                              |           |        |
|----------------------------------------------|-----------|--------|
| RED                                          | -> Pin 36 | GPI016 |
| WHITE                                        | -> Pin 34 | GND    |
| Note: button wires are not polarity-specific |           |        |