Sea-Bird Electronics, Inc.

13431 NE 20th Street, Bellevue, WA 98005-2010 USA

Phone: (+1) 425-643-9866 Fax (+1) 425-643-9954 Email: seabird@seabird.com

SENSOR SERIAL NUMBER: 1806 CALIBRATION DATE: 05-Feb-14

SBE 37 RTC CALIBRATION DATA ITS-90 TEMPERATURE SCALE

COEFFICIENTS:

rtca0 = 9.999751e-001rtca1 = 1.903507e-006rtca2 = -3.322435e-008

BATH TEMP (ITS-90)	RTC FREO (Hz)	COMPUTED FREO (Hz)	RESIDUAL (PPM)
1.0000	0.9999770	0.9999770	-0.0
4.5000	0.9999830	0.9999830	-0.0
15.0000	0.9999960	0.9999962	0.2
18.5000	0.9999990	0.9999989	-0.1
24.0000	1.0000020	1.0000017	-0.3
29.0000	1.0000020	1.0000024	0.4
32.5000	1.0000020	1.0000019	-0.1

RTC frequency = $rtca0 + rtca1 * t + rtca2 * t^2$

Residual = (Computed RTC frequency - Measured RTC frequency) * 1e6

Date, Delta F ppm

0.00

0.00

11-Dec-12

