# Optimal Stopping Problems

November 20, 2017

These notes expand on Ben Moll's superb notes in http://www.princeton.edu/~moll/HACTproject/on solving option value problems as HJB Variational Inequalities, as discussed Huang and Pang (1998).

## 1 Optimal Stopping of a Univariate, Time-Homogenous Process

This section outlines the general approach to the problems.<sup>1</sup>

### 1.1 Variational Inequality Formulation

To set notation:

- x is a stochastic process, with infinitesimal generator  $\mathcal{A}^2$ .
- An agent with state x can optimally stop with value S(x) at any time.
- The agent gains utility flow u(x) and discounts the future at rate  $\rho > 0$ .

Classical Formulation The typical formulation of this is as a free-boundary value problem. Assume that the agent chooses an optimal  $\hat{x}$  stopping rule, then it will solve the ODE in the continuation region along with value matching and optimal stopping. That is, find a v(x) continuation value and stopping point  $\hat{x}$  that fulfills,<sup>3</sup>

$$\rho v(x) = u(x) + \mathcal{A}v(x) \tag{1}$$

$$v(\hat{x}) = S(\hat{x}) \tag{2}$$

$$v'(\hat{x}) = 0 \tag{3}$$

Additionally another boundary value would be required for either a large  $\bar{x}$  or a transversality condition. This formulation requires that there is only a single stopping point.

**HJB Variational Inequality Formulation** Another formulation is to find a v(x) such that the following holds,

$$0 = \min \{ \rho v(x) - u(x) - \mathcal{A}v(x), v(x) - S(x) \}$$
(4)

for all x (adding an appropriate boundary conditions x). This is a variational inequality since  $\mathcal{A}$  is a differential operator. While the value matching condition is clear here, it can be shown that this implies the smooth pasting condition.

<sup>&</sup>lt;sup>1</sup>See http://www.princeton.edu/~moll/HACTproject/option\_simple.pdf for the simplest case. The algebra expands on http://www.princeton.edu/~moll/HACTproject/HACT\_Numerical\_Appendix.pdf and http://www.princeton.edu/~moll/HACTproject/HACT\_Additional\_Codes.pdf.

<sup>&</sup>lt;sup>2</sup>For example, the infinitesimal generator of the SDE  $dx_t = \mu(x_t)dt + \sigma(x_t)dW_t$  is  $\mathcal{A} \equiv \mu(x)\partial_x + \frac{\sigma(x)^2}{2}\partial_{xx}$ 

<sup>&</sup>lt;sup>3</sup>Note that if anything was a function of time, this would no longer be time-invariant. For example, if S(t,x), then  $\mathcal{A}$  would have a  $\partial_t$  term as well, and  $\hat{x}(t)$  is the stopping rule at any time

#### 1.2 Discretized Problem

For an arbitrary operator  $\mathcal{A}$  with associated boundary values, we will find a solution to (4) by discretizing the  $\mathcal{A}$  operator on a grid  $\{x_i\}_{i=1}^I$  with  $x_1 = \underline{x}$  and  $x_I = \bar{x}$  subject to appropriate boundary values on  $\underline{x}$  and  $\bar{x}$ . See operator\_discretization\_finite\_differences.pdf notes for details on the discretization of operators.

**Linear Operator** In the case of a linear operator  $\mathcal{A}$ , the resulting discretized finite-difference operator is a matrix A. Denote  $v \equiv \{v(x_i)\}_{i=1}^I$ ,  $u \equiv \{u(x_i)\}_{i=1}^I$ , and  $S \equiv \{s(x_i)\}_{i=1}^I$ , then (4) becomes

$$0 = \min \left\{ \rho v - u - Av, \, v - S \right\} \tag{5}$$

where  $A \in \mathbb{R}^{I \times I}$ . A solution to this problem is a v fulfilling (5). Note that the boundary values are already in the A operator and do not need to be discussed separately.

## 1.3 LCP Formulation

Following http://www.princeton.edu/~moll/HACTproject/option\_simple.pdf with only minor variations, we note that (4) is a linear-complementarity problem. Define the following (given the identity matrix  $\mathbf{I} \in \mathbb{R}^{I \times I}$ ),

$$B \equiv \rho \mathbf{I} - A \tag{6}$$

$$z \equiv v - S \tag{7}$$

$$q \equiv -u + BS \tag{8}$$

$$w \equiv Bz + q \tag{9}$$

Substitute (6) to (8) into (5)

$$0 = \min \left\{ Bz + q, z \right\} \tag{10}$$

Which could be written as complementarity slackness conditions,

$$z^{T}(Bz+q) = 0 (11)$$

$$z \ge 0 \tag{12}$$

$$Bz + q > 0 \tag{13}$$

Which can be written succinctly with complementarity constraints as,

$$0 < (Bz + q) \perp z > 0 \tag{14}$$

Alternatively, some LCP and MCP solvers prefer to have a slack variable introduced. Use (9) to find the LCP problem as finding  $w, z \in \mathbb{R}^I$  such that,

$$w \equiv Bz + q \tag{15}$$

$$0 \le w \perp z \ge 0 \tag{16}$$

where (15) is added to the solver with a linear equality constraint.

In either case, to unpack the results, drop any slack variables to get the z vector, and undo the transformation in (7).

## References

Huang, J., and J.-S. Pang (1998): "Option Pricing and Linear Complementarity," in *Journal of Computational Finance*. Citeseer.