

Reference excerpt 02-032

Source: arXiv:1604.05177v1 | License: CC BY 4.0 | Word window: 1177-1436

event T are calculated for each cardiac cycle. These intervals are denoted as: $taR_i = tai - tR_i$
 $taP_i = tai - tP_i$ $txT_i = txi - tT_i$ (3) 2 Table 1: Example of mean value and standard deviation
of main JVP parameters are presented. a x v a t a x t v y HR (cm²) (cm²) (cm²) (cm²) (cm²) (s)
(s) Bpm 1.57 0.18 1.29 0.16 1.33 0.18 0.29 0.04 0.04 0.02 0.33 0.06 0.11 0.05 61 Table 2:
Example of mean value and standard deviation of time intervals $t aR$ and $t xT$ averaged over
several cardiac cycles. taR txT taP (s) (s) (s) 0,03 0,02 0,12 0,06 0.14 0.05 Figure 2: The
figure shows an illustrative JVP trace during a cardiac cycle together with the ECG trace. The
waves a , c , x , v and y of the JVP and the events P , R and T of the ECG are indicated. The
average and the standard deviation of these three parameters is calculated. The mean values
and standard deviations of the parameters taR , txT and taP are presented in Table 2. Figure 3:
Examples of CSA and ECG trace are shown. The waves a , x , v and y are correctly detected by an
algorithm. The P , R and T events of the ECG trace are indicated. Figure 4: Examples of CSA and
ECG trace are shown. The x and v and y are not correctly detected. Correct waves are indicated.
The P , R and T events of the ECG are indicated.