OPERATOR / SAFETY / SENSOR DEVICE SCHEDULE

Tag	Device	Location	PLC / Safety Reference	Cable Group
ES-01	Emergency Stop Mushroom PB	Panel Door	SR-01 Safety Circuit / DWG 006	Door Harness
PB-01	Start Push Button	Panel Door	PLC P01 / TB-IN:02 / DWG 007	Door Harness
PB-02	Normal Stop Push Button	Panel Door	PLC P02 / TB-IN:03 / DWG 007	Door Harness
PB-03	PLC Alarm Reset Push Button	Panel Door	PLC P03 / TB-IN:04 / DWG 007	Door Harness
DR-01	Guard Door Interlock	Machine Guard Door	Safety: DWG 006 / AUX: PLC P07	CG-01
PE-01	Infeed Presence Sensor	Conveyor Infeed	PLC P04 / TB-IN:05	CG-01
PE-02	Test Position Sensor	Test Station	PLC P05 / TB-IN:06	CG-01
PE-03	Outfeed Confirm Sensor	Conveyor Outfeed	PLC P06 / TB-IN:07	CG-01
LS-01	Clamp Closed Feedback	Test Clamp	PLC P08 / TB-IN:09	CG-01
LS-02	PASS Gate Position	PASS Gate	PLC P09 / TB-IN:10	CG-01
LS-03	FAIL Gate Position	FAIL Gate	PLC P0A / TB-IN:11	CG-01
LS-04	RETEST Gate Position	RETEST Gate	PLC P0B / TB-IN:12	CG-01

ACTUATOR / INDICATOR / MOTOR DEVICE SCHEDULE

Tag	Device	Location	PLC Output / Terminal	Power Bus	Cable Group
SOL-01	Test Clamp Solenoid	Test Station	P22 / TB-OUT-ACT:01	+24V_SAFE_ACT	CG-02
SOL-02	PASS Gate Solenoid	PASS Gate	P23 / TB-OUT-ACT:02	+24V_SAFE_ACT	CG-02
SOL-03	FAIL Gate Solenoid	FAIL Gate	P24 / TB-OUT-ACT:03	+24V_SAFE_ACT	CG-02
SOL-04	RETEST Gate Solenoid	RETEST Gate	P25 / TB-OUT-ACT:04	+24V_SAFE_ACT	CG-02
LT-01-G	Tower Lamp Green	Machine Cell Top	P26 / TB-OUT-IND:01	+24V_CTRL_OUT	CG-03
LT-01-Y	Tower Lamp Yellow	Machine Cell Top	P27 / TB-OUT-IND:02	+24V_CTRL_OUT	CG-03
LT-01-R	Tower Lamp Red	Machine Cell Top	P28 / TB-OUT-IND:03	+24V_CTRL_OUT	CG-03
BZ-01	Alarm Buzzer	Machine Cell Top	P29 / TB-OUT-IND:04	+24V_CTRL_OUT	CG-03
MTR-01	Conveyor Motor	Conveyor Drive End	P20 / P21 → MCU-01 / DRV-01 TB-MTR:01 / 02 / 03	+V_MOTOR_SAFE	CG-04

NOTE:
SOL-02, SOL-03, AND SOL-04 ARE MUTUALLY EXCLUSIVE.
ONLY ONE SORT GATE SHALL BE ACTUATED PER SORTING CYCLE.

SOL-01 THROUGH SOL-04 ARE FED FROM +24V_SAFE_ACT.
ACTUATOR POWER IS REMOVED DURING E-STOP CONDITION.

CABLE GROUP SCHEDULE

Cable Group	Cable Function	Connected Devices	Panel Interface
Door Harness	Door Control / Safety Wiring	ES-01 → SR-01 PB-01~PB-03 → TB-IN	SR-01 / TB-IN
CG-00	Main Power Incoming Cable	External Supply → X1	X1
CG-01	Sensor / Guard Field Cable	DR-01, PE-01~PE-03, LS-01~LS-04	TB-24V / TB-0V / TB-IN
CG-02	Actuator / Solenoid Cable	SOL-01~SOL-04	TB-OUT-ACT / TB-0V-ACT
CG-03	Indicator Cable	LT-01-G/Y/R, BZ-01	TB-OUT-IND / TB-0V-IND
CG-04	Motor Cable	MTR-01	TB-MTR
CG-05	Communication Cable	PLC-01 RS-485 ↔ COM-01 RS-485	TB-COM

[GEMERAL NOTE]

[1] CG-05 RS-485 COMMUNICATION CABLE SHALL USE TWISTED PAIR. SHIELD, IF PROVIDED, SHALL BE TERMINATED TO PE-BAR AT PANEL END ONLY.

[2] CG-04 MOTOR CABLE SHALL BE ROUTED SEPARATELY FROM CG-01 SENSOR AND CG-05 COMMUNICATION CABLES.

NO.	DATE	REVISION
A	2026-09-07	INITIAL RELEASE

DWG TITLE

EDS Wafer Map Linked Package
Final Test and Multi-Bin Sorting Cell

FIELD DEVICE AND CABLE SCHEDULE

DRAWN BY: J. H. KO
DATE: 2026-09-07
DWG NO: 010
SHEET NO: 1 OF 1