HMI-01 LABVIEW SCADA SCREEN WIREFRAME CONCEPTUAL FRONT PANEL DESIGN SEE DWG 015 / SHEET 1 OF 3 AND SHEET 2 OF 3

A. HMI MANUAL / SETUP SCREEN

HMI-01
MANUAL / SETUP

MAIN | AUTO | MANUAL | ALARM | TREND | SETTINGS

MANUAL MODE STATUS

CURRENT MODE: AUTO / MANUAL
M0010 / M0011

MODE SELECT REQUEST
D0053
0 = AUTO
1 = MANUAL

AUTO MODE | MANUAL MODE

MODE CHANGE ENABLED ONLY WHEN:
SAFETY READY + NO FAULT + S10 READY / IDLE
MODE CHANGE SHALL BE INHIBITED
DURING ACTIVE AUTO CYCLE.

PRODUCTION COUNT RESET

RESET COUNTS

M0204
HMI_COUNT_RESET_REQUEST

MANUAL MODE + HMI CONFIRMATION REQUIRED
COUNT RESET SHALL NOT BE PERMITTED
DURING AUTO CYCLE OR FAULT RESET PROCESS.

SETPOINT ENTRY

CURRENT MODE
D0050
0 ~ 4000 mm
PLC RANGE CHECK REQUIRED

PROXIMITY THRESHOLD
D0054
0 ~ 255
PLC CLAMP: 0~255

MOTOR SPEED SETPOINT
D0051
0 ~ 100 %
PLC CLAMP: 0~100 %

MODE SELECT
D0053
AUTO / MANUAL
PLC VALIDATED MODE REQUEST

PROCESS / VIBRATION THRESHOLD
D0052
ENGINEERING VALUE
PLC RANGE CHECK REQUIRED

ALL SETPOINTS SHALL BE WRITTEN AS HMI REQUESTS.
PLC-01 SHALL VALIDATE RANGE, MODE, SAFETY, AND STATE.

MANUAL COMMAND STATUS
MANUAL OUTPUT COMMANDS
RESERVED FOR PLC VALIDATED FUNCTION
NO DIRECT WRITE TO P20~P29

PLC OUTPUT INTERLOCK:
SEE DWG 011 / SHEET 2 OF 2
AND DWG 013 / SHEET 4 OF 4.

HMI TAG / COMMAND / SETPOINT MAP:
SEE DWG 015 / SHEET 2 OF 3.

B. HMI ALARM / HISTORY SCREEN

HMI-01
ALARM / HISTORY

MAIN | AUTO | MANUAL | ALARM | TREND | SETTINGS

ACTIVE ALARM
ALM-103
TEST COMPLETE TIMEOUT
D0310 / M0120
NO ACTIVE ALARM WHEN D0310 = 0 AND M0120 = OFF

ALARM SUMMARY

ALARM CODE
ALM-103

ALARM DESCRIPTION
TEST COMPLETE...

RESET STATUS
ACTIVE

OCCURRED TIME
YYYY- ... :SS

ACTIVE DURATION
HH:MM:SS

ALARM COMMAND

ACKNOWLEDGE
M0203
HMI_ALARM_ACKNOWLEDGE
ACKNOWLEDGE DOES NOT RESET FAULT

ALARM RESET
M0202
HMI_ALARM_RESET_REQUEST
RESET ENABLED WHEN:
SAFETY READY + FAULT CAUSE CLEARED

ALARM RESET DOES NOT BYPASS HARDWIRED SAFETY FUNCTION.

ALARM HISTORY TABLE ALM-001 / ALM-101~ALM-108 SEE DWG 012.

TIME STAMP	ALARM CODE	DESCRIPTION	STATE	RESET TIME	ACK STATUS
YYYY-MM-DD HH:MM	ALM-103	TEST COMPLETE...	ACTIVE	--	ACK

HISTORY FILTER / EXPORT HMI EVENT LOG: CSV / TDMS FILTERED HISTORY EXPORT: CSV

DATE RANGE	ALARM CODE	ACTIVE / RESET	ACK STATUS
FROM YYYY-MM-DD TO YYYY-MM-DD	ALL	ACTIVE	ACK

APPLY FILTER | CLEAR FILTER | EXPORT CSV

ALARM / HISTORY / DATA LOGGING MAP:
SEE DWG 015 / SHEET 3 OF 3.

HMI COMMANDS SHALL BE PROCESSED AS PLC REQUESTS ONLY.
HMI-01 SHALL NOT DIRECTLY WRITE PLC OUTPUTS P20~P29.

NO.	DATE	REVISION
A	2026-09-18	INITIAL RELEASE

DWG TITLE
EDS Wafer Map Linked Package
Final Test and Multi-Bin Sorting Cell
SCADA HMI MANUAL / SETUP / ALARM HISTORY SCREEN WIREFRAME

DRAWN BY: J. H. KO
DATE: 2026-09-18
DWG NO: 016
SHEET NO: 2 OF 3