Test category	Type Test		
Type	KBN426_16S_WE_G3	**Test Method**	SNI IEC 60884-1: 2014
Ranking	16A 250V~	**Job Order No.**	WO/25110104
Test Date	28/11/2025	**Request No.**	R/25110104
Room Temp.	24	**Sample code**	A
Humidity	57	**Test Equipment No.**	QE/14/PH/56

Clause	Test requirements	Check up result	Decision
21	**NORMAL OPERATION**		**PASSED**
	The accessories shall withstand without excessive wear or other harmful effects the mechanical, electrical and thermal stresses occurring in normal use.	Fixed accessories are resistant tomechanical, electrical and thermal stressin normal use	L
	Compliance is checked by testing the socket outlet, and the plug with a springloaded earthing socket contact or with a non-solid pin.		
	Test conditions:		
	- the plug is inserted into and removed from the socket 5000 times (10000 operating steps); operating rate;	10000 ; 30 operations per minute	
	- test voltage (V);	250V	
	- test current (A); cos ϕ = 0.8 ± 0.05;	16A; cos ϕ 0.83	
	- the period during which the test current flows from insertion to removal of the plug;	1.8 seconds / 3.3 seconds	
	During the test no continuous arcing shall occur.	Unsustainable arc	
	After testing, the specimen should not show:		
	- wear that interferes with further use;	Fulfil	
	- deterioration of the enclosure, insulation layer or barrier;	Fulfil	
	- loose mechanical or electrical connections;	Fulfil	
	- release of the sealing compound For covered contact boxes the gauge as per figure 9 is applied to the inlet connected to the active contact with a force up to 20 N. It is not possible to touch live parts with the test gauge while they remain under the relevant force.	-	
	Then the contact box with the measuring cover as shown in figure 10 is applied with a force of 1 N. It is not possible to touch live parts with the test gauge while they remain under the relevant force.	-	
	Contact Box: temperature rise test (as per clause 19 requirements)		
	The temperature rise should not exceed 45 K (K)	A B C	
		< 45 < 45 < 45	
	Phase contact (K)		

	Neutral contact (K)				
	Earth contact (K)				
	For the purposes of test 25.3, the temperature rise of the external parts of the insulating material need not hold the current-carrying parts and the earthing circuit parts in position (K)				
	Contact Plug: temperature rise test (as per clause 19 requirements)				
	The temperature rise should not exceed 45 K (K)	A	B	C	
		< 45	< 45	< 45	
	Phase contact (K)				
	Neutral contact (K)				
	Earth contact (K)				
	For the purposes of test 25.3, the temperature rise of the external parts of the insulating material need not hold the current-carrying parts and the earthing circuit parts in position (K)				
	A voltage with a sine waveform, having a frequency of 50 Hz or 60 Hz, is applied for 1 minute with the test voltage reduced to 1500 V for equipment having a rated voltage of 250 V and to 1000 V for equipment having a rated voltage of 130 V				
	a) Test voltage 1000 V / Test voltage 1500 V	No breakdown			
	b) Test voltage 1000 V / Test voltage 1500 V	No breakdown			
	c) Test voltage 1000 V / Test voltage 1500 V	-			
	d) Test voltage 1000 V / Test voltage 1500 V	-			
	e) Test voltage 1000 V / Test voltage 1500 V	-			
	Fixed socket outlet: test according to clause 13.2	-The contact box assembly is not having damaged			
	Portable socket-outlets and socket-outlets; testing according to clause 14.2	-			

Test case decision description:

- Testing meets requirements : Pass (L)
- Testing does not meet requirements : Not Passed (TL)
- Testing does not apply to test objects : Not applicable (TB)

PT Qualis Indonesia	Witnessed by		
	Name	Company	Signature

Tested by:			
Checked by:			