

NO.4 E/R VENT. FAN (REV) — Start / Run / Stop & Fault Flow

HI-2536-ME-SD1/SD2 · SMC-503H · Printable one-page guide · Field readings included

START → RUN → STOP SEQUENCE

1 PRE-START

52 ON · SOURCE ON · ABNORMAL OFF · Amp ≈ 0

2 PRESS SUPPLY (or EXHAUST)

SMC 4F/4R ON · HEATING OFF · 88SH open

3 REDUCED-VOLTAGE START

6-1 / 6-2 + ATr · limit inrush

4 TIMER 19 ≈ 30 s

Transfer start → full voltage

5 FULL-VOLTAGE RUN

88F or 88R · 4FX/4RX feedback to SMC

6 MONITOR

Door A · EOCR A · lamps · load

7 NORMAL STOP

STOP → contactors open → HEATING ON

YOUR FIELD OBSERVATIONS (filled)

After stop lamps

SOURCE ON · ABNORMAL OFF · INTERVAL OFF · HEATING ON

Door ammeter (running)

~ 63 A (FLA = 65.4 A) → looks normal

EOCR measured current

3.7 A secondary (> SET'G 3.27 A)

EOCR SET'G (drawing)

3.27 A · CHA=INV · D-TIME 6 s · O-TIME 10 s

88F

Already renewed — stop still occurs

Lamp test

All lamps OK (ABNORMAL lamp works)

Interpretation

Looks like NORMAL/command stop OR EOCR quiet trip
Resolve 63 A vs EOCR 3.7 A with clamp meter

WHEN IT STOPS — DECISION FLOW

IF ABNORMAL = ON

1. Check EOCR for TRIP / OL
2. Clamp all 3 motor phases
3. If clamp high → load / fan mech.
4. If clamp ~63 A but EOCR 3.7
→ CT / EOCR false reading
5. Do NOT only raise SET'G
6. Reset only after cause found

IF ABNORMAL = OFF (your case)

1. Note: HEATING ON = clean stop
2. Watch which dies first:
 - SUPPLY lamp first → SMC/STOP/remote
 - Amp→0 while RUN lit → power side
3. Retest in LOCAL only
4. Check STOP NC contact (heat/intermittent)
5. Check SMC 4F seal-in & GSP2 remote
6. Still check EOCR vs clamp (3.7 vs 63)