

Sun charger, electrical charger, USB charger, adaptor/transformator, rechargeable products

Produit : Electronic / Measuring devices

Legal manager : DLUBALA JULIEN

Updated at : 26/03/2025 10:24:58

Downloaded at : 27/03/2026 12:24:49

CHINA

Product's definition

Category

In which category the product is classified ?

Products covered: sun charger, electrical charger, adapter/transformator.

Definition

What is the exact definition of the product ?

And if it exists, what is the interpretation of the authorities regarding it ?

Definition of electrical and electronic products

Electrical and electronic products means the equipment and supporting products that work by relying on electric currents or electromagnetic fields or are manufactured for the purpose of generating, transmission and measuring electric currents and electromagnetic fields, with the rated working voltage of not more than 1,500 volts measured in direct current or not more than 1,000 volts measured in alternating current, excluding the equipment involving electrical energy production, transmission and distribution. (Administrative Measures for Restricted Use of the Hazardous Substances Contained in Electrical and Electronic Products)

Accordingly, most of the products involved in this section basically meet the definition of electrical and electronic products.

Definition of mechanical and electrical products

The term “mechanical and electrical products” refers to the mechanical equipment, electric equipment, transport tools, electronic products, electrical appliances, apparatus, instruments, metal products, and the parts and components and elements thereof. (Article 2 of Administrative Measures for Import of Mechanical and Electrical Products)

The specific scope of mechanical and electrical products is stipulated in the appendix of the “Administrative Measures for Import of Mechanical and Electrical Products”, which covers a wide range, including electrical and electronic products, instruments and meters, various luminaries and lighting devices, clocks and watches and their parts.

Among them, the import of some mechanical and electrical products is subject to automatic licensing management. The specific product scope is stipulated in the “Automatic Import License Mechanical and Electrical Products Catalog”, including other product categories such as other electronic watches directed mechanically.

Products that require 3C certification

Definition of low-power motors requiring compulsory certification

- Suitable for driving low-power motors with rated voltage greater than 36V (DC or AC rms) and less than 1500V DC and 1000V AC, including:
 - 1. When the speed is converted to 1500r/min, various AC asynchronous motors and AC synchronous motors whose maximum continuous rating does not exceed 1.1kW (rated power $\leq$ synchronous speed $\times$ 1.1kW/1500);
 2. AC commutator motors and DC motors whose maximum continuous rating does not exceed 1.1kW.
- Do not include:
 - 1. Motors for control purposes (such as servo motors, stepping motors, self-aligning machines, resolvers, tachogenerators, induction phase shifters, etc.)
 2. Multi-voltage and multi-speed motor whose one type of rating is beyond the above applicable range.

Definition of plug products requiring compulsory certification

- Plug and fixed, mobile socket suitable for indoor or outdoor use, household and similar purposes, only for alternating current, rated voltage above 50V but not more than 440V, rated current not more than 32A, with or without grounding angle;
- It is also applicable to plugs installed in wire assemblies and plugs and mobile sockets installed in wire extension assemblies, as well as plugs and sockets as a component of electrical appliances, unless otherwise stated in the relevant electrical standards;
- It is also applicable to sockets integrated with the appliance and installed in or fixed to the appliance;
- For fixed sockets equipped with screwless terminals, the maximum rated current is limited to 16A.

Definition of circuit breakers requiring compulsory certification

- A mechanical switching device that can connect, carry and break the current under normal circuit conditions, and could also connect and carry current for a certain period of time and breaking current under specified abnormal conditions (such as short-circuit conditions)

Definition of fuse links and low-voltage fuses requiring compulsory certification

Fuse link

When the current passing through the component exceeds the specified value and lasts for a sufficient time, the component fuses, disconnecting the circuit to which it is connected, thereby cutting off the current. And, a non-resettable device equipped with a thermal element would break the circuit when it is exposed to a temperature exceeding the designed temperature for a long enough time.

Low-voltage fuse

"gG" fuse for household and similar purposes, which is suitable for unskilled persons whose rated current does not exceed 100A and rated voltage does not exceed 500V AC.

Definition of switch products (belonging to low-voltage components) requiring compulsory certification:

- According to external signals and requirements, the circuit could be manually or automatically connected and disconnected to realize the switching, control, protection, detection, transformation and adjustment of the circuit or non-electric objects.

Products such as motors, circuit breakers, fuses, switches, plugs/power supplies, etc. sold by your company may belong to the above product categories, which need to be judged based on product parameters.

Comments

Comments

Labelling

Language

In which language must the information on the product or on the packaging be indicated? If English is sufficient please indicate NA.

Must use Chinese language.

Mandatory labelling on product

What are the mandatory labelling on the product ?

Regulatory requirements for

product labeling

- The producers and importers of electrical and electronic products shall, in accordance with the national or industrial standards for the marking of the restricted use of the hazardous substances contained in electrical and electronic products, mark the hazardous substances contained in the electrical and electronic products they put on markets, and indicate the names and contents of hazardous substances or whether the elements or products which contain such substances may be recycled, the fact that improper use or disposal thereof may affect the environment or human health and other information. Where the aforesaid information cannot be marked on the products due to the restrictions in product volume, shape, surface materials or functions, it shall be indicated in the product manuals.
- The producers and importers of electrical and electronic products shall, in accordance with the national or industrial standards for the marking of the restricted use of the hazardous substances contained in electrical and electronic products, indicate the EFUP on the electrical and electronic products they produce or import. Where the aforesaid information cannot be marked on the products due to the restrictions in product volume, shape, surface materials or functions, it shall be indicated in the product manuals.

General requirements

General Requirements of Labeling

- | | |
|---|---|
| 1 | All necessary information concerning the proper and safe use and (or) related service and maintenance of the products shall be included |
| 2 | Clear and easy to be identified, the smallest English letter shall not be less than 1.5 mm |
| 3 | Must use Chinese language |
| 4 | The contents shall be the same with that contained in other printed materials (such as advertisement and package) |

Content of Labeling and Instruction for Use

- | | |
|----|--|
| 1 | Product summarizes (product name, variety, specifications, model, the main purpose and working conditions, etc.) |
| 2 | Precautions for safe use |
| 3 | Structural characteristics and working principle |
| 4 | Technical characteristics |
| 5 | Size, weight |
| 6 | Installation and adjustment |
| 7 | Use and operation |
| 8 | Malfunction analysis and exclusion |
| 9 | Safety protection device and incident handling |
| 10 | Maintenance and repair |
| 11 | Transport and storage |
| 12 | Unpacking and inspection |
| 13 | Environmental or other requirements |
| 14 | Graphs, charts, photographs (eg outline drawings, installation drawings, schematics, etc.) |

Labeling requirement of charge:

Labeling Requirement of Charge

1	Rated voltage/ Rated voltage range
2	Symbols of the nature of supply
3	Rated power input

4	Name, trademark or identification mark of the manufacturer or the liability underwriter
5	Model or serial number
6	IP code of Waterproof grade
7	Rated d.c. output voltage
8	Rated d.c. output current
9	Rated current of the protection device installed in the d.c. distribution board
10	The time of delay fuses
11	Others

Standards on labeling requirements of general household battery charger:

- 1) rated voltage/rated voltage range
- 2) symbols of the nature of supply

- | | |
|-----|---|
| 3) | rated power input |
| 4) | name of the manufacturer of the liability underwriter |
| 5) | trademark or identification mark |
| 6) | model or serial number |
| 7) | symbol 5712 of GB/T5465.2 ¹ idt IEC 60417 ¹ only marked on classâ... ² |
| 8) | IP code of waterproof grade |
| 9) | rated dc.output voltage |
| 10) | rated d.c. output current |
| 11) | rated current of the protection device installed in the d.c. distribution board |
| 12) | polarity of the output end |
| 13) | the time of delay fuses, and others |

Standards on labeling requirements of the charger for lithium-ion batteries of cellular phones:

- | | |
|----|---|
| 1) | name of manufacturer |
| 2) | model |
| 3) | product name |
| 4) | voltage and current input |
| 5) | frequency input |
| 6) | voltage and current output |
| 7) | polarity (For the device directly charge the lithium-ion battery) |
| 8) | warning and others |

Labeling requirement of adapter:

Labeling Requirements of Adapter

- | | |
|---|---------------------------------------|
| 1 | Name or trademark of the manufacturer |
| 2 | Model mark or other mark |

3	Standard number
4	Symbol of the voltage, supply power nature and power terminal

Standards on labeling requirements of Power Adapter of Mobile Telecommunication Terminal Equipment

- | | |
|----|--|
| 1. | rated input/output voltage |
| 1. | rated input/output current |
| 1. | rated frequency |
| 1. | symbol of output power |
| 1. | name or trademark or identification mark of the manufacturer |
| 1. | Model |
| 1. | symbol of “P” |
| 1. | Identification mark of general Power Adapter of Mobile Telecommunication Terminal Equipment. |
| 1. | CCC certificate |
| 1. | Other labeling of electronic information products, such as the labeling required in SJT11363-2006 and SJT11364-2006 listed in question1. |

3.1 Marking

3.1.1 General requirements

Traceable parts of the product should be clearly and permanently marked with traceable feature symbols such as the manufacturer's name or trademark, model specification, date of manufacture or code.

3.1.2Charger marking

The following should be clearly marked on the body of the charger:

- a Rated input voltage and rated frequency;
- b Maximum input current
- c Output voltage;
- d Output current
- e The name of the manufacturer or manufacturer
- f The model of the charger, the type of battery required to be charged, the specification, and the voltage level;
- g If it is a type II structure, it should be marked with a symbol;
- h Output terminal polarity (+, -)
- i Indicate the warning sign: Read the instructions for use thoroughly before use.

3.1.3 Others

In the contract environment, it can be marked on demand.

Mandatory labelling on packaging

What are the mandatory labelling on the packaging ?

GB/T 36944-2018 Technical requirements of charger for electric bicycles

3.3Package

3.3.1Factory products should be accompanied by product certificate, packing list, product description information.

3.3.2 Each product should be packaged in a single small package, in a carton or other box, and bundled securely. Special circumstances can be determined according to the requirements of the purchaser (contract).

Mandatory labelling on the instructions manual

What are the mandatory labelling on the instructions manual (if one is required) ? In which format, do we have to deliver the instruction manual to our customers ?

GB/T 36944-2018 Technical requirements of charger for electric bicycles

3.2 Instruction manual

3.2.1 Overview

Instructions should be provided with the charger and should have, but are not limited to, the following:

a Warning: Do not charge non-rechargeable batteries

b During charging, the charger must not be covered and should be placed in a well-ventilated area. Beware of flames, sparks and explosive gases

c If the power cord is damaged, it should be replaced by the manufacturer or its service department or a similarly qualified person to avoid danger.

3.2.2 Conditions of Use

The conditions of use should meet the following requirements:

a Ambient temperature: $-20^{\circ}\text{C} \sim +55^{\circ}\text{C}$;

b Relative humidity: no more than 95%;

c Atmospheric pressure: 86kPa~106kpa

Warnings - General ones

Are general warnings required ? If yes, which ones ?

Warnings - Specific ones

Are specific warnings required ? If yes which ones ?

Target Age

Is there any target age applicable? If so, does it have to be indicated and in which form?

Sanctions / Fines

What are the sanctions / fines in case of non conformity ?

Comments

Comments

Environment

Recycling - Eco taxes

Which regulations concerning ecodesign and recycling apply to this product? Are there any ecotaxes applicable to this category of product?

Regulatory requirements for electrical and electronic product

Regulatory requirements for

product design

The designers of electrical and electronic products may not violate the compulsory standards or the standards that must be implemented as prescribed by laws, administrative regulations and rules in the process of designing electrical and electronic products, and shall, on the premise of satisfying the technological requirements, adopt the schemes for making the said substances harmless, less harmful, easy to be degraded or convenient for being recycled, among others, in accordance with the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products,

Product production supervision requirements

- The manufacturers of electrical and electronic products may not violate the compulsory standards or the standards that must be implemented as prescribed by laws, administrative regulations and rules in the process of manufacturing electrical and electronic products, and shall, in accordance with the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products, adopt the materials, technologies and technological processes with higher resource utilization rates, easy to be recycled and disposed of and conducive to environmental protection, and restrict or eliminate the use of the hazardous substances in products.
- The manufacturers of electrical and electronic products may not allow the electrical and electronic products that fail to comply with the requirements of these Measures to leave factories or be sold.

regulatory requirements for packaging

The manufacturers and importers of electrical and electronic products may not violate the compulsory standards or the standards that must be implemented as prescribed by laws, administrative regulations and rules when making and using the packages of electrical and electronic products, and shall adopt the materials harmless, easy to be degraded and convenient for being recycled, and comply with the national or industrial standards for the use of packages.

Regulatory requirements stipulated in Administrative Measures for Prevention and Control of Environmental Pollution by Electronic Waste

Regulatory requirements for

product production

The producers of electrical and electronic products may in accordance with the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products, restrict or eliminate the use of the hazardous substances in products.

Regulatory requirements for information disclosure

Producers, importers and sellers of electronic and electrical products shall disclose the lead, mercury, cadmium, hexavalent chromium, polybrominated biphenyls (PBB), polybrominated diphenyl ethers (PBDE) and other toxic and hazardous substances contained in their products in accordance with relevant national regulations. As well as information on the impact of improper use or disposal on the environment and human health, and tips on how to use or dispose of the product in an environmentally sound manner after it is discarded.

Recycling and disposal regulatory requirements

- Producers, importers and sellers of electronic and electrical products shall establish a recycling system in accordance with relevant national regulations, recycle waste products, and be responsible for storage, utilization or disposal in an environmentally sound manner;
- If the producers, sellers and importers of electronic products discard electronic and electrical products, they shall provide or entrust the electronic wastes to the dismantling, utilization and disposal units (including individual industrial and commercial households) with corresponding business scope listed in the directory (including the temporary directory) for dismantling, utilization or disposal.

Labelling

What are the mandatory labellings to put on the product or on the packaging regarding the environmental rules ?

Technical rules / Standards

General safety requirements

What are the general safety requirements ? Does a risk assessment have to be conducted ? If yes, does it concern specific risk ?

Mandatory or voluntary standards

Are there some mandatory or voluntary standards applicable ? If yes, which ones ?

Please indicate the reference of the applicable standards

Regard to your products, if you want to check what are the technical requirement /toxicology/design... shall respect, thanks to check the labelling of your product first and find code of standards in labelling.

Step 1:

Enter this link: https://docs.google.com/spreadsheets/d/1BDqhm609YySgDqs8cPOQUd-Dc_ZYPEEt7v-lv1sWB0CA/edit#gid=1640363751

Step 2:

Enter the code of product standard selected by you in PACE and open the link in red.

Enter the code of mandatory safety standard above.

Step3:

Open link and find documents of standard, your products shall respect all requirements in file.

PS: If you can't find the translation file in link above, please do not hesitate to contact with CHINA Conformity Leader by mail "chinadmilegal@decathlon.net".

Physical and mechanicals properties

What are the physical and mechanicals properties required ?

2.2 Mechanical behavior

2.2.1 Mechanical strength

2.2.1.1 Shell shock

After the shell shock test according to the specified method, the charger shall comply with the requirements of 21.1 of GB 4706.1-2005.

2.2.1.2 Drop

After the drop test is carried out according to the prescribed method, the charger shall comply with the requirements of 21.101 of GB 4706.18-2014.

2.2.2 Vibration

After the vibration test according to the specified method, the charger should meet the following requirements:

- a Each related electrical device has no abnormal phenomena such as deformation;
- b Meet the requirements of 5.3.2;
- c Can work normally

Electrical aspects

What are requirements regarding electrical aspects ?

Inflammability

Are there any specific requirements to ensure inflammability?

Hygiene

What are the rules regarding hygiene ?

Radioactivity

What are the rules regarding radioactivity ?

Radiofrequency (2G,3G,4G,5G, Bluetooth, Ant+, GPS, Wifi...)

What are the rules regarding the radiofrequency?

Products making noise

What are the requirements regarding products making noise ?

Chemicals substances

What are the requirements regarding chemicals substances ? Which ones are forbidden ? Limited ? Do we have to clearly indicate all substances that are in the product, or is the indication of major substances enough?"

Packaging requirements

Can you please indicate if there are some requirements regarding the packaging of our products (mainly they are in paper, carton, plastic, textile) ? If yes, please explain them.

GB/T 36944-2018 Technical requirements of charger for electric bicycles

3.3Package

3.3.1Factory products should be accompanied by product certificate, packing list, product description information.

3.3.2 Each product should be packaged in a single small package, in a carton or other box, and bundled securely. Special circumstances can be determined according to the requirements of the purchaser (contract).

Laboratory

In which laboratory can we perform the testing of the product according to the standard?

Sanctions / Fines

What are the sanctions / fines in case of non conformity ?

Comments

Comments

Certifications / Registrations

Certifications or registrations

Are there some certifications or registrations applicable to the product ?

Products that require 3C certification

Definition of low-power motors requiring compulsory certification

- Suitable for driving low-power motors with rated voltage greater than 36V (DC or AC rms) and less than 1500V DC and 1000V AC, including:
 - 1. When the speed is converted to 1500r/min, various AC asynchronous motors and AC synchronous motors whose maximum continuous rating does not exceed 1.1kW (rated power d synchronous speed x 1.1kW/1500);
 2. AC commutator motors and DC motors whose maximum continuous rating does not exceed 1.1kW.
- Do not include:
 - 1. Motors for control purposes (such as servo motors, stepping motors, self-aligning machines, resolvers, tacho-generators, induction phase shifters, etc.)
 2. Multi-voltage and multi-speed motor whose one type of rating is beyond the above applicable range.

Definition of plug products requiring compulsory certification

- Plug and fixed, mobile socket suitable for indoor or outdoor use, household and similar purposes, only for alternating current, rated voltage above 50V but not more than 440V, rated current not more than 32A, with or without grounding angle;
- It is also applicable to plugs installed in wire assemblies and plugs and mobile sockets installed in wire extension assemblies, as well as plugs and sockets as a component of electrical appliances, unless otherwise stated in the relevant electrical standards;
- It is also applicable to sockets integrated with the appliance and installed in or fixed to the appliance;
- For fixed sockets equipped with screwless terminals, the maximum rated current is limited to 16A.

Definition of circuit breakers requiring compulsory certification

- A mechanical switching device that can connect, carry and break the current under normal circuit conditions, and could also connect and carry current for a certain period of time and breaking current under specified abnormal conditions (such as short-circuit conditions)

Definition of fuse links and low-voltage fuses requiring compulsory certification

Fuse link

When the current passing through the component exceeds the specified value and lasts for a sufficient time, the component fuses, disconnecting the circuit to which it is connected, thereby cutting off the current. And, a non-resettable device equipped with a thermal element would break the circuit when it is exposed to a temperature exceeding the designed temperature for a long enough time.

Low-voltage fuse

"gG" fuse for household and similar purposes, which is suitable for unskilled persons whose rated current does not exceed 100A and rated voltage does not exceed 500V AC.

Definition of switch products (belonging to low-voltage components) requiring compulsory certification:

- According to external signals and requirements, the circuit could be manually or automatically connected and disconnected to realize the switching, control, protection, detection, transformation and adjustment of the circuit or non-electric objects.

Products such as motors, circuit breakers, fuses, switches, plugs/power supplies, etc. sold by your company may belong to the above product categories, which need to be judged based on product parameters.

Compulsory product certification regulatory requirements

- Switches (belonging to low-voltage components), circuit breakers, low-power motors, fuses, low-voltage fuses and plugs have compulsory certification requirements.
- According to CNCA-C02-01: 2014 Implementation Rules for Compulsory Product Certification Circuit Switches and Electrical Devices for Protection or Connection (Electrical Accessories), the following certification rules apply to plugs:

The principle of dividing certification units for plugs and sockets for household or similar use is: dividing certification units according to product grades, detachable and non-detachable wires, terminal types, etc.

The basic certification mode of certification is: type test + post-certification supervision.

- The certification institution shall formulate a type test plan after the data review, and inform the certification client. The type test plan includes all the sample requirements and quantities for the type test, test standard items, laboratory information, etc.;
- In principle, the type test items shall include all applicable items specified in the product safety standards;
- In principle, the type test shall be completed in the laboratory designated by CNCA.

Post-certification supervision refers to one of the three methods: follow-up inspection after certification, sample testing or inspection at the production site, and market (and/or user) sample testing or inspection.

- According to CNCA-00C-008: 2019 Self-declaration of Implementation Rules for Compulsory Product Certification, the following rules apply to compulsory certification of switches (which belong to low-voltage components), low-power motors, fuses, low-voltage fuses and circuit breakers:

Basic requirements of self-declaration procedure

- Producers (manufacturers) aim at ensuring that their self-declared products continuously meet the applicable standards of compulsory product certification, and implement internal quality control and establish factory quality assurance system according to product characteristics and production and processing characteristics.
- The producer (manufacturer) selects an appropriate type of conformity assessment method to evaluate the conformity of the product, and proves that the product continuously meets the requirements of applicable standards for compulsory product certification.
- The producer establishes technical documents and keeps them properly; since the date of completing the submission of product compliance information, they shall be kept for at least 10 years for future reference.
- The authorized representative of the producer (manufacturer) signs the “Compulsory Certification Product Conformity Self-Declaration” for the qualified products and completes the submission of product conformity information.
- Producers (manufacturers) add CCC marks to their self-declared products.
- When the product design, technical characteristics, relevant compulsory product certification requirements or self-declaration related information are changed, the producer (manufacturer) and authorized representative (if applicable) shall supplement and evaluate the product compliance and update the self-declaration and product compliance information according to the changed content.

Conformity assessment methods applicable to self-declaration procedures

The applicable conformity assessment methods of self-declaration procedure B are as follows: (All products such as low-power motors involved in this part are subject to self-declaration procedure B)

- The type test shall be conducted by the laboratory designated by the corresponding business scope of compulsory product certification (i.e. designated laboratory) and a type test report shall be issued, and the manufacturer (manufacturer) shall organize self-inspection of its factory quality assurance ability and issue a self-inspection report.
- Or, the producer (manufacturer) independently chooses the certification institution to voluntarily certify its products. Among them, the certification institution shall meet the requirements of the following certification institution: the certification process shall at least include type testing and factory inspection; the laboratory conducting the type test shall be a designated laboratory.

Certification institution requirements

- The certification institution shall be established in accordance with the law, comply with the “Requirements for the Management Measures of Certification Institution”, and possess certification qualifications in the corresponding fields.
- Certification institutions shall meet the requirements of GB/T 27065 (or ISO/IEC 17065) standards, and CNAS (or ILAC member institutions) accreditation is encouraged to be obtained.

Submitting compliance information

Producers (manufacturers), laboratories and certification institutions involved in self-declaration shall register in the “Self-declaration Information Submission System for Compulsory Certification of Product Compliance” (hereinafter referred to as the system), and submit relevant organization information and qualification documents.

If the producer (manufacturer) entrusts the design and production of the product in the ODM mode, it shall submit the following compliance information:

a Self-declared product information;

b Standard information that the product complies with;

c Initial self-declaration information;

d ODM agreement among the producer (manufacturer), the ODM initial self-declaration producer (manufacturer) and the production enterprise;

e The manufacturer (manufacturer) and the ODM initial self-declaration agreement between the producer (manufacturer) and the manufacturer on self-declaration and product quality and safety responsibilities;

f ODM product nameplate (external mark);

g Other documents related to product compliance.

After the compliance information above is submitted, the system would automatically generate the “Compulsory Certification Product Compliance Self-Declaration” based on the submitted information. The signer designated by the producer (manufacturer) and authorized representative (if applicable) signs and uploads the system to complete the self-declaration submission.

Laboratory

In case of mandatory certification/ registration that we must follow please precise the name and address of any laboratories where we can conduct them

Comments

Comments

Conformity documents

Documents

What are the conformity documents ? Can you please list them ?

Format

Does it exist a specific format for the conformity documents ? If yes, can you please provide us an example in english ?

Comments

Importation rules

General rules

What are the general rules in order to import the product ?

Regulatory requirements for electrical and electronic product

Regulatory requirements for product import

- The electrical and electronic products imported may not violate the compulsory standards or the standards that must be implemented as prescribed by laws, administrative regulations and rules, and shall comply with the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products.
- The entry-exit inspection and quarantine institutions shall conduct port verification and statutory inspection of the electrical and electronic products imported. The Customs shall verify the Customs Clearance Form for Goods Entering China issued by entry-exit inspection and quarantine institutions and undergo the customs clearance formalities under the relevant provisions.

Regulatory requirements for import of mechanical and electrical products

The regulatory requirements for the import of mechanical and electrical products are mainly stipulated in Administrative Measures for Import of Mechanical and Electrical Products and Implementation Measures of Automatic Import License for Mechanical and Electrical Products and other regulations. Since it has not been retrieved that your company sells products listed in the Catalog of Restricted Imports of Mechanical and Electrical Products and Electrical Products or the Catalog of Mechanical and Electrical Products Prohibited from Importing, this section is mainly aimed at the mechanical and electrical products listed in Automatic Import License Mechanical and Electrical Products Catalog, which are classified as product with automatic import license.

General regulatory requirements

- To import mechanical and electrical products with automatic import license, the import entity shall file an application with the Ministry of Commerce or its authorized institution for an Automatic Import License before it goes through the customs formalities.

Application requirements

- The import of a mechanical and electrical product in Automatic Import License Mechanical and Electrical Products Catalog shall conform to the provisions of the following laws and administrative regulations:

(1) The provisions of Standardization Law of the P.R.C. regarding the standards and enforcement standards on ensuring the human health, personal safety and property safety;

(2) The provisions of [the Environmental Protection Law of the People's Republic of China](#) and other laws and administrative regulations on environmental protection;

- (3) The provisions [the Law of the People's Republic of China on the Prevention and Control of Air Pollution](#) and other laws and administrative regulations;

(4) The relevant provisions of [the Regulation of the People's Republic of China on Certification and Accreditation](#);

(5) The import of measurement instruments shall conform to the relevant provisions of [Measurement Law of the P.R.C.](#) and Administrative Measures for Supervision of Imported Instruments of Measurement;

(6) The import of radio transmission equipment shall conform to Administrative Regulations for Radio of the P.R.C.;

(7) Conforming to relevant provisions of other laws and administrative regulations.

Application process

The applicant may submit a written application or an on-line application.

1.

1. Written application procedure: The import applicant can obtain the "Mechanical and Electrical Products Import Application Form" from the issuing agency or download (copy) from the website authorized by the Ministry of Commerce, and submit it to the corresponding competent authority together with other relevant written materials.
2. Online application procedure: The applicant for import logs on the website authorized by the Ministry of Commerce, enters the national mechanical and electrical product import document management system, and truthfully fills in the "Mechanical and Electrical Product Import Application Form" online as required and submits it to the corresponding competent authority

The procedure for issuing "Automatic Import License" for mechanical and electrical products is as follows:

1.

1. For the import of an mechanical and electrical product that shall be handled by the local or departmental mechanical and electrical office, as soon as the local or departmental mechanical and electrical office receives a Form of Application for Import of mechanical and electrical Products and relevant materials, whose contents are correct and which meet the formal requirements, it shall issue an Automatic Import License. In a special case, it may issue an Automatic Import License within 10 working days.
2. For the import of a mechanical and electrical product that shall be handled by the Ministry of Commerce, the local or departmental mechanical and electrical office shall, within 3 working days after it receives a complete set of application materials, submit to the Ministry of Commerce the electronic data thereof upon verification. As soon as the Ministry of Commerce receives the corresponding data, it shall issue an Automatic Import License. In special cases, it may issue an Automatic Import License within 10 working days.

Documents

What are the required documents ?

Time period

In which time period may we obtain the right to import ?

Administration

What is the administration in charge of importations ? Name and address ?

Comments

Comments

Inspection of the product

Inspection method

Does it exist an inspection procedure applicable to the product ? If yes, which administration is in charge of ? Can you please describe the procedure ?

Commercialization rules

Notification / Declaration

What are the general rules in order to comercialize a product ?
Is there a notification / declaration to do ?

Regulatory requirements for electrical and electronic product

regulatory requirements for

product sales

The sellers of electrical and electronic products may not sell the electrical and electronic products that violate the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products.

Documents

What are the required documents ?

Delay

What is the delay to obtain the right to commercialize ?

Display in store

Is there some specific rules on the way to display the product in store ?

Display on internet

Is there some specific mentions to display the product on internet ?

Information to consumers

Do some specific information to have be given to consumers when the product is placed on the market ?

Comments

Comments

Administration

What is the administration in charge of commercialization ? Name and address ?

Documents