

Produit : Electronic / Measuring devices

Legal manager : DLUBALA JULIEN

Updated at : 26/03/2025 10:22:14

Downloaded at : 27/03/2026 12:23:00

CHINA

---

## Product's definition

### Category

In which category the product is classified ?

Products covered: battery(labelling, hazardous substances,recycling).

### Definition

What is the exact definition of the product ?

And if it exists, what is the interpretation of the authorities regarding it ?

Definition of electrical and electronic products5h5P\$Á-'è

Electrical and electronic products means the equipment and supporting products that work by relying on electric currents or electromagnetic fields or are manufactured for the purpose of generating, transmission and measuring electric currents and electromagnetic fields, with the rated working voltage of not more than 1,500 volts measured in direct current or not more than 1,000 volts measured in alternating current, excluding the equipment involving electrical energy production, transmission and distribution. (Administrative Measures for Restricted Use of the Hazardous Substances Contained in Electrical and Electronic Products)

Accordingly, most of the products involved in this section basically meet the definition of electrical and electronic products.

Definition of mechanical and electrical products:5\$Á-Đ`Kh

The term “mechanical and electrical products” refers to the mechanical equipment, electric equipment, transport tools, electronic products, electrical appliances, apparatus, instruments, metal products, and the parts and components and elements thereof. (Article 2 of Administrative Measures for Import of Mechanical and Electrical Products)

The specific scope of mechanical and electrical products is stipulated in the appendix of the “Administrative Measures for Import of Mechanical and Electrical Products”, which covers a wide range, including electrical and electronic products, instruments and meters, various luminaries and lighting devices, clocks and watches and their parts.

Among them, the import of some mechanical and electrical products is subject to automatic licensing management. The specific product scope is stipulated in the “Automatic Import License Mechanical and Electrical Products Catalog”.

---

Labelling

Language

In which language must the information on the product or on the packaging be indicated? If English is sufficient please indicate NA.

Must use Chinese language.

Mandatory labelling on product

What are the mandatory labelling on the product ?

General Requirements of Labeling

|   |                                                                                                                                         |
|---|-----------------------------------------------------------------------------------------------------------------------------------------|
| 1 | All necessary information concerning the proper and safe use and (or) related service and maintenance of the products shall be included |
| 2 | Clear and easy to be identified, the smallest English letter shall not be less than 1.5 mm                                              |
| 3 | Must use Chinese language                                                                                                               |
| 4 | The contents shall be the same with that contained in other printed materials (such as advertisement and package)                       |

General Labeling requirements of battery(In accordance with GB/T 8897.1-2013 Primary Batteries- Part1: General)

Labeling Requirements of Batteries

|    |                                                                                              |
|----|----------------------------------------------------------------------------------------------|
| 1  | Model                                                                                        |
| 2  | Production time and shelf life, or the suggested deadline of use                             |
| 3  | Polarity of positive electrode                                                               |
| 4  | Nominal voltage                                                                              |
| 5  | The name and address of manufacturer or supplier                                             |
| 6  | Trademark                                                                                    |
| 7  | Serial number for standard of implementation                                                 |
| 8  | Precautions for safe use (warning specifications)                                            |
| 9  | Amount of mercury (mercury-low or mercury-free)(if applicable)                               |
| 10 | Precautions to prevent swallow of a small battery by mistake<br>(for the small battery only) |
| 11 | The sign of waste battery disposal method as followed                                        |

## Detailed requirements of battery product label

| Label                                                                                      | Battery (In addition to small batteries) | Small Battery | P System Battery |
|--------------------------------------------------------------------------------------------|------------------------------------------|---------------|------------------|
| a)Model                                                                                    | A                                        | A             | C                |
| b)Production date (year and month) and shelf life, or the suggested deadline of shelf life | A                                        | B             | B                |
| c)Polarity of the positive pole terminal +                                                 | A                                        | A             | D                |
| d)Nominal voltage                                                                          | A                                        | B             | B                |
| e)Name or address of manufacturer or supplier                                              | A                                        | B             | B                |
| f)Trademark                                                                                | A                                        | B             | B                |
| g)Serial number of the implementing standard                                               | A                                        | B             | B                |
| h)Precautions for safe use                                                                 | A                                        | Ba            | Ba               |
| i)Mercury content (mercury-low or mercury-free)(if applicable)                             | A                                        | B             | B                |

A Shall be marked on the battery;

B Could be marked on the battery direct package (the sales package) and not be marked on the battery;

C Could be marked on the battery, seal or directly be marked on the package (sales package);

D Could be marked on the battery seal and or on the battery.

Precautions to prevent swallow of a small battery by mistake:the battery should be placed out of the reach of children. The batteries which are easily swallowed by children shall be placed out of the reach of children, especially the small battery of which the size is within the scope of inhalation gauge limits. In case that someone swallow the battery by mistake, please seek medical advice immediately.

Specific labeling requirement of batteries for watches (In accordance with GB/T 8897.3-2013 Primary Batteries-Part 3: Batteries for watches8897.3-2013Primary Batteries-Part 3: Batteries for watches)

## Labeling Requirements of Batteries for watches

|   |                                                                                                                                                                                                                    |
|---|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 1 | Model named according to Appendix A                                                                                                                                                                                |
| 2 | The polarity of the electrical connector                                                                                                                                                                           |
| 3 | The name of manufacturer or supplier and trademark                                                                                                                                                                 |
| 4 | Manufacture date or code consisting of two symbols, that is, the last number of the year and the number representing the month. October, November and December are represented respectively by character O,Y and Z |
| 5 | The package of the battery should be labeled with the name and address of battery manufacturer or supplier as well as the expire date                                                                              |
| 6 | Please refer to GB/T 8897.1 and GB 8897.5 for other applicable marks                                                                                                                                               |

## GB/T 36943-2018 Designation and marking requirements of lithium-ion batteries for electric bicycle

According to Article 6.2, the marking of the single battery shall have the following information:

- a) product name;
- b) specifications and models;
- c) nominal voltage;
- d) rated capacity;
- e) polarity;

- f) date of manufacture or batch number;
- g) the name of the manufacturer or producer.

The battery pack logo should have the following Chinese information:

- a) product name;
- b) specifications and models;
- c) the name of the manufacturer or producer;
- d) nominal voltage;
- e) rated capacity;
- f) polarity;
- g) maximum operating current;
- h) date of manufacture or batch number;
- i) Environmental protection mark (recycling mark);
- j) Required safety warning instructions.

1. importers of electrical and electronic products shall, in accordance with the national or industrial standards for the marking of the restricted use of the hazardous substances contained in electrical and electronic products, mark the hazardous substances contained in the electrical and electronic products they put on markets, and indicate the names and contents of hazardous substances or whether the elements or products which contain such substances may be recycled, the fact that improper use or disposal thereof may affect the environment or human health and other information. Where the aforesaid information cannot be marked on the products due to the restrictions in product volume, shape, surface materials or functions, it shall be indicated in the product manuals.
2. The producers and importers of electrical and electronic products shall, in accordance with the national or industrial standards for the marking of the restricted use of the hazardous substances contained in electrical and electronic products, indicate the EFUP on the electrical and electronic products they produce or import. Where the aforesaid information cannot be marked on the products due to the restrictions in product volume, shape, surface materials or functions, it shall be indicated in the product manuals.

## Mandatory labelling on packaging

### What are the mandatory labelling on the packaging ?

## Mandatory labelling on the instructions manual

What are the mandatory labelling on the instructions manual (if one is required) ?  
In which format, do we have to deliver the instruction manual to our customers ?

### Warnings - General ones

Are general warnings required ? If yes, which ones ?

### Warnings - Specific ones

Are specific warnings required ? If yes which ones ?

### Target Age

Is there any target age applicable? If so, does it have to be indicated and in which form?

### Sanctions / Fines

What are the sanctions / fines in case of non conformity ?

### Comments

### Comments

---

## Environment

### Recycling - Eco taxes

Which regulations concerning ecodesign and recycling apply to this product? Are there any ecotaxes applicable to this category of product?

### Regulatory requirements for electrical and electronic product

Regulatory requirements for

product design

The designers of electrical and electronic products may not violate the compulsory standards or the standards that must be implemented as prescribed by laws, administrative regulations and rules in the process of designing electrical and electronic products, and shall, on the premise of satisfying the technological requirements, adopt the schemes for making the said substances harmless, less harmful, easy to be degraded or convenient for being recycled, among others, in accordance with the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products,

## Product production supervision requirements

- The manufacturers of electrical and electronic products may not violate the compulsory standards or the standards that must be implemented as prescribed by laws, administrative regulations and rules in the process of manufacturing electrical and electronic products, and shall, in accordance with the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products, adopt the materials, technologies and technological processes with higher resource utilization rates, easy to be recycled and disposed of and conducive to environmental protection, and restrict or eliminate the use of the hazardous substances in products.
- The manufacturers of electrical and electronic products may not allow the electrical and electronic products that fail to comply with the requirements of these Measures to leave factories or be sold.

## regulatory requirements for packaging

The manufacturers and importers of electrical and electronic products may not violate the compulsory standards or the standards that must be implemented as prescribed by laws, administrative regulations and rules when making and using the packages of electrical and electronic products, and shall adopt the materials harmless, easy to be degraded and convenient for being recycled, and comply with the national or industrial standards for the use of packages.

## Regulatory requirements stipulated in Administrative Measures for Prevention and Control of Environmental Pollution by Electronic Waste

### Regulatory requirements for

### product production

The producers of electrical and electronic products may in accordance with the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products, restrict or eliminate the use of the hazardous substances in products.

### Regulatory requirements for information disclosure

Producers, importers and sellers of electronic and electrical products shall disclose the lead, mercury, cadmium, hexavalent chromium, polybrominated biphenyls (PBB), polybrominated diphenyl ethers (PBDE) and other toxic and hazardous substances contained in their products in accordance with relevant national regulations. As well as information on the impact of improper use or disposal on the environment and human health, and tips on how to use or dispose of the product in an environmentally sound manner after it is discarded.

### Recycling and disposal regulatory requirements

- Producers, importers and sellers of electronic and electrical products shall establish a recycling system in accordance with relevant national regulations, recycle waste products, and be responsible for storage, utilization or disposal in an environmentally sound manner;
- If the producers, sellers and importers of electronic products discard electronic and electrical products, they shall provide or entrust the electronic wastes to the dismantling, utilization and disposal units (including individual industrial and commercial households) with corresponding business scope listed in the directory (including the temporary directory) for dismantling, utilization or disposal.



The recycling of waste batteries shall comply with the provisions of The Solid Waste Pollution Prevention Act of the People's Republic of China, Policy on the Control Technology of Waste Battery Pollution, and Primary Batteries-Part1:General (GB/T 8897.1-2013).

#### Recycling of Waste Batteries:

The recycling of waste batteries shall comply with the provisions of The Solid Waste Pollution Prevention Act of the People's Republic of China, Policy on the Control Technology of Waste Battery Pollution, and Primary Batteries-Part1:General (GB/T 8897.1-2013).

#### Recycling of Waste Batteries

- |   |                                                                                                                                  |
|---|----------------------------------------------------------------------------------------------------------------------------------|
| 1 | The battery shall not be disassembled.                                                                                           |
| 2 | The battery shall not be incinerated at will.                                                                                    |
| 3 | The recycled batteries shall be stored in a clean and dry environment, avoiding direct sunlight, away from extreme heat sources. |
| 4 | The recycled batteries shall be stored in well-ventilated place.                                                                 |
| 5 | Do not mix the recycled batteries with other materials.                                                                          |
| 6 | Protect the two electrodes of batteries.                                                                                         |

#### Labelling

What are the mandatory labellings to put on the product or on the packaging regarding the environmental rules ?

---

### Technical rules / Standards

#### General safety requirements

What are the general safety requirements ? Does a risk assessment have to be conducted ? If yes, does it concern specific risk ?

#### Mandatory or voluntary standards

Are there some mandatory or voluntary standards applicable ? If yes, which ones ?

Please indicate the reference of the applicable standards

Regard to your products, if you want to check what are the technical requirement /toxicology/design... shall respect, thanks to check the labelling of your product first and find code of standards in labelling.

Step 1:

Enter this link: [https://docs.google.com/spreadsheets/d/1BDqhm609YySgDqs8cPOQUd-Dc\\_ZYPEEt7v-lv1sWB0CA/edit#gid=1640363751](https://docs.google.com/spreadsheets/d/1BDqhm609YySgDqs8cPOQUd-Dc_ZYPEEt7v-lv1sWB0CA/edit#gid=1640363751)

Step 2:

Enter the code of product standard selected by you in PACE and open the link in red.

Enter the code of mandatory safety standard above.

Step3:

Open link and find documents of standard, your products shall respect all requirements in file.

PS: If you can't find the translation file in link above, please do not hesitate to contact with CHINA Conformity Leader by mail "chinadmilegal@decathlon.net".

## Physical and mechanicals properties

What are the physical and mechanicals properties required ?

## Electrical aspects

What are requirements regarding electrical aspects ?

## Inflammability

Are there any specific requirements to ensure inflammability?

## Hygiene

What are the rules regarding hygiene ?

## Radioactivity

What are the rules regarding radioactivity ?

## Radiofrequency (2G,3G,4G,5G, Bluetooth, Ant+, GPS, Wifi...)

What are the rules regarding the radiofrequency?

## Products making noise

## Chemicals substances

Have a look on [Toxiline](#) to check our toxicological specifications.

## Limits for certain hazardous substances in battery

## Limits for certain hazardous substances in battery

## Limitation of Mercury, Cadmium and Lead Contents for Alkaline and Non-Alkaline Zinc Manganese Dioxide Batteries

## Limitation of Mercury Content for Zinc Silver Oxide, Zinc Oxygen and Zinc Manganese Dioxide Button Batteries

| Category                  | Type                                                                                                     | Limitation of Mercury/(mg/g) |
|---------------------------|----------------------------------------------------------------------------------------------------------|------------------------------|
| Free Mercury Battery      | Mercury Battery                                                                                          |                              |
| Zinc silver oxide battery | SR62 SR63 SR65 SR64 SR60 SR60 SR66 SR58 SR68 SR59 SR69 SR41 SR57 SR55 SR48 SR56                          |                              |
|                           | SR516 SR521 SR527 SR614 SR616 SR621 SR626 SR712 SR714 SR716 SR721 SR726 SR731 SR736 SR754 SR916 SR920 SR |                              |

|                                         |                                   |     |
|-----------------------------------------|-----------------------------------|-----|
| Alkaline zinc air battery               | PR70 PR41 PR48 PR43 PR44d 0.005   | d20 |
| Alkaline zinc manganese dioxide battery | LR9 LR53 LR41 LR55 LR54 LR43 LR44 | d20 |

Limitation of Heavy Metal in Battery mg/kg

| Item                  | Heavy Metal |      |     |
|-----------------------|-------------|------|-----|
| Pb                    | Cd          | Hg   |     |
| Monomer Power Battery | d 40        | d 20 | d 5 |

Marking Styles for the Names and Contents of the Hazardous Substances (Replaced by SJ/T 11364-2014/XG1-2017)

Names and Contents of the Hazardous Substances

| Part Name |              |              |                              |                                |                                      |       |
|-----------|--------------|--------------|------------------------------|--------------------------------|--------------------------------------|-------|
| Lead (Pb) | Mercury (Hg) | Cadmium (Cd) | Hexavalent Chromium (Cr(VI)) | Polybrominated Biphenyls (PBB) | Polybrominated diphenyl ether (PBDE) |       |
| .....     | .....        | .....        | .....                        | .....                          | .....                                | ..... |

This table is prepared in accordance with the provisions of SJ/T 11364.

● Indicates that said hazardous substance contained in all of the homogeneous materials for this part is below the limit requirement of GB/T 26572.

×: Indicates that said hazardous substance contained in at least one of the homogeneous materials used for this part is above the limit requirement of GB/T 26572.

(Enterprises may further provide in this box technical explanation for marking “×” based on their actual circumstances.)

The special regulatory requirements for battery products are mainly Regulations on Limiting Mercury Content in Battery Products, and the main regulatory requirements are summarized as follows:

- Since January 1, 2001, it is prohibited to produce all kinds of batteries with a mercury content greater than 0.025% of the battery weight in China;
- Since January 1, 2001, all domestic and foreign battery products (including batteries matching electrical appliances) that enter the domestic market must be marked with mercury content on the single battery (for example: "low mercury" or "No mercury" indicated), batteries without mercury content are not allowed to enter the market;
- Since January 1, 2002, it is prohibited to distribute batteries with mercury content greater than 0.025% of the battery weight in the domestic market;
- Since January 1, 2005, it is prohibited to produce alkaline zinc-manganese batteries with mercury content greater than 0.0001% of the battery weight in China;
- Since January 1, 2006, it is prohibited to distribute alkaline zinc-manganese batteries with mercury content greater than 0.0001% of the battery weight in China.

## Packaging requirements

Can you please indicate if there are some requirements regarding the packaging of our products (mainly they are in paper, carton, plastic, textile) ? If yes, please explain them.

## Laboratory

In which laboratory can we perform the testing of the product according to the standard?

## Sanctions / Fines

What are the sanctions / fines in case of non conformity ?

## Comments

## Comments

---

## Certifications / Registrations

### Certifications or registrations

Are there some certifications or registrations applicable to the product ?

There is no need for certification or record filing.

## Laboratory

In case of mandatory certification/ registration that we must follow please precise the name and address of any laboratories where we can conduct them

## Comments

## Conformity documents

### Documents

What are the conformity documents ? Can you please list them ?

### Format

Does it exist a specific format for the conformity documents ? If yes, can you please provide us an example in english ?

### Comments

### Comments

---

## Importation rules

### General rules

What are the general rules in order to import the product ?

Regulatory requirements for electrical and electronic product

Regulatory requirements for product import

- The electrical and electronic products imported may not violate the compulsory standards or the standards that must be implemented as prescribed by laws, administrative regulations and rules, and shall comply with the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products.
- The entry-exit inspection and quarantine institutions shall conduct port verification and statutory inspection of the electrical and electronic products imported. The Customs shall verify the Customs Clearance Form for Goods Entering China issued by entry-exit inspection and quarantine institutions and undergo the customs clearance formalities under the relevant provisions.

Regulatory requirements for import of mechanical and electrical products

The regulatory requirements for the import of mechanical and electrical products are mainly stipulated in Administrative Measures for Import of Mechanical and Electrical Products and Implementation Measures of Automatic Import License for Mechanical and Electrical Products and other regulations. Since it has not been retrieved that your company sells products listed in the Catalog of Restricted Imports of Mechanical and Electrical Products and Electrical Products or the Catalog of Mechanical and Electrical Products Prohibited from Importing, this section is mainly aimed at the mechanical and electrical products listed in Automatic Import License Mechanical and Electrical Products Catalog, which are classified as product with automatic import license.

## General regulatory requirements

- To import mechanical and electrical products with automatic import license, the import entity shall file an application with the Ministry of Commerce or its authorized institution for an Automatic Import License before it goes through the customs formalities.

## Application requirements

- The import of a mechanical and electrical product in Automatic Import License Mechanical and Electrical Products Catalog shall conform to the provisions of the following laws and administrative regulations:

(1) The provisions of Standardization Law of the P.R.C. regarding the standards and enforcement standards on ensuring the human health, personal safety and property safety;

(2) The provisions of [the Environmental Protection Law of the People's Republic of China](#) and other laws and administrative regulations on environmental protection;

- (3) The provisions [the Law of the People's Republic of China on the Prevention and Control of Air Pollution](#) and other laws and administrative regulations;

(4) The relevant provisions of [the Regulation of the People's Republic of China on Certification and Accreditation](#);

(5) The import of measurement instruments shall conform to the relevant provisions of [Measurement Law of the P.R.C.](#) and Administrative Measures for Supervision of Imported Instruments of Measurement;

(6) The import of radio transmission equipment shall conform to Administrative Regulations for Radio of the P.R.C.;

(7) Conforming to relevant provisions of other laws and administrative regulations.

## Application process

The applicant may submit a written application or an on-line application.

1.

1. Written application procedure: The import applicant can obtain the "Mechanical and Electrical Products Import Application Form" from the issuing agency or download (copy) from the website authorized by the Ministry of Commerce, and submit it to the corresponding competent authority together with other relevant written materials.
2. Online application procedure: The applicant for import logs on the website authorized by the Ministry of Commerce, enters the national mechanical and electrical product import document management system, and truthfully fills in the "Mechanical and Electrical Product Import Application Form" online as required and submits it to the corresponding competent authority

The procedure for issuing "Automatic Import License" for mechanical and electrical products is as follows:

1.

1. For the import of an mechanical and electrical product that shall be handled by the local or departmental mechanical and electrical office, as soon as the local or departmental mechanical and electrical office receives a Form of Application for Import of mechanical and electrical Products and relevant materials, whose contents are correct and which meet the formal requirements, it shall issue an Automatic Import License. In a special case, it may issue an Automatic Import License within 10 working days.
2. For the import of a mechanical and electrical product that shall be handled by the Ministry of Commerce, the local or departmental mechanical and electrical office shall, within 3 working days after it receives a complete set of application materials, submit to the Ministry of Commerce the electronic data thereof upon verification. As soon as the Ministry of Commerce receives the corresponding data, it shall issue an Automatic Import License. In special cases, it may issue an Automatic Import License within 10 working days.

## Documents

What are the required documents ?

Time period

In which time period may we obtain the right to import ?



## Administration

What is the administration in charge of importations ? Name and address ?

Comments

Comments

---

## Inspection of the product

Inspection method

Does it exist an inspection procedure applicable to the product ? If yes, which administration is in charge of ? Can you please describe the procedure ?

---

## Commercialization rules

Notification / Declaration

What are the general rules in order to comercialize a product ?  
Is there a notification / declaration to do ?

Regulatory requirements for electrical and electronic product

regulatory requirements for

product sales

The sellers of electrical and electronic products may not sell the electrical and electronic products that violate the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products.

Documents

What are the required documents ?

Delay

What is the delay to obtain the right to commercialize ?

Display in store

Is there some specific rules on the way to display the product in store ?

The sale display of battery shall meet the specific requirements of GB/T 8897.1-2013: Primary Batteries-Part1: General.

Requirements of Sale Display:

1. The battery shall not be huddled together; but shall be stored in original packaging.
2. The battery for sale shall not be displayed in shop window which was exposed to direct sunlight for long time.
3. The height of battery box stack shall not exceed the height specified by manufacturer.
4. Retailers shall be able to select battery for customer correctly.

## Display on internet

Is there some specific mentions to display the product on internet ?

## Information to consumers

Do some specific information to have be given to consumers when the product is placed on the market ?

## Comments

## Comments

## Administration

What is the administration in charge of commercialization ? Name and address ?

---

## Documents