

Night Shift Reports

Part 3 — Build the Final Pick Sheets

Turn the routed workbook into the four pick-and-order reports the warehouse team works from.

Prepared for B&R Food Services Inc.

Field	Detail
Input	The Part 2 routed workbook — the Driver Setup pull sequence is already filled in.
Output	Four report blocks — PO by vendors, Dry by driver, Freezer page, WH Pickup.
Also	The All orders Sheet is re-ordered to the driver pull sequence.
Next	Part 4 — Jetro branch.

1. The Driver Setup Sheet

The Driver Setup sheet was created in Part 1 and filled in by the office during Part 2. Part 3 only reads it — there is no office step here. It is the single source for all driver ordering.

1.1 Pull sequence (Jetro & Dry)

A single ordered column. The office listed the drivers in the order they leave the warehouse.

- **The first driver in the list leaves the warehouse first** — their orders are pulled first, most urgent.
- **The last driver leaves last** — least urgent.
- This one sequence orders the All orders Sheet, the Dry report, the WH Pickup blocks, and the Jetro reports (Part 4). It also sets the Freezer groups (see 1.2).

1.2 Freezer groups

Freezer groups are derived automatically from the pull sequence — the office does not assign them.

- **Freezer one** — the first 3 drivers in the pull sequence.
- **Freezer two** — all other drivers.

2. Re-order the All orders Sheet

Sort the All orders Sheet so its rows follow the driver pull sequence from the Driver Setup sheet — the first driver's rows first, the last driver's rows last. This is the master order; every driver-organized report inherits it.

3. Block 1 — PO by vendors

Built from the PO sheet. Grouped by vendor, each group with a spanned Vendor name + date header.

Col	Header	Source
A	Qty	PO ordered Qty
B	total QTY	Sum of Qty per code, on the first row of the code
C	Product Name	Product Name
D	Code	Item code
E	Price	Price
F	CURRENT COST PRICE	Current cost price
G	Jetro cost	Case price
H	Name	Customer name
I	Driver	Driver

PO is sorted by vendor, then by item code within each vendor.

4. Block 2 — Dry by driver

Built from the All orders Sheet — every row whose Bin is DRY.

Col	Header	Source / Rule
A	Bin	Bin (the general bin, 'DRY')

Col	Header	Source / Rule
B	QTY	Ordered Qty
C	Product Name	Product Name + Description, merged into one cell
D	Vendor	Vendor
E	Customer	Customer name
F	Driver	Driver
G	QTY	Quantity On Hand
H	Internal bin	Internal bin (the exact location)

- Each driver is a separate group with a spanned header (driver name + date).
- Driver groups follow the pull sequence from the Driver Setup sheet.
- Within each driver group, rows are sorted by internal bin so the picker walks the dry area in location order.

5. Block 3 — Freezer page

Built from the All orders Sheet — every row whose Bin is FREEZER. Split into two delivery groups derived from the pull sequence.

Col	Header	Source
A	bin	Bin
B	qty	Ordered Qty
C	product name	Product Name
D	Customer	Customer name
E	qty	Quantity On Hand

- Freezer one — the first 3 drivers in the pull sequence. Freezer two — all others.
- Each group has a spanned date + group headline.

6. Block 4 — WH Pickup

A single consolidated pull file covering every bin still in the All orders Sheet — COOLER, COOLER-PD, DRY, FREEZER, PICK UP and any others.

Col	Header	Source / Rule
A	qty	Ordered Qty
B	Product Name	Product Name + Description, merged into one cell
C	bin	Bin
D	internal bin	Internal bin
E	vendor	Vendor
F	Driver	Driver
G	qty	Quantity On Hand

- One block per customer, with a spanned header: Customer name + Driver name + date.
- Customer blocks are ordered by the driver pull sequence — the first driver's customers first.
- Within each customer block, rows are sorted by bin in the order Cooler → Cooler-pd → Dry → Freezer, any other bin after, then by internal bin.

7. Step-by-Step — Part 3

1. Take the Part 2 routed workbook — the Driver Setup pull sequence is already filled in.
2. Re-order the All orders Sheet to the driver pull sequence.
3. Build Block 1 — PO by vendors (vendor groups, 9 columns).
4. Build Block 2 — Dry by driver (DRY rows, driver groups in pull-sequence order, sorted by internal bin).
5. Build Block 3 — Freezer page (FREEZER rows, split into Freezer one = top 3 drivers, Freezer two = the rest).
6. Build Block 4 — WH Pickup (all bins, customer blocks in pull-sequence order, bin-sorted).
7. The final pick sheets are ready. — End of Part 3. Continue with Part 4 (Jetro).

8. Key Rules — Quick Reference

Rule	Detail
Driver pull sequence	From the Driver Setup sheet. First driver leaves first, last driver leaves last.
Master order	The pull sequence orders the All orders Sheet, Dry, WH Pickup and Jetro.
Freezer split	Freezer one = first 3 drivers in the pull sequence; Freezer two = all others.
PO by vendors	Vendor groups, spanned Vendor + date header, 9 columns, total QTY summed per code.
Dry by driver	DRY-bin rows, 8 columns, driver groups in pull-sequence order, sorted by internal bin.
Freezer page	FREEZER-bin rows, 5 columns, split into Freezer one and Freezer two.
WH Pickup	All bins, one block per customer, bins ordered Cooler → Cooler-pd → Dry → Freezer → others.
Merged Product Name	Dry and WH Pickup merge Product Name + Description into one cell.