GivHome + Marstek Venus

Interoperability update | 4.2.0-beta.1 | 9 November 2026

GivHome now includes a Marstek Venus E 3.0 add-on built on the 4.1.3 GivEnergy controls. The aim is to make the batteries work together through familiar Apple Home controls. **Commissioning is included in this beta; the installed Venus still needs to pass its checks.**

What is ready

- **One combined battery percentage.** SOC is weighted by supported battery capacity, rather than averaging unlike batteries. Charge To and Export To use that shared view; individual reserves remain separate.
- **Charging together.** Overnight charging follows the Night Target, normally 100%. IOG slots charge both batteries when Charge mode is selected. Pause modes remain pauses. Joined simulations cover slot arrival, slot ending and restoration.
- **A clear division of work.** Our GivModbus reads the Gateway for household evidence. The AIO keeps its established direct readings and controls. Venus uses a separate Modbus connection. Gateway access stays read-only.
- **Optional, simple setup.** Marstek has its own section at the bottom of settings, with Gateway IP/serial and Venus connection details. Choose 800 W or 2.5 kW to match the battery setting. Time is inherited and supported capacities are supplied automatically. There is no import-budget field.
- **Recovery without blind retries.** Controls check identity and fresh evidence, share communications deliberately, retain cancellation and reconcile interrupted actions. Pause Venus automation keeps targets and monitoring while holding Venus plans; independent GivEnergy schedules continue.

One-time setup in the Homebridge web page

Save and restart, then Check connections. Enter the expected Gateway serial and reserve the Venus IP in the router. No desktop helper, terminal command or extra commissioning tile is needed.

Run battery check. With Venus idle and 25-90% charged, the helper briefly requests 100 W charge and discharge, checks measured stopping between them, and verifies restoration of the original idle settings. Cancel is available.

Ready. Successful checks save a result tied to the device, firmware and configuration. Selected physical controls can then run without another beta to unlock them. Changed identity, firmware or power settings require rechecking.

What the evidence does - and does not - establish

662 automated checks pass on Node 22 and 24. Native HomeKit checks and an isolated browser commissioning journey also pass. Tests cover targets, IOG, household changes, missing data, wrong identities, cancellation, lost acknowledgements, stop refusal and restart recovery. A small Pi comparison supported retaining the Gateway as an additional source. **These results do not replace installed-Venus testing.**

Installation must confirm the electrical metering boundary, intended power limits and real stopping behaviour. A 100 W check does not qualify full-power operation. Software cannot send Pause while the Pi is stopped or Venus is unreachable; a device-side watchdog remains unproven. Stopping Venus alone cannot always enforce the 6 kW export allowance if AIO and PV already exceed it. No whole-house import limiter is claimed.

Beta Marstek Addon. Not for public use. Existing GivEnergy-only users can leave the add-on off.