Web-Socket Audio Controller for FreecShot Plus Stream Deck Plugin Manual

2026-11-10

A plugin that controls the volume, mute, monitoring and balance of the **FreecShot Plus** audio mixer from a Stream Deck, and shows level meters on the keys and dial screens. It installs separately from the OBS edition of Web-Socket Audio Controller, so you can use OBS and FreecShot Plus side by side.

Made by **김탄2 (Kimtan2)**

What you need

Item	Requirement
Computer	Windows 10 or later
Stream Deck app	Stream Deck software 7.3 or later
FreecShot Plus	FreecShot Plus (SOOP broadcasting software)
Installer	A `.streamDeckPlugin` file (e.g. `Web-Socket-Audio-Controller-for-FreecShot-Plus.streamDeckPlugin`)

With a Stream Deck + you can also use the dial actions (VU Dial, Balance Dial). Other Stream Decks use the key actions only.

Step 1: Install the plugin

1. Double-click the `.streamDeckPlugin` file.
2. The Stream Deck app opens and asks whether to install it. Click **Install**.
3. If it is already installed, it may ask to replace it. Choose install again.
4. Check that the **Web-Socket Audio Controller for FreecShot Plus** category appears in the action list on the right of the Stream Deck app.

Step 2: Turn on WebSocket in FreecShot Plus (auto setup)

The plugin talks to FreecShot Plus through its built-in **WebSocket** server. It is off at first, and FreecShot Plus has no menu to turn it on, so the plugin's **WebSocket auto setup** button does it once.

1. **Close FreecShot Plus completely.** While it runs, the button changes nothing and tells you so.
2. Drag any action from **Web-Socket Audio Controller for FreecShot Plus** onto a key and click it.
3. At the very bottom of the settings screen, unfold ▶ **FreecShot Plus connection (WebSocket)**.
4. Usually leave Port and Password empty: the port becomes `24455` and the password stays the one FreecShot Plus already has. Enter your own values if you want (port 1024–65535).
5. Press **WebSocket auto setup**. When it says Done, you are set; the Port and Password fields fill in with the values it used.
6. Start FreecShot Plus and **sign in to SOOP**. Until you sign in, the keys show **LOGIN**.

Before changing anything, the button backs up the original file in the same folder as `config.json.bak-date-time`. The file: `%APPDATA%\SOOPStudio\plugin_config\obs-websocket\config.json`

Step 3: Connect the plugin

The auto setup button in Step 2 also fills in these settings, so there is usually nothing to change here. Use this to check or edit the values.

1. Drag any action from **Web-Socket Audio Controller for FreecShot Plus** onto a key and click it.
2. At the very bottom of the settings screen, click ▶ **FreecShot Plus connection (WebSocket)** to unfold it. (It is folded by default.)
3. Check or change the values. They apply to every action.

Field	Default	Meaning
Host	`127.0.0.1`	Address of the PC running FreecShot Plus (keep it for the same PC)
Port	`24455`	Must match the FreecShot Plus server port (auto setup sets both)
Password	empty	The FreecShot Plus WebSocket password (auto setup fills it in)

Changes reconnect right away; no restart is needed. While FreecShot Plus is not running the keys show **OFFLINE**, and the plugin retries every 3 seconds.

Changing the language: unfold ▶ **Language** at the bottom of the same screen and pick English / 한국어 / 日本語. The settings screen and the text on the keys (MUTED, OFFLINE and so on) change at once, for every action. The default is English; action names in the action list do not change.

How to tell it is connected: no key shows OFFLINE, and the **Source** list on the settings screen shows your FreecShot Plus audio sources (e.g. Mic/Aux, Desktop Audio).

Step 4: Make your first key

This example mutes your microphone with one key. It works on every Stream Deck.

1. Drag **Web-Socket Audio Controller → Mute** onto an empty key.
2. Click the key and pick your microphone in **Source**. Sources without audio (images, browsers and so on) are not listed.
3. Each press turns mute on or off. While muted the key turns red, with the source name and **MUTED** in the middle.

Renaming the source in FreecShot Plus keeps the key working.

A volume fader on two keys

This example raises and lowers the microphone volume with two keys. It works on every Stream Deck.

1. Drag **Fader(2-Button)** onto two keys, one directly above the other.
2. Click the top key, pick the microphone in **Source** and **Top (up)** in **Role**.
3. Give the bottom key the same source, and **Bottom (down)** in **Role**.
4. The top key raises the volume by 1 dB, the bottom key lowers it by 1 dB. Hold a key to keep moving. Change the amount in **Step (dB)** (e.g. 0.5, 2).

For two keys side by side, pick **Left (down)** and **Right (up)** as the roles.

Reading the keys (stacked vertically):

- Top of the upper key: source name and current volume
- Bottom of the lower key: current audio level
- Two bars (L/R): the incoming level, running across both keys, on the FreecShot Plus scale of −60 to 0 dB
- Sky-blue line inside the bars: volume (fader) position
- MUTED: the source is muted (the bars keep moving in grey)

The source name always takes one line so every fader has the same size. Long names end in …; enter a short name in **Display name**. This action cannot mute; add a Mute key for that.

With a Stream Deck +: VU Dial

This example controls the microphone volume with a Stream Deck + dial.

1. Drag **VU Dial** onto a dial slot.
2. Pick the microphone in **Source**.
3. Each tick changes the volume by 1 dB. Change the amount in **Step per tick (dB)** (e.g. 0.5, 2). Pressing the dial toggles mute.

Reading the screen:

- Top: source name
- Two bars (L/R): the incoming level (green → yellow → red)
- Sky-blue line inside the bars: volume position
- Bottom left / right: audio level / volume
- MUTED: the source is muted

Tapping the screen also mutes. If that happens by accident, turn off **Touch tap mutes**. The level at the bottom left can show L and R separately (`L -14.0 R -18.0`) or one value (**Combined**, `-14.0 dB`); choose in **Level text**.

Changing the press actions: unfold ▶ **Press actions** on the settings screen. (It is folded by default.)

- **Press:** press and release. **Mute toggle** (default) or **Recall volume**
- **Press + turn left / right:** turning while pressed. **Step volume** (default), Mute toggle, Mute on, Mute off, Recall volume
- With Recall volume, a **Recall volume (dB)** field appears below it. Enter the volume to go back to (e.g. −20).

If you turned the dial while pressing, the press action does not run on release.

Action list

Key actions work on every Stream Deck; dial actions need a Stream Deck +.

Action	Type	What it does
VU Dial	Dial	Turn for volume (1 dB per tick by default), press or tap to mute, shows a level meter
Balance Dial	Dial	Turn to move the balance by 1 as shown (e.g. L 40 → L 39), press to centre
Fader(2-Button)	2 keys	Raise/lower the volume with two keys (1 dB per press by default), meter across both keys
Mute	Key	Mute on/off. Red frame and a faint red tint while muted
Volume	Key	Set the volume to a value (Set to) or move it by an amount (Step by). Shows a meter
Push to talk / Push to mute	Key	Sound goes out (talk) or is blocked (mute) only while held
Talkback	Key	Mutes or lowers other sources at once; release (or press again) to put them back
Audio monitoring	Key	Switch audio monitoring between off / monitor only / monitor and output
Balance	Key	Set the balance to a value or move it by an amount

Keys that repeat while held (Fader(2-Button), Volume and Balance in Step by) can be stopped by pressing the key once more if a repeat does not stop.

Volume and Balance keys

Volume: choose in **Mode**.

- **Set to:** sets the volume to **Volume (dB)** (e.g. −20).
- **Step by:** moves the volume by that amount (e.g. 1 or −1). Hold to keep moving.

The range matches the FreecShot Plus slider: −∞ to 0 dB. Going below −60 dB gives −∞ (silent); going up from −∞ gives −60 dB.

Balance: choose in **Mode** and enter a value in **Balance**.

- **Set to:** −100 = L 100, 0 = centre, 100 = R 100 (e.g. −40 → L 40)
- **Step by:** 5 = 5 to the right, −5 = 5 to the left

Push to talk / Push to mute

1. Put **Push to talk / Push to mute** on a key and pick the microphone in **Source**.
2. Choose in **Mode**. **Push to talk** lets sound out only while held; **Push to mute** blocks it only while held.
3. **Release delay (ms):** how long to wait after release before switching back (default 200 ms, like FreecShot Plus's PTT). It keeps the end of a sentence from being cut.

The key shows the source name and its mode (**Push to talk** or **Push to mute**). It gets a sky-blue frame and a faint sky-blue tint while sound goes out; the text is red while it is blocked.

- The key remembers the mute state at the moment you press it and goes back to **that state** on release. Push to mute on an already-muted microphone does not unmute it on release.
- Switching pages while holding puts it back at once. Releasing while FreecShot Plus is disconnected puts it back the moment it reconnects.
- It does not work inside a Multi Action: the release is not reliable there, and the microphone could stay on.

Talkback

A key that lowers music or game audio all at once while you talk.

1. Put **Talkback** on a key.
2. Choose in **Target**: **All except the list** lowers every source except those in the list (usually your microphone); **Only the list** lowers only the listed sources.
3. Click **+ Add Source** to add sources one row at a time. Remove a row with its ×.
4. Choose how to lower them in **Style**.
5. Choose **While held** or **Toggle** (press once to turn on, again to turn off) in **Behavior**.

Style	What it does
Mute	Mutes the target sources
Set volume	Lowers them to **Volume (dB)** (default −30). Sources already quieter stay as they are
Talkback	Lowers them by **Lower by (dB)** from their current volume (default 15)

- The key gets a sky-blue frame and a faint sky-blue tint while on. Sources that are already muted are left alone.
- Turning it off puts every source back to **its value from before the press**.
- If several Talkback keys hold the same source, turning one off also turns off the others holding that source, and their keys show off.
- The original values survive a restart of the Stream Deck app or the PC. While held is put back as soon as FreecShot Plus connects; Toggle stays on.
- **Deleting a key while its Toggle is on leaves the sources lowered**, so turn it off first.
- Inside a Multi Action only Toggle works.

Audio monitoring

Switches the **Audio Monitoring** setting from FreecShot Plus's Advanced Audio Properties. Choose in **Mode**.

Mode	What it does
Set to	Sets the value chosen in **Monitoring** (Monitor off / Monitor only / Monitor and output)
Toggle with off	Each press switches between off and the chosen value
Cycle	Each press goes off → monitor only → monitor and output

The key shows the source name and the current monitoring; it gets a sky-blue frame and a faint sky-blue tint while monitoring is on.

Meter settings

Actions with a meter (VU Dial, Fader(2-Button), Volume) have **Meter style**. Match FreecShot Plus **Settings → Audio → Peak Meter Type**.

Meter style	FreecShot Plus setting	Colour ranges
Standard	Sample Peak	yellow from −20 dB, red from −9 dB
Wide green	True Peak	yellow from −13 dB, red from −2 dB

FreecShot Plus sends the plugin sample-peak values only, so Wide green matches FreecShot Plus in its colour ranges only; loud peaks may read slightly lower than in FreecShot Plus. Like FreecShot Plus, the meter falls back gradually and shows a peak-hold mark for 20 seconds.

Changing what a key shows

Renaming the source: enter a name in **Display name** on the settings screen. Empty shows the FreecShot Plus source name. The Stream Deck app's own title would overlap the plugin's text, so rename with Display name.

A different look for each state: the Mute, Push to talk / Push to mute, Talkback and Audio monitoring keys have two states.

1. Click the key in the Stream Deck app.
2. Find the two dots under the icon. The table below shows which state each dot is.
3. Click a dot, then set the icon and title for that state.

Key	Left dot	Right dot
Mute	the source's sound is going out	the source's sound is off (muted)
Talkback	the other sources sound as usual	the other sources are off or lowered (Talkback on)
Push to talk	the source's sound is going out (while pressed)	the source's sound is off (usually while not pressed)
Push to mute	the source's sound is going out (usually while not pressed)	the source's sound is off (while pressed)
Audio monitoring	monitoring is off	monitoring is on (monitor only, or monitor and output)

With a title set, the plugin hides its own name and status text (the frame and tint stay). While your own icon is shown, signs such as OFFLINE may not be visible. If you see only one dot, the key was placed with an older version; delete it and drag it in again from the action list.

Signs on the keys and troubleshooting

If a key or dial shows one of these, check the right-hand column in order.

Sign / symptom	Meaning	What to do
OFFLINE	Not connected to FreecShot Plus	Check that FreecShot Plus is running → auto setup in Step 2 was done → port 24455 → password
LOGIN	Connected, but FreecShot Plus takes no requests until you sign in to SOOP	Sign in to SOOP in FreecShot Plus; it clears at once
SET SOURCE	No source chosen yet	Click the action and pick a Source
SETUP	Another required setting is empty	Fill in the empty fields (Mode, value and so on)
N/A	The chosen source is not in FreecShot Plus (deleted)	Pick another source
Level bars do not move	No audio is coming into that source	Check that its meter moves in the FreecShot Plus audio mixer
Source list is empty	Not connected yet	The list fills once connected. If not, see OFFLINE
A repeat does not stop	The key release was missed	Press that key once more
Still quiet after Talkback	The key was deleted while on, or FreecShot Plus disconnected	Check the FreecShot Plus connection. If the key was deleted, restore the volume in FreecShot Plus

Contact

If you have a problem or a question, contact the author (Kimtan2 / 김탄2).

- **Discord:** kimtan2
- **Chzzk (치지직):** 김탄2

FreecShot Plus and SOOP are trademarks of their owner. This plugin is unofficial and not affiliated with SOOP. obs-websocket is software of the OBS Project.