

Product Search

Login

New Member Registration

FA-130RA-18100

(Brush motors)





Typical Applications

- Home Appliances > Hair Dressing, Beauty Appliance
- Home Appliances > Epilator
- Toys and Models

OUTPUT: 0.2W-2.5W (APPROX)

WEIGHT:17g (APPROX)

Metal Brush

Ferrite magnets

Performance Table

1 of 3

Performance Table

MODEL	VOLTAGE		NO LOAD		AT MAXIMUM EFFICIENCY					STALL		
	OPERATING RANGE	NOMINAL	SPEED	CURRENT	SPEED	CURRENT	TORQUE		OUTPUT	TORQUE		CURRENT
		V	r/min	Α	r/min	Α	mN⋅m	g∙cm	W	mN⋅m	g∙cm	А
FA-130RA 18100	1.5 - 3.0	3	12300	0.15	9710	0.56	0.74	7.6	0.76	3.53	36	2.10

Other Winding Specifications Available in the Web Catalog

FA-130RA-18100

FA-130RA-2270

Frequently Asked Questions About Products

Q

Where can I purchase your motors?



What is the minimum purchase amount for your motors?

See list

For inquiries related to products

Contact Form

For inquiries by telephone, please refer to the contact list to confirm

2 of 3

your point of contact.

Return to Product Search Index

Copyright © MABUCHI MOTOR CO., LTD. All rights reserved.