

Alfabeto en código binario.

Mayúsculas.			Minúsculas.		
Letra	Nro	Cod.Binario	Letra	Nro	Cod.Binario
A	65	01000001	a	97	01100001
B	66	01000010	b	98	01100010
C	67	01000011	c	99	01100011
D	68	01000100	d	100	01100100
E	69	01000101	e	101	01100101
F	70	01000110	f	102	01100110
G	71	01000111	g	103	01100111
H	72	01001000	h	104	01101000
I	73	01001001	i	105	01101001
J	74	01001010	j	106	01101010
K	75	01001011	k	107	01101011
L	76	01001100	l	108	01101100
M	77	01001101	m	109	01101101
N	78	01001110	n	110	01101110
O	79	01001111	o	111	01101111
P	80	01010000	p	112	01110000
Q	81	01010001	q	113	01110001
R	82	01010010	r	114	01110010
S	83	01010011	s	115	01110011
T	84	01010100	t	116	01110100
U	85	01010101	u	117	01110101
V	86	01010110	v	118	01110110
W	87	01010111	w	119	01110111
X	88	01011000	x	120	01111000
Y	89	01011001	y	121	01111001
Z	90	01011010	z	122	01111010

Tabla de conversión entre decimal, binario, hexadecimal, octal, BCD, Exceso 3 y Gray o reflejado.

Decimal	Binario	Hexadecimal	Octal	BCD	Exceso 3	Gray o Reflejado
0	0000	0	0	0000	0011	0000
1	0001	1	1	0001	0100	0001
2	0010	2	2	0010	0101	0011
3	0011	3	3	0011	0110	0010
4	0100	4	4	0100	0111	0110
5	0101	5	5	0101	1000	0111
6	0110	6	6	0110	1001	0101
7	0111	7	7	0111	1010	0100
8	1000	8	10	1000	1011	1100
9	1001	9	11	1001	1100	1101
10	1010	A	12	0001 0000		1111
11	1011	B	13	0001 0001		1110
12	1100	C	14	0001 0010		1010
13	1101	D	15	0001 0011		1011
14	1110	E	16	0001 0100		1001
15	1111	F	17	0001 0101		1000