

MIYAMA TRANSFORMER DATASHEET
MODEL MYT-3A122a

- **Input/Primary**
 - **L1:** 0V
 - **L2:** (+/-) 220V
 - **Power max:** 72 W
 - **Current max:** approx. 0.33 A
 - **Turns:** approx. 1, 468 turns
 - **Center turn:** approx. 734 turns
 - **Wire thickness:** approx. 0.4 mm

- **Output/Secondary**
 - **L1:** (+/-) 12V
 - **Center Tap:** 0V
 - **L2:** (-/+) 12V
 - **Power max:** 72W
 - **Current max:** approx. 3 A
 - **Turns:** 160 turns (exact)
 - **Center turn:** 80 turns (exact)
 - **Wire thickness:** 0.8 mm

- **Other details**
 - **Primary coil weight:** approx. 97.19 grams
 - **Secondary coil weight:** approx. 93.50 grams

END OF DATASHEET