

Allwinner Technology CO., Ltd.

秘密▲5年

Allwinner Technology

R818_MR813 eMMC Support List
V1.00

Allwinner Technology CO., Ltd.

秘密▲5年

• Note Introduction

Note	Description
D/S	Datasheet Support but no sample test
S/T	Support and sample test
√	Support and mass produce
X	Not support

Allwinner Technology CO., Ltd.

秘密▲5年

• Allwinner R818_MR813 eMMC Flash Support List v1.00

黄色代表此次支持列表更新

Vendor	Capacity (B)	Part Number	eMMC /SD	Cell&Process	Pkg Size (mm)	R818	MR813	Remark
						linux 4.9	linux 4.9	
						V1.01	V1.01	
Samsung	16G	KLMAG2GEND-B031	v5.0	MLC/16nm	11.5*13-BGA153	S/T	S/T	
	32G	KLMBG4GEND-B031	v5.0	MLC/16nm	11.5*13-BGA153	S/T	S/T	
	8G	KLM8G1WEPD-B031	v5.0	TLC/16nm	11.5*13-BGA153	S/T	S/T	
	16G	KLMAG2WEPD-B031	v5.0	TLC/16nm	11.5*13-BGA153	S/T	S/T	
	32G	KLMBG4WEBD-B031	v5.0	TLC/16nm	11.5*13-BGA153	S/T	S/T	
	64G	KLMCG8GEND-B031	v5.0	MLC/16nm	11.5*13-BGA153	S/T	S/T	
	8G	KLM8G1GEND-B031	v5.0	MLC/16nm	11.5*13-BGA153	S/T	S/T	
	64G	KLMCG8WEBD-B031	v5.0	TLC/16nm	11.5*13-BGA153	S/T	S/T	
	4G	KLM4G1FEPD-B031	v5.0	MLC/16nm	11*10-BGA153	S/T	S/T	
	8G	KLM8G1GEME-B041	v5.1	MLC/14nm	11.5*13-BGA153	S/T	S/T	
	8G	KLM8G1GETF-B041	v5.1	MLC/14nm	11.5*13-BGA153	S/T	S/T	
	16G	KLMAG1JENB-B041	v5.1	MLC/14nm	11.5*13-BGA153	S/T	S/T	
	16G	KLMAG1JETA-B041	v5.1	MLC/14nm	11.5*13-BGA153	S/T	S/T	
	32G	KLMBG2JENB-B041	v5.1	MLC/14nm	11.5*13-BGA153	S/T	S/T	
	32G	KLMBG2JETA-B041	v5.1	MLC/14nm	11.5*13-BGA153	S/T	S/T	
	64G	KLMCG4JENB-B041	v5.1	MLC/14nm	11.5*13-BGA153	S/T	S/T	
	64G	KLMCG4JETA-B041	v5.1	MLC/14nm	11.5*13-BGA153	S/T	S/T	
	8G	KLM8G1GESD-B04P (车规)	v5.1	MLC/16nm	11.5*13-BGA153	S/T	S/T	
	16G	KLMAG2GESD-B04P (车规)	v5.1	MLC/16nm	11.5*13-BGA153	S/T	S/T	
Sandisk	8G	SDIN7DU2-8G	v4.41		11.5*13-BGA153	S/T	S/T	EOL
	64G	SDIN9DW4-64G	v5.1	MLC/20nm	11.5*13-BGA153	S/T	S/T	EOL
	32G	SDINADF4-32G-H	v5.1	TLC/15nm	11.5*13-BGA153	S/T	S/T	IO电压不支持3.3V
	8G	SDIN8DE1-8G-I	v4.51	MLC/1xnm	11.5*13-BGA153	S/T	S/T	EOL
	8G	SDIN8DE2-8G-A	v4.51	MLC/1xnm	11.5*13-BGA153	S/T	S/T	EOL
	8G	SDINBDG4-8G	v5.1	MLC/1znm	11.5*13-BGA153	S/T	S/T	
	16G	SDINBDG4-16G	v5.1	MLC/1znm	11.5*13-BGA153	S/T	S/T	
	64G	SDINBDG4-64G	v5.1	MLC/1znm	11.5*13-BGA153	S/T	S/T	
	32G	SDINBDA4-32G	v5.1	3D TLC	11.5*13-BGA153	S/T	S/T	
	64G	SDINBDA4-64G	v5.1	3D TLC	11.5*13-BGA153	S/T	S/T	
Micron	16G	SDINBDA2-16G	v5.1	3D TLC	11.5*13-BGA153	S/T	S/T	-25 ~+85
	8G	5QA27-JY995 (MTFC8GAKAJCN-1WMT)	v5.0	MLC	11.5*13-BGA153	S/T	S/T	
	4G	6FA27-JY976 (MTFC4GAKAJCN-1WMT)	v5.0	MLC	11.5*13-BGA153	S/T	S/T	
	16G	6FA28-JWB74 (MTFC16GAKAECN-2WMT)	v5.0	MLC	11.5*13-BGA153	S/T	S/T	

Allwinner Technology CO., Ltd.

秘密▲5年

	32G	5SA28-JWB79 (MTFC32GAKAECN-3MWT)	v5.0	MLC	11.5*13-BGA153	S/T	S/T	
Toshiba	4G	THGBMBG5D1KBAIL	v5.0	MLC/A19nm	11.5*13-BGA153	S/T	S/T	
	32G	THGBMFG8C2LBAIL	v5.0	MLC/15nm	11.5*13-BGA153	S/T	S/T	
	8G	THGBMFG6C1LBAIL	v5.0	MLC/15nm	11.5*13-BGA153	S/T	S/T	
	4G	THGBMDG5D1LBAIL	v5.1	MLC/15nm	11.5*13-BGA153	S/T	S/T	
	8G	THGBMJG6C1LBAU7	V5.1		11.5*13-BGA153	S/T	S/T	
	4G	THGBMNG5D1LBAIL	V5.0	MLC/15nm	11.5*13-BGA153	S/T	S/T	
	8G	THGBMHG6C1LBAIL	v5.1	MLC/15nm	11.5*13-BGA153	S/T	S/T	
	16G	THGBMHG7C1LBAIL	v5.1	MLC/15nm	11.5*13-BGA153	S/T	S/T	
	32G	THGBMHG8C2LBAIL	v5.1	MLC/15nm	11.5*13-BGA153	S/T	S/T	
	64G	THGBMHG9C4LBAIL	v5.1	MLC/15nm	11.5*13-BGA153	S/T	S/T	
	8G	THGBM6G6T1JBAIR	v4.41		11.5*13-BGA153	S/T	S/T	
	16G	THGBMHG7C2LBAAR (车规)	v5.1	MLC/15nm	11.5*13-BGA153	S/T	S/T	
KIOXIA	32G	THGAMRG8T13BAIL	v5.1			S/T	S/T	
	64G	THGAMRG9T23BAIL				S/T	S/T	
	128G	THGAMRT0T43BAIR				S/T	S/T	
SKhynix	16G	H26M51002HPR	v5.1	3D V2 MLC	11.5*13-BGA153	S/T	S/T	
	32G	H26M62002GMR	v5.1	3D V2 MLC	11.5*13-BGA153	S/T	S/T	
	16G	H26M52208FPRI (车规)	v5.1	MLC/1ynm	11.5*13-BGA153	S/T	S/T	
	8G	H26M41208HPRI	v5.1	1ynm/MLC	11.5*13-BGA153	S/T	S/T	
Kingston	8G	EMMC08G-M325	v5.1	MLC/15nm	11.5*13-BGA153	S/T	S/T	
	16G	EMMC16G-M525	v5.1	MLC/15nm	11.5*13-BGA153	S/T	S/T	
	8G	EMMC08G-M728	v5.0	3D MLC	11.5*13-BGA153	S/T	S/T	
	16G	EMMC16G-W525	v5.0	MLC/T15nm	11.5*13-BGA153	S/T	S/T	Industrial
	32G	EMMC32G-W525	v5.0	MLC/T15nm	11.5*13-BGA153	S/T	S/T	Industrial
	64G	EMMC64G-W525	v5.0	MLC/T15nm	11.5*13-BGA153	S/T	S/T	Industrial
	16G	EMMC16G-TB28 (车规)	v5.1	3D TLC	11.5*13-BGA153	S/T	S/T	
FORESEE	16G	NCEMAD6B-16G	v5.1	TLC/15nm	11.5*13-BGA153	S/T	S/T	
	8G	NCEMAD7B-08G	v5.0	TLC/15nm	11.5*13-BGA153	S/T	S/T	
	16G	NCEMAD99-16G	v5.0		11.5*13-BGA153	S/T	S/T	
	32G	NCEMASLD-32G	v5.1		11.5*13.5-BGA153	S/T	S/T	-25~+85
	16G	FEMDNN016G-58A43	v5.1		11.5*13.5*1.0	S/T	S/T	
	8G	FEMDNN008G-08A39	v5.1		11.5*13.5*1.0	S/T	S/T	-25~+85
	4G	FEMDNN004G-58A42	v5.1		11.5*13.5*0.8	S/T	S/T	-25~+85
JSC	32G	JSMC32BUA2HYAEA	v5.0	H3D V2 MLC	11.5*13-BGA153	S/T	S/T	
	16G	JSMC16AU2HYAEA	v5.0	H3D V2 MLC	11.5*13-BGA153	S/T	S/T	
ESSENCORE	8G	I3E-8GTH7CMRE	v5.0	MLC/T16nm	11.5*13-BGA153	S/T	S/T	
	16G	ENEAGQ8BE1MR-HB	v5.1			S/T	S/T	-20~+60
Biwin	8G	BWCE28NH-08G	V5.0		11.5*13*0.9	S/T	S/T	

Allwinner Technology CO., Ltd.

秘密▲5年

Artemem	16G	AT70B16G3S02C	v5.1	2D MLC/K9GDD8U0B	11.5*13-BGA153	S/T	S/T	
	32G	AT70B32G3S01C	v5.1	3D TLC/K9AFGD8H0A	11.5*13-BGA153	S/T	S/T	
	8G	AT70B08G3S03F	v5.1	MLC	11.5*13-BGA153	S/T	S/T	
	32G	AT70B32G4Y01F	v5.1		11.5*13-BGA153	S/T	S/T	
	64G	AT70B64G4Y01F	v5.1		11.5*13-BGA153	S/T	S/T	
ISOCOM	32G	MEMA032G-M0S00	v5.1		11.5*13-BGA153	S/T -20°~60°	S/T -20°~60°	
SCY	4GB	E04GDML31ABE00	v5.1			S/T -25°~75°	S/T -25°~75°	
SkyHigh	4G	S40FC004C1B1C	v5.1	MLC	11.5*13-BGA153	S/T	S/T	-40 ~ +85
YMTC	32G	YMEC6A2TB1A2C3	v5.1	TLC	11.5*13-BGA153	S/T	S/T	-25 ~ +85
	64G	YMEC7A2TB2A2C3	v5.1	MLC	11.5*13-BGA153	S/T	S/T	-25 ~ +85
Konka Kowin	4G	KAS03111	v5.1		11.5*13-BGA153	S/T	S/T	-25 ~ +85
SiliconGo	32G	SGM8100C-Y02BBG	v5.1			D/S	D/S	-40 ~ +85
		SGM8000C-S21BAG	v5.1			D/S	D/S	-40 ~ +85

注1: 支持该eMMC需要将各环节MMC驱动更新到最新, 并修改sys_config.fex让该eMMC工作在SDR模式下。

Allwinner Technology CO., Ltd.

秘密▲5年

• Declaration

This document is the original work and copyrighted property of Allwinner Technology (“Allwinner”). Reproduction in whole or in part must obtain the written approval of Allwinner and give clear acknowledgement to the copyright owner.

The information furnished by Allwinner is believed to be accurate and reliable. Allwinner reserves the right to make changes in circuit design and/or specifications at any time without notice. Allwinner does not assume any responsibility and liability for its use. Nor for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Allwinner. This datasheet neither states nor implies warranty of any kind, including fitness for any particular application.