

8085 assembly language program to add two 8-bit numbers stored at memory locations 2051H and 2052H. Store sum at 2055H & carry at 2056H.

Memory Address	Mnemonics	Opcode
2000H	LDA 2051H	3A 51 20
2003H	MOV B, A	47
2004H	LDA 2052H	3A 52 20
2007H	ADD B	80
2008H	STA 2055H	32 55 20
200BH	MVI A, 00H	3E 00
200DH	ADC A	8F
200EH	STA 2056H	32 56 20
2011H	HLT	76

— X — X — X — X — X — X — X — X — X — X — X —

8085 assembly language program to subtract 8-bit number stored at 2052H from 2051H. Store the result at memory location 2055H & borrow at 2056H.

→

Memory Address	Mnemonics	Opcode
2000H	LDA 2051H	3A 51 20
2003H	MOV B, A	47
2004H	LDA 2052H	3A 52 20
2007H	MOV C, A	4F
2008H	MOV A, B	78
2009H	SUB C	91
200AH	STA 2055H	32 55 20
200DH	MVI A, 00H	3E 00
200FH	ADC A	8F
2010H	STA 2056H	32 56 20
2013H	HLT	76