

Butcher x NDI workflow setup guide

NDi Transmitter setup:

1. Open a touch designer project and press tab to add a MovieFileInTOP and an NDIoutTOP
2. Connect the Movie FileInTOP output to the NDIoutTOP input
3. Open the NDIoutTOP parameters and type in a source name.
4. Ensure that the TOP is set to active

NDI Receiver Setup (Meatop):

1. On Meat top, install and extract the NDI SDK, you may need to move it to the library if it installs on the desktop.
When you first launch the SDK, you will be presented with a user agreement in the terminal, press Y then enter to accept
2. To ensure each python library is installed and ready to use, install the following:
pip install numpy
pip install opencv-python
pip install ndi-python
3. To ensure the receiving laptop is seeing all incoming NDI data streams, make sure these ports are open by running the following:
sudo ufw allow 5353/udp
sudo ufw allow 5960:5970/tcp
sudo ufw allow 5960:5970/udp
4. Install avahi to amenable device discovery
sudo apt update sudo apt install avahi-daemon avahi-utils libnss-mdns
5. CD to file location then run the following
Python3 -u NDI2.py
Press escape to exit