

TT

TT36 & TT48

Easteley TT Series
Rotary Accumulation Tables

User Guide



EASTELEY®

TT

TT36 & TT48

Eastey TT Series Rotary Accumulation Tables

User Guide

Revised 05/15/2018

P/N TT001000 Rev A

Copyright and Trademarks

Copyright ©2018 Eastey Enterprises

All rights reserved. All trademarks and brand names
are the property of their respective owners.

Eastey Enterprises, Inc.
7041 Boone Ave. N.
Brooklyn Park, MN 55428

Phone: (763) 428-4846; Fax (763) 795-8867; 1-800-835-9344
www.eastey.com

Contents:

Safety	7
Explanation of Symbols	8
Introduction	9
General System Description	9
Specifications	9
Dimensions	11
Installation	12
Optional Casters	12
Height Adjustment	12
Location Requirements	13
Operation	14
Power	14
Control Box	15
Adjustments	17
Machine Base Height and Leveling Adjustment	17
Sidewall Height Adjustment	17
Turntable Leveling Adjustment	18
Advanced Speed and Control Function Adjustment	19
Maintenance	23
Preventative Maintenance	23
Cleaning the Table Top Surface and Sidewall	23
Troubleshooting	24
Parts List	27
Accumulation Table — TT36 & TT48	27
Appendix A: Electrical Schematic	29
Warranty Statement	31
Customer Support	33

Safety

General Safety Precautions

Before installing, operating or servicing this equipment, please read the following precautions carefully:

- This machine is equipped with a rotating turntable disk for product accumulation. The rotating motion of the disk, and drive chain and sprockets under it create several potential pinch points. Do not place hands under or near the edges of the turntable disk or optional divider paddle when the accumulation table is operating as fingers may be pinched, sheared, or otherwise injured or possibly severed in these areas.
- Do not attempt to open or work on the electrical box, junction boxes or other electrical components of the unit without first disconnecting power to the machine. Electrical shock hazard exists if power is not disconnected.
- Do not by-pass any factory-designed safety features such as guards, interlocks, switches, etc.
- Do not place hands or body inside the confines of the machine unless all mechanisms are securely fastened and the electrical supply is shut off.
- Never provide service or clear a jam when machine is running.
- Do not wear loose clothing such as ties, scarves, jewelry etc. Long hair should be pulled back and/or covered while operating this machine.
- Do not stand or climb on any part of the accumulation table or its frame.

Explanation of Symbols



Caution sign or Safety Alert symbol. Indicates caution, be alert, Your safety is involved. Knowledge of safe operation is required.




Ground symbol. Indicates ground. Use Class-3 (lower than 1000) cable to ground to earth. Incomplete grounding may lead to electrical shock.



Electrical hazard. Indicates electrical danger. Only a trained electrician can uncover the electrical panel or box.



Electrical shock hazard. Indicates electrical shock danger from exposed or broken wires or electrical components. Only a trained technician can uncover the electrical panel box.



Cut or shear hazard. Do not place your hands or any object into the area under the rotating turntable near the vertical sidewall support brackets. Shut down the machine before performing maintenance.



Pinch or crush hazard. Do not place your hands or any object under the rotating turntable near tabletop support wheels. Shut down the machine before performing maintenance.



Moisture hazard. Keep equipment dry. This equipment is designed for indoor operation in a typical clean, dry factory environment, protected from rain and moisture. Do not operate the machine in any extremely wet or oily environment that may exceed operating specifications.