

```

//Last 3 digits of my ID- 131

void setup() {

  DDRD=0b11111100;//initializing (2-7) pins as output

  DDRB=0b00011111;//initializing (8-12) pins as output

}

void loop() {

  PORTB=0b00000101;PORTD=0b00001100;delay(2000);

  //to show "1" in the 1st SSD & turn off other 2

  PORTB=0b00001101;PORTD=0b10110100;delay(2000);

  //to show "3" in the 2nd SSD & turn off other 2

  PORTB=0b00000101;PORTD=0b00011000;delay(2000);

  //to show "1" in the 3rd SSD & turn off other 2

  //delay 2000ms is to show digits at 2s intervals

}

```