

4G LTE - SIM CARD




Q2000

2GB RAM | 16/32GB FLASH


4GB RAM | 16/32GB FLASH



Amlogic S905X3
Quad-Core ARM
Cortex-A55 up to 2.0GHz



ARM Mali-G31
GPU processor



100/1000M
Ethernet port



Power on :Blue; Standby:Red



HDR 10+, Dolby Vision



Android/9.0/ATV



WIFI 11ac+Bluetooth 4.1 IEEE802.11
a/b/g/n/ac(AP6255) 4G/5G



5.1 Bluetooth



Internal 4G LTE Module
(optional)

MAIN FEATURES

Video Decoder

- VP9/H.265/AVS2 up to 4Kx2K@60fps,H.264 4K @30fps, AVS+/VC-1/MPEG1-4 1080P @60fps

Video Encoder

- H.264/H.265 1080P @60fps

KODI

- KODI newest version Support local high-definition play, support plug-in installation and play

Decoder Format

- HD MPEG1/2/4,H.265/HEVC,AVS2 , HD AVC/VC-1, RM/RMVB, Xvid/DivX3/4/5/6 , RealVideo8/9/10

Media Format

- Avi/Rm/Rmvb/Ts/Vob/Mkv/Mov/ISO/wmv/asf/flv/dat/mpg/mpeg

Music Format

- MP3/WMA/AAC/WAV/OGG/DDP/TrueHD/HD/FLAC/APE

Photo Format

- HD JPEG/BMP/GIF/PNG/TIFF

DRM

- Widevine (Verimatrix/ Playready optional)

Network Function

- Miracast,DLNA,Skype,Netflix,Twitter,Picasa,Youtube,Flicker,Facebook,Online movies,Games,etc.

Language

- English ,German, Russian, French, Spanish, Italian, Arabic, Japanese, Korean, Hebrew, etc.
multi languages

Input/Output

- 1* High speed USB 2.0 ,1* USB3.0 , support USB Flash Drive and USB HDD

- 1* AV output

- 1*TF card slot

- 1* RJ45 wire Ethernet connection

- 1 *HDMI 2.1 With 3D,HDR,CEC and 4Kx2K@60fps max resolution

- 1* Optical Support Optical Output

- 1*LED Display time

- Built in RTC, Built in USB device

- 1*Power DC Adapter - Input: AC100-240V 50/60Hz, Output: DC 5V 2A

- 1*IR Port - Internal Infrared Receiver

- 1*LED Indicator - Power on :Blue; Standby: Red

Hardware Specifications

Internal 4G LTE Module(optional)

- LTE-FDD/LTE-TDD/WCDMA/TD-SCDMA/EDGE/GPRS/GSM, downstream 150Mbps, upstream 50Mbps

MHZ-E (EUROPE)

- B1/B3/B5/B7/B8/B20@FDD LTE, B1/B5/B8@WCDMA, 850/900/1800/1900@GSM

MHZ-A (AMERICA)

- B2/B4/B8/B17@FDD LTE, B38/B39/B40/B41@TDD LTE, B1/B8@WCDMA, B34/39@TD-SCDMA, 900/1800@GSM

MHZ-CE (CHINA/INDIA/Saudi Arabia)

- B1/B3/B5/B8@FDD LTE, B38/B39/B40/B41@TDD LTE, B1/B8@WCDMA, B34/B39@TD-SCDMA BC0@CDMA20001X/EXDO, 900/1800@GSM

MHZ-E (EMEA/KOREA/THAILAND/INDIA)

- B1/B3/B5/B7/B8/B20@FDD LTE; B38/B40/B41@TDD LTE; B1/B5/B8@WCDMA; B3/B8@GSM

MHZ-V (NORTH AMERICA)

- B4/B13@FDD LTE

MHZ-A (NORTH AMERICA)

- B2/B4/B12@FDD LTE; B2/B4/B5@WCDMA

MHZ-AU (Latin America/ANZ/TAIWAN)

- B1/B2/B3/B4/B5/B6/B7/B8/B28@FDD LTE; B40@TDD LTE;
B1/B2/B5/B8@WCDMA; B2/B3/B5/B8@GSM

MHZ-J (JAPAN)

- B1/B3/B8/B18/B19/B26@FDD LTE; B41@TDD LTE; B1/B6/B8/B19@WCDMA

Others

- Support mouse and keyboard via USB or BT; Support 2.4GHz wireless mouse and keyboard via 2.4GHz USB dongle