

INSITE

Inspection Report

Field Safety Inspection Record

Riverside Bridge Deck Project

Full Inspection

Inspection date: August 18, 2026

Inspector: Riley Okafor

Findings documented: 2

Report generated: August 18, 2026

Executive Summary

METRIC	VALUE
Total findings	2
Critical / High risk findings	2
Open corrective actions	4
Inspection status	Completed

Risk Distribution

Critical	0
High	2
Moderate	0
Low	0

Summary

This inspection identified findings requiring prioritized corrective action. Critical and High findings should be assigned an owner and closure date without delay.

Inspection Information

FIELD	DETAIL
Site / facility	Riverside Bridge Deck Project
Inspection	Full Inspection
Inspection date	August 18, 2026
Inspector	Riley Okafor
Status	Completed
Regulatory context	OSHA - Construction (29 CFR 1926), set for this inspection

Findings Summary

Concise reference of every finding documented in this inspection.

#	HAZARD	RISK	STATUS	ACTION STATUS
1	Electrical	High	Finalized	Open
2	Fall Protection	High	Finalized	Open

Detailed Findings

Finding 1 — Electrical

WHAT WAS OBSERVED

cord

FULL SOURCE OBSERVATION (SHARED ACROSS THIS INSPECTION'S FINDINGS)

A roofer is working within four feet of an unprotected roof edge about 18 feet above grade with no guardrail or personal fall arrest system in use. Manual finding: the extension cord powering the circular saw at the deck edge has exposed copper conductors and remains energized while crew members are working around it.

RISK

HIGH

APPLICABLE STANDARD

Not established for this specific finding.

QUALIFIED-PERSON REVIEW

Accepted — Reviewed against the observed facts; accepted as an advisory conclusion.

RECOMMENDED CORRECTIVE ACTION

Electrical corrective action

Immediate: Isolate the affected extension cord from service and route damaged electrical-integrity concerns for qualified review before reuse.

Permanent: Replace damaged wiring assemblies with rated replacement components appropriate for the affected equipment and environment to ensure continuous, safe electrical-integrity barriers.

Verification: Perform a formal inspection and functional verification by a competent person before removing interim controls or resuming normal operations.

Status: Open · Priority: Medium

Verify and correct reviewed condition 1

Immediate: Place the affected electrical equipment in a safe state and restrict access pending qualified electrical verification.

Permanent: Repair or replace the electrical component with appropriately rated equipment and verify the installation.

Verification: Have a qualified person document the electrical inspection before returning the equipment to service.

Status: Open · Priority: Urgent

Finding 2 — Fall Protection

WHAT WAS OBSERVED

edge

FULL SOURCE OBSERVATION (SHARED ACROSS THIS INSPECTION'S FINDINGS)

A roofer is working within four feet of an unprotected roof edge about 18 feet above grade with no guardrail or personal fall arrest system in use. Manual finding: the extension cord powering the circular saw at the deck edge has exposed copper conductors and remains energized while crew members are working around it.

RISK

HIGH

APPLICABLE STANDARD

Not established for this specific finding.

QUALIFIED-PERSON REVIEW

Accepted — Reviewed against the observed facts; accepted as an advisory conclusion.

RECOMMENDED CORRECTIVE ACTION

Fall Protection corrective action

Immediate: Isolate the affected extension cord from service and route damaged electrical-integrity concerns for qualified review before reuse.

Permanent: Replace damaged wiring assemblies with rated replacement components appropriate for the affected

equipment and environment to ensure continuous, safe electrical-integrity barriers.

Verification: Perform a formal inspection and functional verification by a competent person before removing interim controls or resuming normal operations.

Status: Open · Priority: Medium

Verify and correct reviewed condition 2

Immediate: Restrict access to the elevated exposure and stop the task until compliant fall protection is verified.

Permanent: Provide and maintain a compliant guardrail, personal fall-arrest system, or other approved fall control for the work area.

Verification: Verify the fall-control system and access route before resuming work.

Status: Open · Priority: Urgent

Corrective Action Summary

Consolidated view of all corrective actions from this inspection for management follow-up.

FINDING	ACTION	OWNER	DUE	STATUS
#2	Fall Protection corrective action	Unassigned	—	Open
#1	Electrical corrective action	Unassigned	—	Open
#1	Place the affected electrical equipment in a safe state and restrict access pending qualified electrical verification.	Unassigned	—	Open
#2	Restrict access to the elevated exposure and stop the task until compliant fall protection is verified.	Unassigned	—	Open

HazLenz AI output is advisory and requires qualified human review. This report reflects findings as reviewed at the time of generation.