

Line-Goto/From Tool

September 2016



McMaster Centre for Software Certification (McSCert)

1 Introduction

The Line-Goto/From tool is used to convert signal lines to **Goto/From** blocks, as well as **Goto/From** blocks to signal lines.

The tool aims to assist software development activities by automating frequently performed actions by developers when creating, modifying, or maintaining models. The use of **Goto/From** blocks or signal lines helps to increase readability where appropriate. In models with many signal line crossings, converting some signal lines to **Goto/From** blocks will help in decluttering the model. Conversely, using signal lines for straightforward connections, instead of **Goto/From** blocks, will allow developers to more easily follow the visual data flow.

2 How to Use the Tool

2.1 Prerequisites

Please ensure the following, before using the tool:

- Use MATLAB/Simulink 2011b or newer.
- The tool is present in your MATLAB path. If it is not, go to **File > Set Path...**, press **Add with Subfolders**, and select the **McMaster_Tools** folder. Restart MATLAB after doing so.
- The model is open (or loaded, for command line use).

2.2 Getting Started

The tool can be used via the Simulink Context Menu, which can be viewed by right-clicking in a model. The following options can be available, depending on what is selected in the model (as shown in Figure 1).

- *Goto/Froms to Line* – Available when one or more **Goto/From** blocks are selected.
- *Line to Goto/Froms* – Available when one or more signal lines are selected.

2.3 Functionality

Goto/Froms to Line

Selecting one or more **Goto/From** blocks and then selecting **Goto/Froms to Line** from the Context Menu will convert the selected blocks to signal line connections. Multiple blocks can be selected by either dragging the cursor over several blocks, or by pressing shift and then selecting blocks.

Goto/From blocks with global or scoped visibilities, i.e. those with corresponding blocks outside of the current subsystem, will not be converted.




Figure 1: How the tool will appear in the Simulink Context Menu

Line to Goto/Froms

Selecting one or more signal lines and then selecting **Line to Goto/Froms** from the Context Menu will convert the selected signal lines to **Goto/From** connections. If a signal line has a name which is a valid variable name, it will automatically be used as the **Goto/From** tag. If the line has no name or it is an invalid variable name, the user will be prompted to provide one through a GUI, shown in Figure 2.

If the tag for the **Goto/From** is not a valid variable name, the user will be prompted to provide another name. If the tag corresponds to existing **Goto/From** blocks which are within scope, that is, they will conflict, the user will be prompted to provide another name.

Multiple signal lines can be selected by either dragging the cursor over several signal lines, or by pressing shift and then selecting signal lines.

Note: For MATLAB 2011b Simulink, it is not possible to directly right-click on multiple signal lines. To overcome this, you must also select one of the source blocks of a selected signal line, and perform the right-click on this block.

2.4 Configuration Parameters

The configuration file `config.txt` is included in `McMaster.Tools\LineToGotoFrom\src`. The following configuration parameters are utilized by the tool, and can be mod-



Figure 2: Tool dialog window prompting for the Goto/From name

ified by the user in order to tailor tool functionality:

- **resize_block** – Enables or disables the the resizing of **Goto/From** block length to a specific size.
- **static_resize** – Enables or disables the ability to resize **Goto/From** block length to a fixed value. Otherwise, **Goto/From** blocks will be resized dynamically. This parameter is used only when **resize_block** is enabled.
- **static_length** – The number of pixels that **Goto/From** blocks are resized to lengthwise, when **static_resize** is enabled.
- **px_per_letter** – The number of pixels to allocate per letter of a **Goto/From** tag, that the block will be resized to. This parameter is used when **static_length** is disabled (i.e., dynamic resizing is enabled).
- **block_offset** – The distance in pixels between **Goto/From** blocks and the blocks that they are connected to.
- **line_routing** – Enables or disables *autorouting* when adding new lines.

Please see the configuration file for more details regarding parameter usage and values. These parameters can be modified with MATLAB open, and do not require that MATLAB be restarted for the changes to become effective.

2.5 Errors and Warnings

Any errors or warnings during tool use will be visible in the MATLAB Command Window.

3 Example

Use the command `Line2GotoFromDemo` in the Simulink command window to open the example model, shown in Figure 3. There are **Goto/From** blocks in this example with tag **A**. To transform them into a signal line connection, right-click on the **Goto** block, one of the **From** blocks, or by selecting all these blocks. Then




Figure 3: Line-Goto/From demo model.

choose the **Goto/Froms to Line** option from the Context Menu. The resulting model is given in Figure 4. Likewise, to transform the line named **signalB** to a Goto/From block connection, right-click on the signal line and select the **Line to Goto/Froms** option. The resulting model is given in Figure 5.

4 Matlab Commands

The tool can also be used via the MATLAB command line, with the following functions.

| | |
|-----------------|--|
| Function | <code>goto2Line</code> |
| Syntax | <code>goto2Line(address, blocks)</code> |
| Description | Converts selected local Goto/From block connections into signal lines. |
| Input Arguments | <i>address</i> : Path of where the Goto/From blocks reside in the model. <i>blocks</i> : Cell array of Goto/From block path names to convert. |

Example: The following command transforms the Goto/From blocks with tag A, named **From0**, into a signal line connection in model **Line2GotoFromDemo**. The resulting model is shown as Figure 4.

```
goto2Line('Line2GotoFromDemo', {'test2/From0'})
```




Figure 4: Resulting model after Goto/Froms to Line transformation on A Goto/From blocks.




Figure 5: Resulting model after Line to Goto/Froms transformation on signalB.

| | |
|-----------------|--|
| Function | <code>line2Goto</code> |
| Syntax | <code>line2Goto(address, line, tag)</code> |
| Description | Converts a signal line into a Goto/From connection. |
| Input Arguments | <p><i>address</i>: Path of where the signal line resides in the model.</p> <p><i>line</i>: Handle of the signal line to convert.</p> <p><i>tag</i>: String to be used as the Goto/From tag.</p> |

Example: The following command transforms the signal line named `signalB`, with line handle given as variable `lh`, into a **Goto/From** block connection in model `Line2GotoFromDemo`. The resulting model is shown as Figure 5.

```
line2Goto('Line2GotoFromDemo', lh, 'signalB')
```

Note: Included with this tool are two functions, *gcl* and *gcls*, which get the current line handle(s) for one or more lines, respectively. They are provided to assist with the command line operation of this tool.